bookboon.com

Software Solutions to Problems on Heat Transfer

Radiation Heat Transfer – Part II

Dr. M. Thirumaleshwar

Download free books at
bookboon.com

Dr. M. Thirumaleshwar

Software Solutions to Problems on Heat Transfer
RADIATION HEAT TRANSFER – PART-II

(Electrical network method & Radiation energy exchange in 2-zone and 3-zone enclosures, Radiation shielding, Radiation error in temperature measurement)

Download free eBooks at bookboon.com

Software Solutions to Problems on Heat Transfer: Radiation Heat Transfer – Part II
(Electrical network method & Radiation energy exchange in 2-zone and 3-zone enclosures, Radiation shielding, Radiation error in temperature measurement)
1st edition
© 2014 Dr. M. Thirumaleshwar & bookboon.com
ISBN 978-87-403-0627-9

Download free eBooks at bookboon.com

Contents

To see the Part I download:
Software Solutions to problems on heat transfer – Radiation Heat Transfer I

	Preface to vol. 5	**Part I**
	About the Author	**Part I**
	About the Software used	**Part I**
	To the Student	**Part I**
5	**Radiation heat transfer**	**Part I**
5A	**Laws of Radiation and Radiation properties:**	**Part I**
5B	**View factors (or, Shape factor, configuration factor) and Radiation energy exchange between Black bodies:**	**Part I**



Download free eBooks at bookboon.com

Click on the ad to read more

5C	**Electrical network method & Radiation energy exchange between gray surfaces:**	**6**
5D	**Radiation shields**	**191**
5E	**'Radiation error' in temperature measurement**	**273**
	References	**302**

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

5C Electrical network method & Radiation energy exchange between gray surfaces:

5.C.1 Radiation energy exchange in 2-surface enclosures:

Prob. 5.C.1.1. Write Mathcad Functions for a general two-surface enclosures, and also for few special cases of two-surface enclosures:

Radiation heat exchange for a general two surface enclosure:

Following is the schematic diagram and the radiation network (Ref: Cengel):



Note: In the following Function, A1, A2 are areas of inner and outer surfaces(m), ε1,ε2 are emissivities of the surfaces;

T1, T2 are temps. in Kelvin, F12 is the view factor from surface 1 to 2.

$$Q12\_two\_surface\_enclosure(A1, A2, F12, \varepsilon 1, \varepsilon 2, T1, T2) := \frac{5.67 \cdot 10^{-8} \cdot \left(T1^4 - T2^4\right)}{\left(\frac{1 - \varepsilon 1}{A1 \cdot \varepsilon 1}\right) + \frac{1}{A1 \cdot F12} + \left(\frac{1 - \varepsilon 2}{A2 \cdot \varepsilon 2}\right)}$$

Example: $A1 := 6.283 \quad A2 := 3.142 \quad \varepsilon 1 := 0.8 \quad \varepsilon 2 := 0.5 \quad F12 := 0.5 \quad T1 := 800 \quad T2 := 600$

$$Q12\_two\_surface\_enclosure(A1, A2, F12, \varepsilon 1, \varepsilon 2, T1, T2) = 2.347 \times 10^4 \quad W$$

Download free eBooks at bookboon.com

Radiation heat exchange between two black surfaces:



In the Function given below:

We have: A1 (m2), F12 is view factor from surface 1 to surface 2, T1, T2 are temps. in Kelvin

$$Q12\_black\_surfaces(A1,F12,T1,T2) := 5.67\cdot10^{-8}\cdot A1\cdot F12\cdot\left(T1^4 - T2^4\right) \quad W$$

Example: $A1 := 0.785 \quad F12 := 0.232 \quad T1 := 1000 \quad T2 := 600$

$$Q12\_black\_surfaces(A1,F12,T1,T2) = 8.988\times10^3 \quad W$$

Few special cases of two-surface enclosures: (Ref: Cengel)

Small object in a large cavity



$\frac{A_1}{A_2} \approx 0$

$F_{12} = 1$

$\dot{Q}_{12} = A_1\sigma\varepsilon_1(T_1^4 - T_2^4)$ (22-37)

Infinitely large parallel plates



$A_1 = A_2 = A$

$F_{12} = 1$

$\dot{Q}_{12} = \frac{A\sigma(T_1^4 - T_2^4)}{\frac{1}{\varepsilon_1} + \frac{1}{\varepsilon_2} - 1}$ (22-38)

Download free eBooks at bookboon.com

Infinitely long concentric cylinders



$$\frac{A_1}{A_2} = \frac{r_1}{r_2}$$

$$F_{12} = 1$$

$$\dot{Q}_{12} = \frac{A_1\sigma(T_1^4 - T_2^4)}{\frac{1}{\varepsilon_1} + \frac{1-\varepsilon_2}{\varepsilon_2}\frac{r_1}{r_2}} \qquad (22\text{-}39)$$

Concentric spheres



$$\frac{A_1}{A_2} = \left(\frac{r_1}{r_2}\right)^2$$

$$F_{12} = 1$$

$$\dot{Q}_{12} = \frac{A_1\sigma(T_1^4 - T_2^4)}{\frac{1}{\varepsilon_1} + \frac{1-\varepsilon_2}{\varepsilon_2}\left(\frac{r_1}{r_2}\right)^2} \qquad (22\text{-}40)$$

The Wake
the only emission we want to leave behind
Low-speed Engines Medium-speed Engines Turbochargers Propellers Propulsion Packages PrimeServ
The design of eco-friendly marine power and propulsion solutions is crucial for MAN Diesel & Turbo.
Power competencies are offered with the world's largest engine programme – having outputs spanning
from 450 to 87,220 kW per engine. Get up front!
Find out more at www.mandieselturbo.com
Engineering the Future – since 1758.
MAN Diesel & Turbo
MAN

Download free eBooks at bookboon.com

Click on the ad to read more

Mathcad Functions for the above cases are written below:

1. **Radiation heat exchange for a small object in a large enclosure: (ex: pipe in a large Plant room)**

   Note: In the Function below, A1 (m2), ε1 is emissivity of the small object, T1, T2 are temps. in Kelvin

$$Q12\_small\_object(A1, \varepsilon1, T1, T2) := 5.67 \cdot 10^{-8} \cdot A1 \cdot \varepsilon1 \cdot \left(T1^4 - T2^4\right) \quad W$$

Example: $A1 := 0.157 \quad \varepsilon1 := 0.6 \quad T1 := 93 + 273 \quad T2 := 20 + 273$

$$Q12\_small\_object(A1, \varepsilon1, T1, T2) = 56.478 \quad W$$

---

2. **Radiation heat exchange between infinitely large parallel plates:**

   Note: In the Function below, A (m2), ε1, ε2 are emissivities of the surfaces, T1, T2 are temps. in Kelvin

$$Q12\_parallel\_plates(A, \varepsilon1, \varepsilon2, T1, T2) := \frac{5.67 \cdot 10^{-8} \cdot A \cdot \left(T1^4 - T2^4\right)}{\frac{1}{\varepsilon1} + \frac{1}{\varepsilon2} - 1} \quad W$$

Example: $A := 1 \quad T1 := 800 + 273 \quad T2 := 300 + 273 \quad \varepsilon1 := 0.3 \quad \varepsilon2 := 0.6$

$$Q12\_parallel\_plates(A, \varepsilon1, \varepsilon2, T1, T2) = 1.726 \times 10^4 \quad W/m^2$$

---

3. **Radiation heat exchange between infinitely long concentric cylinders:**

   Note: In the Function below, L (m), r1, r2 are radii of inner and outer cylinders(m), ε1, ε2 are emissivities of the surfaces, T1, T2 are temps. in Kelvin

$$Q12\_long\_cylinders(L, r1, r2, \varepsilon1, \varepsilon2, T1, T2) := \frac{5.67 \cdot 10^{-8} \cdot (2 \cdot \pi \cdot r1 \cdot L) \cdot \left(T1^4 - T2^4\right)}{\frac{1}{\varepsilon1} + \frac{r1}{r2} \cdot \left(\frac{1}{\varepsilon2} - 1\right)}$$

Example: $\varepsilon1 := 1 \quad \varepsilon2 := 0.7 \quad T1 := 950 \quad T2 := 500 \quad r1 := 0.1 \quad r2 := 0.25 \quad L := 1$

$$Q12\_long\_cylinders(L, r1, r2, \varepsilon1, \varepsilon2, T1, T2) = 2.287 \times 10^4 \quad W/m$$

Download free eBooks at bookboon.com

4. **Radiation heat exchange between concentric spheres:**

Note: In the Function below, r1, r2 are radii of inner and outer spheres(m), ε1, ε2 are emissivities of the surfaces, T1, T2 are temps. in Kelvin

$$Q12\_concentric\_spheres(r1, r2, \varepsilon1, \varepsilon2, T1, T2) := \frac{5.67 \cdot 10^{-8} \cdot (4 \cdot \pi \cdot r1^2) \cdot (T1^4 - T2^4)}{\frac{1}{\varepsilon1} + \left(\frac{r1}{r2}\right)^2 \cdot \left(\frac{1}{\varepsilon2} - 1\right)} \quad W$$

Example: $T1 := -183 + 273$

$T2 := 25 + 273 \quad \varepsilon1 := 0.2 \quad \varepsilon2 := 0.25 \quad r1 := 0.15 \quad r2 := 0.2$

$Q12\_concentric\_spheres(r1, r2, \varepsilon1, \varepsilon2, T1, T2) = -18.748$ W... -ve sign indicates that heat flows from outer sphere to inner sphere, i.e. from surface 2 to surface 1.

---

5. **Energy radiated from a gray cavity:**



(a) Gray cavity



(b) Radiation network

$R_1 = (1-\epsilon_1)/(A_1.\epsilon_1)$

$R_{12} = 1/(A_1.F_{12})$

$$Q_{12} = A_1 \cdot \varepsilon_1 \cdot \sigma \cdot T_1^4 \cdot \left[\frac{1 - F_{11}}{1 - (1 - \varepsilon_1) \cdot F_{11}}\right]$$ W....net radiation from gray cavity..(13.62)

Download free eBooks at bookboon.com

Note: In the Function below, A1 is area of cavity surface(m^2), ε1 is emissivity of the surface, T1 is temp. in Kelvin, F11 is the view factor from surface 1 to itself = 1-(A2/A1) where A2 is area of closing surface.

$$Q12\_from\_gray\_cavity(A1, F11, \varepsilon1, T1) := 5.67 \cdot 10^{-8} \cdot A1 \cdot \varepsilon1 \cdot T1^4 \cdot \left[\frac{1 - F11}{1 - (1 - \varepsilon1) \cdot F11} \right] \quad W$$

Example: $F11 := 0.857 \quad A1 := 2.199 \cdot 10^{-3} \quad \varepsilon1 := 0.6 \quad T1 := 350 + 273$

$$Q12\_from\_gray\_cavity(A1, F11, \varepsilon1, T1) = 2.452 \quad W$$

==========

Prob. 5C.1.2. A convex grey body having a surface area of 4 m^2 has ε_1= 0.35 and T_1= 680 K. This is completely enclosed by a grey surface having an area of 36 m^2, ε_2=0.75 and T_2 = 310 K. Find the net rate of heat transfer Q_{12} between the two surfaces. [M.U. May, 1999]

In addition: If ε1 varies from 0.1 to 0.6, plot the variation of Q12, all other quantities remaining the same:

See the light!
The sooner you realize we are right, the sooner your life will get better!
A bit over the top? Yes we know!
We are just that sure that we can make your media activities more effective.

Get "Bookboon's Free Media Advice"
Email kbm@bookboon.com
bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com
Download free eBooks at bookboon.com
Click on the ad to read more

Mathcad Solution:

Data:

$T1 := 680\ K \quad T2 := 310\ K \quad \varepsilon_1 := 0.35 \quad \varepsilon_2 := 0.75$

$\sigma := 5.67 \cdot 10^{-8}\ W.m^2.K^4 \quad A1 := 4\ m^2 \quad A2 := 36\ m^2$

$F_{12} := 1$ ..since all the heat radn. emitted by surface 1 is intercepted by surface 2.

Solution:

Starting from Fundamentals:

$E_{b1} := \sigma \cdot T1^4$ i.e. $E_{b1} = 1.212 \times 10^4$ W/m^2

$E_{b2} := \sigma \cdot T2^4$ i.e. $E_{b2} = 523.636$ W/m^2

$R12 := \frac{1}{A1 \cdot F_{12}}$ i.e. $R12 = 0.25$ 1/m^2

$R1 := \frac{1 - \varepsilon_1}{\varepsilon_1 \cdot A1}$ i.e. $R1 = 0.464$ 1/m^2

$R2 := \frac{1 - \varepsilon_2}{\varepsilon_2 \cdot A2}$ i.e. $R2 = 9.259 \times 10^{-3}$ 1/m^2

$R_{tot} := R1 + R12 + R2$ i.e. $R_{tot} = 0.724$ 1/m^2

Therefore:

$Q_{12} := \frac{E_{b1} - E_{b2}}{R_{tot}}$ i.e. $Q_{12} = 1.603 \times 10^4$ Watts.....Ans.

Download free eBooks at bookboon.com

Using the Mathcad Function for a general 2-surface enclosure:

We have the Function written earlier:

$$Q12\_two\_surface\_enclosure(A1, A2, F12, \varepsilon1, \varepsilon2, T1, T2) := \frac{5.67\cdot10^{-8}\cdot\left(T1^4 - T2^4\right)}{\left(\frac{1-\varepsilon1}{A1\cdot\varepsilon1}\right) + \frac{1}{A1\cdot F12} + \left(\frac{1-\varepsilon2}{A2\cdot\varepsilon2}\right)}$$

Then, we write:

$$Q12 := Q12\_two\_surface\_enclosure(A1, A2, F_{12}, \varepsilon_1, \varepsilon_2, T1, T2)$$

i.e. $Q12 = 1.603 \times 10^4$ W.....Ans.. same as obtained above.

==========

If ε1 varies from 0.1 to 0.6, plot the variation of Q12, all other quantities remaining the same:

Let: $Q12(\varepsilon_1) := Q12\_two\_surface\_enclosure(A1, A2, F_{12}, \varepsilon_1, \varepsilon_2, T1, T2)$ ...define Q12 as a function of ε1

$\varepsilon_1 := 0.1, 0.15 .. 0.6$ ...define a range variable

ε_1 =	$Q12(\varepsilon_1)$ =
0.1	$4.623\cdot10^3$
0.15	$6.921\cdot10^3$
0.2	$9.211\cdot10^3$
0.25	$1.149\cdot10^4$
0.3	$1.377\cdot10^4$
0.35	$1.603\cdot10^4$
0.4	$1.829\cdot10^4$
0.45	$2.054\cdot10^4$
0.5	$2.278\cdot10^4$
0.55	$2.501\cdot10^4$
0.6	$2.723\cdot10^4$

Download free eBooks at bookboon.com



==========

Prob.5C.1.3. Calculate the net radiant heat interchange per sq. meter for two large parallel plates maintained at 800 C and 300 C. The emissivities of two plates are 0.3 and 0.6 respectively. [M.U. 1993]

be > your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more



Fig. Two infinitely large parallel plates

Mathcad Solution:

Data:

$T1 := 800 + 273$ K $T2 := 300 + 273$ K $\varepsilon 1 := 0.3$ $\varepsilon 2 := 0.6$

$\sigma := 5.67 \cdot 10^{-8}$ W/m^2.K^4....Stefan Boltzmann const.

Solution:

We have:

$$q := \frac{\sigma \cdot \left(T1^4 - T2^4\right)}{\frac{1}{\varepsilon 1} + \frac{1}{\varepsilon 2} - 1}$$

i.e. $q = 1.726 \times 10^4$ W/m^2.....Ans.

==========

Prob.5.C.1.4. Liquid O_2 at atmospheric pressure and temp –183 C is stored in a spherical vessel of outer diameter 0.3 m. The system is insulated by enclosing the container inside another concentric sphere of 0.5 m inner diameter, with space between them evacuated. Both the sphere surfaces are made of aluminum for which emissivity is 0.3. If the temp of outer surface is 40C. estimate the rate of heat flow due to radiation. What will be heat flow if polished Al with an emissivity of 0.05 is used for container walls. [M.U. 1992]

Download free eBooks at bookboon.com

Mathcad Solution:

Data:

$T1 := -183 + 273\ K$ $T2 := 40 + 273\ K$ $\sigma := 5.67 \cdot 10^{-8}$ W/m^2.K^4

$D1 := 0.3\ m$ $D2 := 0.5\ m$

$\varepsilon 1 := 0.3$ $\varepsilon 2 := 0.3$

Calculations:

$A1 := \pi \cdot D1^2$ i.e. $A1 = 0.283$ m^2

$A2 := \pi \cdot D2^2$ i.e. $A2 = 0.785$ m^2

Then:

$$Q12 := \frac{\sigma \cdot A1 \cdot \left(T1^4 - T2^4\right)}{\left(\frac{1}{\varepsilon 1}\right) + \frac{A1}{A2} \cdot \left(\frac{1}{\varepsilon 2} - 1\right)}$$

i.e. $Q12 = -36.618$ **W...Ans., -ve sign indicates heat flow *into* A1**

If the emissivity ε1 changes to 0.05:

$\varepsilon 1 := 0.05$

$$Q12' := \frac{\sigma \cdot A1 \cdot \left(T1^4 - T2^4\right)}{\left(\frac{1}{\varepsilon 1}\right) + \frac{A1}{A2} \cdot \left(\frac{1}{\varepsilon 2} - 1\right)}$$

i.e. $Q12' = -7.333$ **W...Ans., -ve sign indicates heat flow *into* A1**

Therefore, change in heat flow:

$\frac{Q12'}{Q12} = 0.2$ **...reduced to 20% of the earlier case.**

Download free eBooks at bookboon.com

Note: We can also use the Mathcad Function written earlier:

We have:

$\varepsilon 1 := 0.3 \quad \varepsilon 2 := 0.3 \quad r1 := 0.15 \ \text{m} \quad r2 := 0.25 \ \text{m}$

Then:

$Q12 := Q12\_concentric\_spheres(r1, r2, \varepsilon 1, \varepsilon 2, T1, T2)$ ..usind the Function

i.e. $Q12 = -36.618$ **W.... Ans. .... same as obtained above.**

In addition: plot the variation of Q12 as ε1 varies from 0.03 to 0.3, all other quantities remaining the same:

$\varepsilon 1 := 0.03, 0.04 .. 0.3$ ...define a range variable

Let: $Q12(\varepsilon 1) := |Q12\_concentric\_spheres(r1, r2, \varepsilon 1, \varepsilon 2, T1, T2)|$



Download free eBooks at bookboon.com

Click on the ad to read more

Note that we taken the Absolute value of Q12 to get the heat loss as positive.

We get:

ε1 =	Q12(ε1) =
0.03	4.472
0.04	5.914
0.05	7.333
0.06	8.729
0.07	10.103
0.08	11.456
0.09	12.787
0.1	14.098
0.11	15.388
0.12	16.659
0.13	17.91
0.14	19.143
0.15	20.358
0.16	21.554

ε1 =	Q12(ε1) =
0.17	22.733
0.18	23.894
0.19	25.039
0.2	26.167
0.21	27.28
0.22	28.376
0.23	29.457
0.24	30.523
0.25	31.574
0.26	32.61
0.27	33.633
0.28	34.641
0.29	35.636
0.3	36.618



==========

Prob.5.C.1.5. A blind cylindrical hole of diameter and length 3 cm is drilled into metal slab having emissivity 0.6. If the metal slab is maintained at temp 350 C. Find heat escaping out of the hole by radiation. [M.U. 1991]

Download free eBooks at bookboon.com

Mathcad Solution:

This is a problem on determining energy escaping from gray cavity. We use eqn.(13.62), viz.

$$Q_{12} = A_1 \cdot \varepsilon_1 \cdot \sigma \cdot T_1^4 \cdot \left[\frac{1 - F_{11}}{1 - \left(1 \cdot - \varepsilon_1\right) \cdot F_{11}} \right]$$ W....net radiation from gray cavity..(13.62)



Fig.Prob.5.C.1.5

Data:

$D := 0.02$ m...dia. of cylindrical cavity

$H := 0.03$ m...height of the cylindrical cavity

$\varepsilon_1 := 0.6$ ...emissivity of cyl. surface

$T_1 := 350 + 273$ K....temp. of cavity

$\sigma := 5.67 \cdot 10^{-8}$ W/(m^2.K)...Stefan-Boltzmann const.

Now, F_{11} for a cavity is already shown to be:

$$F_{11} = 1 - \frac{A_2}{A_1}$$ where A_2 = area of closing surface, A_1 = area of the cavity surface

i.e. $$F_{11} = 1 - \frac{\frac{\pi \cdot D^2}{4}}{\frac{\pi \cdot D^2}{4} + \pi \cdot D \cdot H}$$ ....for cylindrical cavity of this problem

i.e. $$F_{11} = 1 - \frac{D}{D + 4 \cdot H} = \frac{4 \cdot H}{4 \cdot H + D}$$

Download free eBooks at bookboon.com

Then, from eqn. (13.62):

$$Q_{12} := A_1 \cdot \varepsilon_1 \cdot \sigma \cdot T_1^4 \cdot \left[\frac{1 - F_{11}}{1 - (1 - \varepsilon_1) \cdot F_{11}} \right]$$

i.e. $Q_{12} = 2.45$ **W....energy escaping from the cavity....Ans.**

Therefore, $F_{11} := \frac{4 \cdot H}{4 \cdot H + D}$

i.e. $F_{11} = 0.857$ ...view factor of the cavity w.r.t. itself

And, $A_1 := \pi \cdot D \cdot H + \frac{\pi \cdot D^2}{4}$

i.e. $A_1 = 2.199 \times 10^{-3}$ m^2....area of surface of cylindrical cavity

Who is your target group?
And how can we reach them?

At Bookboon, you can segment the exact right audience for your advertising campaign.

Our eBooks offer in-book advertising spot to reach the right candidate.

Contact us to hear more
kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

Alternatively:

Use the Mathcad Function written above for the energy escaping from a cavity:

$Q12 := Q12\_from\_gray\_cavity(A_1, F_{11}, \varepsilon_1, T_1)$

i.e. $Q12 = 2.45$ **W.....Ans.....same as obtained above.**

==========

Prob.5.C.1.6. A long pipe, 50 mm dia passes through a room and is exposed to air at 20 C. The pipe surface temp is 93 C. Assuming that the emissivity of pipe surface is 0.6, calculate the radiation heat loss per meter length of the pipe. [M.U. 1991]

Mathcad Solution:



Fig.Prob.5.C.1.6.

The pipe is enclosed by the room; so, it **is two-surface enclosure problem**.

Further, area of the pipe is *very small*, compared to the area of the room. Therefore, this is a case of a *small object surrounded by a large area,* and we have:

$$\frac{A_1}{A_2} = 0$$

and, $F_{12} = 1$

$$Q_{12} = A_1 \cdot \sigma \cdot \varepsilon_1 \cdot \left(T_1^4 - T_2^4\right)$$ ....for small object in a large cavity.....(13.58)

Download free eBooks at bookboon.com

Data:

$d_1 := 0.05$ m....dia. of the pipe

$L := 1$ m....length of pipe

$\varepsilon_1 := 0.6$ ..emissivity of the surface of the pipe

$T_1 := 93 + 273$ K...temperature of the pipe

$T_2 := 20 + 273$ K...temperature of surroundings

$\sigma := 5.67 \cdot 10^{-8}$ W/(m^2.K)...Stefan-Boltzmann const.

Now, $A_1 := \pi \cdot d_1 \cdot L$

i.e. $A_1 = 0.157$ m^2....surface area of the pipe per metre length

Then, applying eqn. (13.58), we get:

$$Q_{12} := A_1 \cdot \sigma \cdot \varepsilon_1 \cdot \left(T_1^{\,4} - T_2^{\,4} \right)$$

i.e. $Q_{12} = 56.507$ **W...net radiant heat loss from the pipe per metre length...Ans.**

Alternatively: Use the Function written earlier:

$Q12 := Q12\_small\_object(A_1, \varepsilon_1, T_1, T_2)$

i.e. $Q12 = 56.507$ **W.....Ans.....same as obtained above.**

==========

Prob.5.C.1.7: A spherical steel ball, 50 mm in diameter, at a temperature of 600 deg. C, is taken out of a furnace and rests on the floor of a foundry room. Assuming that the surroundings are at a temperature of 30 deg.C, and the emissivity of the surface of the ball to be 0.8, calculate the net radiant heat loss from the ball.

(b) Also, plot the heat transferred Q12 as emissivity of ball surface varies from 0.1 to 0.9:

Mathcad Solution:

The steel ball is enclosed by the room; so, it is a *two-surface enclosure* problem.

Further, area of the ball is very small, compared to the area of the room.

Download free eBooks at bookboon.com

Therefore, *this is a case of a small object surrounded by a large area,* and we use the Mathcad Function written earlier:

Data:

$r_1 := 0.025$ m....radius of the ball

$\varepsilon_1 := 0.8$ ..emissivity of the surface of the ball

$T_1 := 600 + 273$ K...temperature of the ball

$T_2 := 30 + 273$ K...temperature of surroundings

$\sigma := 5.67 \cdot 10^{-8}$ W/(m^2.K)...Stefan-Boltzmann const.

Now, $A_1 := 4 \cdot \pi \cdot r_1^2$

i.e. $A_1 = 7.854 \times 10^{-3}$ m^2....surface area of the ball

Using the Mathcad Function written earlier:

$Q12 := Q12\_small\_object(A_1, \varepsilon_1, T_1, T_2)$

i.e. $Q12 = 203.925$ **W.....Ans.**

Brain power
By 2020, wind could provide one-tenth of our planet's electricity needs. Already today, SKF's innovative know-how is crucial to running a large proportion of the world's wind turbines.
Up to 25 % of the generating costs relate to maintenance. These can be reduced dramatically thanks to our systems for on-line condition monitoring and automatic lubrication. We help make it more economical to create cleaner, cheaper energy out of thin air.
By sharing our experience, expertise, and creativity, industries can boost performance beyond expectations.
Therefore we need the best employees who can meet this challenge!
The Power of Knowledge Engineering
Plug into The Power of Knowledge Engineering.
Visit us at www.skf.com/knowledge
SKF

Download free eBooks at bookboon.com

Click on the ad to read more

Also, plot the heat transferred Q12 as ε_1 varies from 0.1 to 0.9:

$Q12(\varepsilon_1) := Q12\_small\_object(A_1, \varepsilon_1, T_1, T_2)$ **...express Q12 as a Function of ε1**

$\varepsilon_1 := 0.1, 0.2 .. 0.9$ ....define a range variable

ε_1 =	$Q12(\varepsilon_1)$ =
0.1	25.491
0.2	50.981
0.3	76.472
0.4	101.963
0.5	127.453
0.6	152.944
0.7	178.435
0.8	203.925
0.9	229.416



==========

Prob.5.C.1.8. A hemispherical furnace of radius 1.0 m has a roof temperature of T1 = 800 K and emissivity ε1 = 0.8. The flat circular floor of the furnace has a temperature of T2 = 600 K and emissivity ε2 = 0.5. Calculate the net radiant heat exchange between the roof and the floor. [M.U. 1998]

(b) Also, plot Q12 as the emissivity of base, ε_2 varies from 0.1 to 0.8.

Download free eBooks at bookboon.com



Fig.Prob.5.C.1.8

Mathcad Solution:

This is *a two-zone enclosure problem*.

Fig. above shows the radiation network for this problem.

We have:

$$Q_{12} = \frac{E_{b1} - E_{b2}}{R_1 + R_{12} + R_2}$$

where R1 and R2 are the two *surface resistances* and,

R12 is the *space resistance* between the two radiosity potentials.

Data:

$T_1 := 800$ K...temp. of surface 1 (i.e. hemisphere)

$T_2 := 600$ K...temp. of surface 2 (i.e. base)

$\varepsilon_1 := 0.8$ ...emissivity of surface 1

$\varepsilon_2 := 0.5$ ...emissivity of surface 2

Download free eBooks at bookboon.com

$R := 1$ m....radius of surface 1

$A_1 := \frac{4 \cdot \pi \cdot R^2}{2}$ m^2....area of hemispherical surface 1

i.e. $A_1 = 6.283$ m^2....area of surface 1

$A_2 := \pi \cdot R^2$ m^2....area of surface 2

i.e. $A_2 = 3.142$ m^2....area of surface 2

$\sigma := 5.67 \cdot 10^{-8}$ W/(m^2.K)...Stefan-Boltzmann const.

Are you looking for
an affordable MBA education?
Join **American** LIGS University today!

- tuition starting at **$155 / month**
- Interactive **Online education**
- study **without** leaving your home
- programs in **English** or **Russian**

visit www.ligsuniversity.com to find out more!

Download free eBooks at bookboon.com

Click on the ad to read more

View factors:

$F_{21} := 1$ **..since all the heat radiated by surface 2 is intercepted by hemispherical surface 1.**

Now, $A_1 \cdot F_{12} = A_2 \cdot F_{21}$ **..by reciprocity**

Therefore, $F_{12} := \frac{A_2 \cdot F_{21}}{A_1}$

i.e. $F_{12} = 0.5$ **...view factor from surface 1 to surface 2**

Resistances:

Now, $R_1 := \frac{1 - \varepsilon_1}{\varepsilon_1 \cdot A_1}$

i.e. $R_1 = 0.0398$ **m^{-2}....surface resistance of inner surface**

and, $R_2 := \frac{1 - \varepsilon_2}{\varepsilon_2 \cdot A_2}$

i.e. $R_2 = 0.318$ **m^{-2}....surface resistance of outer surface**

Also, $R_{12} := \frac{1}{A_1 \cdot F_{12}}$

i.e. $R_{12} = 0.318$ **m^{-2}....space resistance between inner and outer surface**

Therefore,

$$R_{tot} := R_1 + R_{12} + R_2$$

i.e. $R_{tot} = 0.676$ **m^{-2}....total resistance between inner and outer surface**

Also,

$E_{b1} := \sigma \cdot T_1^4$ i.e. $E_{b1} = 2.322 \times 10^4$ W/m^2

$E_{b2} := \sigma \cdot T_2^4$ i.e. $E_{b2} = 7.348 \times 10^3$ W/m^2

Download free eBooks at bookboon.com

Then, net rate of heat transfer between surfaces 1 and 2 is given by:

$$Q_{12} := \frac{E_{b1} - E_{b2}}{R_{tot}}$$

i.e. $Q_{12} = 2.347 \times 10^4$ **Watts.....Ans.**

Additionally:

If both the surfaces are black: Now, both the surface resistances become zero, since ε = 1 for both the black surfaces. Then,

$$Q_{12} := \frac{E_{b1} - E_{b2}}{R_{12}}$$

i.e. $Q_{12} = 4.988 \times 10^4$ **W....if both the surfaces are black.**

(b) Also, plot Q12 as the emissivity of base, ε_2 varies from 0.1 to 0.8, other quantities remaining the same:

Express relevant quantities as functions of ε_2:

$$R_2(\varepsilon_2) := \frac{1 - \varepsilon_2}{\varepsilon_2 \cdot A_2}$$ ....R2 as a function of ε2

$$R_{tot}(\varepsilon_2) := R_1 + R_{12} + R_2(\varepsilon_2)$$ ....Rtot as a function of ε2

$$Q_{12}(\varepsilon_2) := \frac{E_{b1} - E_{b2}}{R_{tot}(\varepsilon_2)}$$ ....Q12 as a function of ε2

$\varepsilon_2 := 0.1, 0.15 .. 0.8$ ...define a range variable

Download free eBooks at bookboon.com

ε_2 =	$Q_{12}(\varepsilon_2)$ =
0.1	$4.926 \cdot 10^3$
0.15	$7.344 \cdot 10^3$
0.2	$9.732 \cdot 10^3$
0.25	$1.209 \cdot 10^4$
0.3	$1.442 \cdot 10^4$
0.35	$1.672 \cdot 10^4$
0.4	$1.9 \cdot 10^4$
0.45	$2.125 \cdot 10^4$
0.5	$2.347 \cdot 10^4$
0.55	$2.567 \cdot 10^4$
0.6	$2.784 \cdot 10^4$
0.65	$2.998 \cdot 10^4$
0.7	$3.21 \cdot 10^4$
0.75	$3.42 \cdot 10^4$
0.8	$3.627 \cdot 10^4$



==========

Prob.5.C.1.9. A pipe carrying steam, having an outside dia 20 cm, runs in a large room and is exposed to air at a temp. of 30 C. The pipe surface temp. is 400 C.

i) Calculate the loss of heat to the surrounding per metre length of pipe due to thermal radiation. Emissivity of pipe surface is 0.8.
ii) What would be the rate of heat loss due to radiation if the pipe is enclosed in a 40 cm. dia brick conduit of emissivity 0.91? [M.U. 1997]

Download free eBooks at bookboon.com

Mathcad Solution:

Case 1. Pipe in a large area:

This is a case of a small object surrounded by a large area, and we have:

$d := 0.2\ m$ $L := 1\ m$ $\varepsilon := 0.8$

$Ta := 30 + 273\ K$ $Ts := 400 + 273\ K$

$\sigma := 5.67 \cdot 10^{-8}$ W/m^2.K^4... Stefan-Boltzmann const.

$A := \pi \cdot d \cdot L$ i.e. $A = 0.628$ m^2... pipe surface area

Therefore:

$Q := \sigma \cdot \varepsilon \cdot A \cdot \left(Ts^4 - Ta^4\right)$ .W..heat loss to srroundings

i.e. $Q = 5.607 \times 10^3$ **W.....Ans.**

Download free eBooks at bookboon.com

Click on the ad to read more

Case 2. Pipe enclosed in a 40 cm dia conduit:

This is a case of a concentric cylinders, and we have:

$d := 0.2\ m \qquad D := 0.4\ m$

$\varepsilon 1 := 0.8 \qquad \varepsilon 2 := 0.91$

$A1 := \pi \cdot d \cdot L$ i.e. $A1 = 0.628$ m^2... pipe surface area

$A2 := \pi \cdot D \cdot L$ i.e. $A2 = 1.257$ m^2... brick conduit surface area

Then, we have:

$$Q := \frac{\sigma \cdot A1 \cdot \left(Ts^4 - Ta^4\right)}{\left(\frac{1}{\varepsilon 1}\right) + \frac{A1}{A2} \cdot \left(\frac{1}{\varepsilon 2} - 1\right)}$$

i.e. $Q = 5.393 \times 10^3$ **W...Ans.**

==========

Prob. 5.C.1.10. Write EES Functions for a general two-surface enclosures, and also for few special cases of two-surface enclosures:

Following are the EES Functions. Later, we shall use them in solving some problems.

```
$UnitSystem SI Pa J K

FUNCTION Q12_TwoSurfaceEnclosure(A_1, A_2, F_12, epsilon_1, epsilon_2, T_1, T_2)

{Returns Q12 from surface 1 to 2 in a general, two-surface enclosure; 1 is the internal surface.

Inputs: A1, A2 (m^2), T1, T2 (K)}

sigma := 5.67E-08 "[W/m^2-K^4]….Stefan Boltzmann constant"

R_12 := 1/(A_1 * F_12) "[1/m^2]…space resistance"

R_1 := (1 – epsilon_1) / (A_1 * epsilon_1) "[1/m^2]..surface resistance of surface 1"
```

Download free eBooks at bookboon.com

```
R_2 := (1 – epsilon_2) / (A_2 * epsilon_2) "[1/m^2]..surface resistance of surface 2"

R_tot := R_1 + R_2 + R_12 "…total resistance"

E_b1 := sigma * T_1^4 "[W/m^2]"

E_b2 := sigma * T_2^4 "[W/m^2]"

Q12_TwoSurfaceEnclosure := (E_b1 – E_b2) / R_tot "[W]"

END

"-----------------------------------------------------------------------------------------------------------------------"

FUNCTION Q12_SmallObject(A_1, epsilon_1, T_1, T_2)

{Returns Q12 from small object 1 to a large surrounding surface 2; 1 is the internal surface.

Inputs: A1 (m^2), T1, T2 (K)}

sigma := 5.67E-08 "[W/m^2-K^4]….Stefan Boltzmann constant"

Q12_SmallObject := sigma * A_1 * epsilon_1 * (T_1^4 – T_2^4) "[W]"

END

"-----------------------------------------------------------------------------------------------------------------------"

FUNCTION Q12_parallel_plates(A, epsilon_1, epsilon_2,T_1, T_2)

{Returns net Q12 from plate 1 to a parallel plate 2;

Inputs: A (m^2), T1, T2 (K)}

sigma := 5.67E-08 "[W/m^2-K^4]….Stefan Boltzmann constant"

Q12_parallel_plates := sigma * A * (T_1^4 – T_2^4) / (1/epsilon_1 + 1/epsilon_2 – 1)"[W]"

END

"-----------------------------------------------------------------------------------------------------------------------"
```

Download free eBooks at bookboon.com

FUNCTION Q12_long_concentric_cylinders(L, R_1, R_2, epsilon_1, epsilon_2,T_1, T_2)

{Returns net Q12 from surface 1 to surface 2; 1 is the inner cylindrical surface.

Inputs: L, R_1, R_2 (m), T1, T2 (K)}

sigma := 5.67E-08 "[W/m^2-K^4]….Stefan Boltzmann constant"

Q12_long_concentric_cylinders := sigma * (2 * pi * R_1 * L) * (T_1^4 – T_2^4) / (1/epsilon_1 + (R_1 / R_2) * (1/epsilon_2 – 1))"[W]"

END

"----------"

FUNCTION Q12_concentric_spheres(R_1, R_2, epsilon_1, epsilon_2,T_1, T_2)

{Returns net Q12 from surface 1 to surface 2; 1 is the inner spherical surface.

Inputs: R_1, R_2 (m), T1, T2 (K)}



Download free eBooks at bookboon.com

Click on the ad to read more

sigma := 5.67E-08 "[W/m^2-K^4]….Stefan Boltzmann constant"

Q12_concentric_spheres := sigma * (4 * pi * R_1^2) * (T_1^4 – T_2^4) / (1/epsilon_1 + (R_1 / R_2)^2 * (1/epsilon_2 – 1))"[W]"

END

"----------"

FUNCTION Q12_from_gray_cavity(A_1,F_11, epsilon_1, T_1)

{Returns net Q12 from surface 1 of cavity to a closing surface 2;

Inputs: A_1 (m^2), T1 (K)}

sigma := 5.67E-08 "[W/m^2-K^4]….Stefan Boltzmann constant"

Q12_from_gray_cavity := sigma * A_1 * epsilon_1 * T_1^4 * ((1 – F_11) / (1 – (1 – epsilon_1) * F_11))"[W]"

END

"----------"

Prob. 5.C.1.11. Two large parallel plates are at 1000 K and 800 K. Determine the heat exchange per unit area, when:

i) The surfaces are black
ii) The hot surface has an emissivity of 0.9 and the cold surface has emissivity = 0.6 [VTU – Dec. 2006/Jan. 2007]

In addition, plot the variation of Q12 with e2, all other conditions remaining the same.



Fig. Two infinitely large parallel plates

Download free eBooks at bookboon.com

EES Solution:

"Data:"

A = 1 [m^2]

epsilon_1 = 0.9

epsilon_2 = 0.6

T_1 = 1000 [K]

T_2 = 800 [K]

"Case 1: when both surfaces are black:"

Q12_both_black = 5.67E-08[W/m^2-K^4] * A * (T_1^4 – T_2^4)

"Case 2: When epsilon_1 and epsilon_2 are 0.9 and 0.6 respectively:"

"Using the EES Function for parallel plates, written above:"

Q12_both_gray = Q12_parallel_plates(A, epsilon_1, epsilon_2,T_1, T_2)

Results:





Download free eBooks at bookboon.com

Thus:

Q12 when both surfaces are black: 33476 W …. Ans.

Q12 when ε1 and ε2 are 0.9 and 0.6, respectively = 18830 W … Ans.

---

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

In addition, plot the variation of Q12 with e2, all other conditions remaining the same:

First, compute the parametric Table:

Parametric Table

Table 1

1..9	1 ε_2	2 $Q12_{both,gray}$ [W]
Run 1	0.1	3311
Run 2	0.2	6550
Run 3	0.3	9719
Run 4	0.4	12820
Run 5	0.5	15857
Run 6	0.6	18830
Run 7	0.7	21742
Run 8	0.8	24594
Run 9	0.9	27389

Now, plot the results:



==========

Download free eBooks at bookboon.com

Prob. 5.C.1.12. A solid copper sphere of 10 cm dia at 1000 C is suspended in a large enclosure. If the walls of the enclosure are at 30 C, determine: (i) the initial rate of cooling of the sphere (ii) time taken by the sphere to cool to 900 C.

Use the following properties for copper: density, ρ = 8954 kg/m^3, specific heat, cp = 381 J/kg.K, thermal conductivity, k = 386 W/m.K, emissivity, ε = 0.78. [VTU – Aug. 2001]

(b) Additionally, plot the variation of these quantities as emissivity of surface of sphere varies from 0.1 to 0.9.

EES Solution:

This is the case of a *small object in a large surrounding*.

So, to get Q12, use the EES Function written above.

"Data:"

R = 0.05 [m] "….radius of sphere"

epsilon_1 = 0.78 "…emissivity of sphere surface"

T_1 = 1273 [K] "…sphere temp."

T_2 = 303 [K] "….surroundings temp."

rho = 8954[kg/m^3] "…density of copper"

cp = 381 [J/kg-K] "…sp. heat of copper"

k = 386 [W/m-K] "…thermal cond. of copper"

"Calculations:"

A_1 = 4 * pi * R^2 "[m^2]… surface area of sphere"

"To find Q12, use the EES Function already written for a small object in a large enclosure:"

Q12 = Q12_SmallObject(A_1, epsilon_1, T_1, T_2) "[W]…finds rate of initial heat loss from the sphere"

Download free eBooks at bookboon.com

"But, Q12 is also equal to:

Q12 = mass * cp * dTbydtau, where dTbydtau is the initial rate of cooling"

"Therefore:"

mass = rho * (4/3) * pi * R^3 "…[kg]… mass of sphere"

Q12 = mass * cp * dTbydtau "…[C/s]….finds initial rate of cooling"

"Time taken to cool to 900 C:"

"Find the rate of heat loss when the sphere temp is 900 C. Then, take the average rate of heat loss from 1000 C to 900 C, and the find the approx. time taken to cool from 1000 C to 900 C, knowing the total amount of heat removed in the process:"

Q12_2 = Q12_SmallObject(A_1, epsilon_1, 1173, T_2)"[W]…finds rate of heat loss from the sphere when it is at 900 C"

The Wake
the only emission we want to leave behind
Low-speed Engines Medium-speed Engines Turbochargers Propellers Propulsion Packages PrimeServ
The design of eco-friendly marine power and propulsion solutions is crucial for MAN Diesel & Turbo.
Power competencies are offered with the world's largest engine programme – having outputs spanning from 450 to 87,220 kW per engine. Get up front!
Find out more at www.mandieselturbo.com
Engineering the Future – since 1758.
MAN Diesel & Turbo
MAN

Download free eBooks at bookboon.com

Click on the ad to read more

"Therefore:"

Q12_avg = (Q12 + Q12_2) / 2

"And:"

Q_lost = mass * cp * (1000 – 900)"[J]"

"Therefore, approx. time taken to cool to 900 C:"

time = Q_lost / Q12_avg "[s]……time taken to cool to 900 C"

Results:

Main | Q12_SmallObject

Unit Settings: SI K Pa J mass deg

A_1 = 0.03142 [m^2]	cp = 381 [J/kg-K]	dTbydtau = 2.036 [C/s]	ε_1 = 0.78
k = 386 [W/m-K]	mass = 4.688 [kg]	Q12 = 3637 [W]	$Q12_2$ = 2619 [W]
$Q12_{avg}$ = 3128 [W]	Q_{lost} = 178624 [J]	R = 0.05 [m]	ρ = 8954 [kg/m^3]
time = 57.11 [s]	T_1 = 1273 [K]	T_2 = 303 [K]	

Main | Q12_SmallObject

Local variables in Function Q12_SmallObject (2 calls, 0.00 sec)

A_1=0.03142 [m^2]	ε_1 =0.78	$Q12_{SmallObject}$ =2619 [W]
σ =5.670E-08 [W/m^2K^4]	T_1=1173 [K]	T_2=303 [K]

Thus:

Initial rate of heat loss, Q12 = 3637 W.…Ans.

Initial rate of cooling, dT/dτ = 2.036 C/s … Ans.

Approx. time taken to cool to 900 C = time = 57.11 s …. Ans.

Download free eBooks at bookboon.com

Additionally, plot the variation of these quantities as emissivity of surface of sphere varies from 0.1 to 0.9:

First, compute the Parametric Table:

Table 1 | Table 2

1..9	1 ε_1	2 Q12 [W]	3 dTbydtau [C/s]	4 time [s]
Run 1	0.1	466.3	0.261	445.4
Run 2	0.2	932.6	0.5221	222.7
Run 3	0.3	1399	0.7831	148.5
Run 4	0.4	1865	1.044	111.4
Run 5	0.5	2331	1.305	89.09
Run 6	0.6	2798	1.566	74.24
Run 7	0.7	3264	1.827	63.63
Run 8	0.8	3730	2.088	55.68
Run 9	0.9	4197	2.349	49.49

Now, plot the results:



Download free eBooks at bookboon.com



See the light!
The sooner you realize we are right, the sooner your life will get better!

A bit over the top? Yes we know!

We are just that sure that we can make your media activities more effective.

Get "Bookboon's Free Media Advice"
Email kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more



Prob. 5.C.1.13. Refer to Fig. below. Three thin walled, long, circular cylinders 1, 2 and 3, of diameters 15 cm, 25 cm and 35 cm respectively, are arranged concentrically as shown. Temperature of cylinder 1 is 80 K and that of cylinder 3 is 300 K. Emissivities of cylinders 1, 2 and 3 are 0.05, 0.1 and 0.2 respectively. Assuming that there is vacuum inside the annular spaces, determine the steady state temperature attained by cylinder 2.

(b) In addition, plot Q12 and T2 as ε_2 varies from 0.1 to 0.9.



Fig.Prob.5C.1.13

Download free eBooks at bookboon.com

EES Solution:

This is the case of long, concentric cylinders.

To find T2, use the fact that: in steady state, net radiant heat transfer between cylinders 1 and 2 must be equal to the net radiant heat transfer between cylinders 2 and 3.

To find Q12 between long, concentric cylinders, use the EES Function already written.

"Data:"

R1 = 0.075 [m]"….radius of inner cyl"

R2 = 0.125 [m]"….radius of middle cyl"

R3 = 0.175 [m]"….radius of outer cyl"

L = 1[m] "…assumed"

epsilon_1 = 0.05"…emissivity of surface 1"

epsilon_2 = 0.1"…emissivity of surface 2"

epsilon_3 = 0.2"…emissivity of surface 3"

T_1 = 80 [K]"…inner cylinder temp."

T_3 = 300 [K]"….outer cylinder temp."

"Calculations:"

"Net heat transfer between surfaces 1 and 2:

Using the EES Function already written:"

Q12 = Q12_long_concentric_cylinders(L, R1, R2, epsilon_1, epsilon_2,T_1, T_2)

"Similarly, Net heat transfer between surfaces 2 and 3:"

Q23 = Q12_long_concentric_cylinders(L, R2, R3, epsilon_2, epsilon_3,T_2, T_3)

"Equating Q12 and Q23, we get the unknown temp, T2:"

Q12 = Q23 "..equate Q12 to Q23 to get T2"

Download free eBooks at bookboon.com

Results:

Main | Q12_long_concentric_cylinders

Unit Settings: SI K Pa J mass deg

$\varepsilon_1 = 0.05$	$\varepsilon_2 = 0.1$	$\varepsilon_3 = 0.2$
L = 1 [m]	Q12 = -6.503 [W]	Q23 = -6.503 [W]
R1 = 0.075 [m]	R2 = 0.125 [m]	R3 = 0.175 [m]
σ = 5.670E-08 [W/m^2-K^4]	T_1 = 80 [K]	T_2 = 280.9 [K]
T_3 = 300 [K]		

Main | Q12_long_concentric_cylinders

Local variables in Function Q12_long_concentric_cylinders (36 calls, 0.02 sec)

ε_1 =0.1	ε_2 =0.2
L=1 [m]	$Q12_{long.concentric.cylinders}$=-6.503 [W]
R_1 =0.125 [m]	R_2 =0.175 [m]
σ =5.670E-08 [W/m^2-K^4]	T_1=280.9 [K]
T_2=300 [K]	

be > your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

Thus:

Temp of middle cylinder = T2 = 280.9 K … Ans.

Net heat transfers Q12 = Q23 = -6.503 W.… Ans. (-ve sign indicates heat flow from outer cylinder to inner cylinder)

In addition, plot Q12 and T2 as ε_2 varies from 0.1 to 0.9:

First, compute the Parametric Table:

1..9	1 ε_2	2 Q12 [W]	3 T_2 [K]
Run 1	0.1	-6.503	280.9
Run 2	0.2	-7.942	286.1
Run 3	0.3	-8.574	288.3
Run 4	0.4	-8.93	289.5
Run 5	0.5	-9.157	290.3
Run 6	0.6	-9.316	290.8
Run 7	0.7	-9.433	291.2
Run 8	0.8	-9.522	291.5
Run 9	0.9	-9.593	291.8

Now, plot the results:



Download free eBooks at bookboon.com



==========

Prob.5.C.1.14. For a hemispherical furnace, the flat floor is at 700 K and has an emissivity of 0.5. The hemispherical roof is at 1000 K and has an emissivity of 0.25. Find the net radiant heat transfer from the roof to floor. [V.T.U – July–Aug. 2003]

(b) Also, plot Q12 as the emissivity of base, ε_2 varies from 0.1 to 0.9, all other conditions remaining the same.



Fig.Prob.5.C.1.14

Download free eBooks at bookboon.com

EES Solution:

Assume the radius of hemisphere as 1 m.

Note that *this problem is similar to Prob.5.C.1.8,* which was solved in Mathcad; but, now, temperatures and emissivity values are different.

This is a *two-surface enclosure problem.*

Use the EES Function written earlier, to find Q12 of a two-surface enclosure:

"Data:"

R1 = 1 [m]"….radius of hemisphere"

epsilon_1 = 0.25"…emissivity of hemisph. surface 1"

epsilon_2 = 0.5"…emissivity of base surface 2"

T_1 = 1000 [K]"…hemisph. surface temp."



Download free eBooks at bookboon.com

Click on the ad to read more

T_2 = 700 [K]"….base temp."

"Calculations:"

A_1 = 4 * pi * R1^1 / 2 "[m^2]….area of hemisph. surface"

A_2 = pi * R1^2 "[m^2]..area of base surface"

"View factors:"

F_21 = 1 "…since all the energy leaving surface 2 is intercepted by surface 1"

"To find F_12, View factor from surface 1 to surface 2:"

A_1 * F_12 = A_2 * F_21 "…by reciprocity… finds F_12"

"Now, to get Q12 use the EES Function for a general, two-surface enclosure, already written:"

Q12 = Q12_TwoSurfaceEnclosure(A_1, A_2, F_12, epsilon_1, epsilon_2, T_1, T_2)

Results:

Main | Q12_TwoSurfaceEnclosure

Unit Settings: SI K Pa J mass deg

$A_1 = 6.283$ [m^2]	$A_2 = 3.142$ [m^2]	$\varepsilon_1 = 0.25$	$\varepsilon_2 = 0.5$	$F_{12} = 0.5$
$F_{21} = 1$	$Q12 = 38674$ [W]	$R1 = 1$ [m]	$T_1 = 1000$ [K]	$T_2 = 700$ [K]

Main | Q12_TwoSurfaceEnclosure

Local variables in Function Q12_TwoSurfaceEnclosure (1 call, 0.00 sec)

A_1=6.283 [m^2]	A_2=3.142 [m^2]
ε_1 =0.25	ε_2 =0.5
E_{b1}=56700 [W/m^2]	E_{b2}=13614 [W/m^2]
F_{12}=0.5	$Q12_{TwoSurfaceEnclosure}$ =38674 [W]
R_1 =0.4775 [1/m^2]	R_{12}=0.3183 [1/m^2]
R_2 =0.3183 [1/m^2]	R_{tot}=1.114 [1/m^2]
σ =5.670E-08 [W/m^2-K^4]	T_1=1000 [K]
T_2=700 [K]	

Download free eBooks at bookboon.com

Thus:

Net radiant heat transfer from roof to floor = Q12 = 38674 W …. Ans.

(b) Also, plot Q12 as the emissivity of base, ε_2 varies from 0.1 to 0.9:

First, compute the Parametric Table:

Table 1 | Table 2 | Table 3 | Table 4

1..9	1 ε_2	2 Q12 [W]
Run 1	0.1	11770
Run 2	0.2	20825
Run 3	0.3	28005
Run 4	0.4	33840
Run 5	0.5	38674
Run 6	0.6	42745
Run 7	0.7	46220
Run 8	0.8	49222
Run 9	0.9	51840

And, plot the results:



Download free eBooks at bookboon.com

Prob.5.C.1.15. Write EXCEL – VBA Functions for heat transfer in a general, two-surface enclosure and also for a few special cases of the same.

1. **For a general, two-surface enclosure:**

```
Option Explicit
'General two-surface enclosure:
Function Q_12_Two_surface_enclosure(A_1 As Double, A_2 As Double, eps_1 As Double, _
eps_2 As Double, T_1 As Double, T_2 As Double, F_12 As Double) As Double

'Finds Q_12 = Q1 = -Q2 for a two-surface enclosure (W)

Dim sigma As Double, R1 As Double, R2 As Double, R_12 As Double

sigma = 0.0000000567  'W/m2.K^4
R1 = (1 - eps_1) / (A_1 * eps_1) 'surface resistance of surface 1
R2 = (1 - eps_2) / (A_2 * eps_2) 'surface resistance of surface 2
R_12 = 1 / (A_1 * F_12)    'space resistance between surface 1 and 2

Q_12_Two_surface_enclosure = (sigma * (T_1 ^ 4 - T_2 ^ 4)) / (R1 + R_12 + R2)

End Function
```

Who is your target group?
And how can we reach them?

At Bookboon, you can segment the exact right audience for your advertising campaign.

Our eBooks offer in-book advertising spot to reach the right candidate.

Contact us to hear more
kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

2. **Small object in a large cavity:**

```
'Special cases of Two-surface enclosures:

Function Q_12_small_object_in_large_cavity(A_1 As Double, eps_1 As Double, _
T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) for a small object placed in a large enclosure, i.e. (A_1/A_2) = 0, F_12 = 1

Dim sigma As Double
sigma = 0.0000000567 'W/m2.K^4

Q_12_small_object_in_large_cavity = sigma * A_1 * eps_1 * (T_1 ^ 4 - T_2 ^ 4)

End Function
```

3. **Infinite, large, parallel plates:**

```
Function Q_12_Infinite_large_parallel_plates(Area As Double, eps_1 As Double, eps_2 As Double, _
T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) between two infinite parallel plates of area A (m2) each,
'i.e. (A_1/A_2) = 1, F_12 = 1

Dim sigma As Double
sigma = 0.0000000567 'W/m2.K^4

Q_12_Infinite_large_parallel_plates = (sigma * Area * (T_1 ^ 4 - T_2 ^ 4)) / _
(1 / eps_1 + 1 / eps_2 - 1)

End Function
```

4. **Infinite, concentric cylinders:**

```
Function Q_12_Infinite_concentric_cylinders(A_1 As Double, R_1 As Double, R_2 As Double, _
eps_1 As Double, eps_2 As Double, T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) between infinite concentric cylinders,
'i.e. (A_1/A_2) = R_1/R_2, F_12 = 1

Dim sigma As Double
sigma = 0.0000000567 'W/m2.K^4

Q_12_Infinite_concentric_cylinders = (sigma * A_1 * (T_1 ^ 4 - T_2 ^ 4)) / _
(1 / eps_1 + ((1 - eps_2) / eps_2) * (R_1 / R_2))

End Function
```

Download free eBooks at bookboon.com

5. **Concentric spheres:**

```
Function Q_12_concentric_spheres(A_1 As Double, R_1 As Double, R_2 As Double, _
eps_1 As Double, eps_2 As Double, T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) between concentric spheres,
'i.e. (A_1/A_2) = (R_1/R_2)^2, F_12 = 1

Dim sigma As Double
sigma = 0.0000000567 'W/m2.K^4

Q_12_concentric_spheres = (sigma * A_1 * (T_1 ^ 4 - T_2 ^ 4)) / _
(1 / eps_1 + ((1 - eps_2) / eps_2) * (R_1 / R_2) ^ 2)

End Function
```

Now, let us solve a few problems using these VBA Functions:

Prob.5.C.1.16. Consider the Prob.5.C.1.14 again. Solve it with EXCEL.

(b) Plot the variation of Q12 with ε1when ε1 varies from 0.1 to 0.9 and (c) also, plot the variation of Q12 with T1 when T1 varies from 800 K to 1300 K.

EXCEL Solution:

We have:



Fig.Prob.5.C.1.16

We have already shown that:

A1 = 6.283 m^2, A2 = 3.142 m^2,

ε1 = 0.25, ε2 = 0.5,

Download free eBooks at bookboon.com

T1 = 1000 K, T2 = 700 K, and

View factor, F12 = 0.5

Set up the EXCEL worksheet as shown:


H8
=Q_12_Two_surface_enclosure(B8,C8,D8,E8,F8,G8,E6)
Two - surface enclosures:
Using VBA Function
1. General two-surface enclosure:
Stefan_const = 5.67E-08
ViewFactor_12 = 0.5
Area_1 (m2) Area_2 (m2) epsilon_1 epsilon_2 Temp_1 (K) Temp_2 (K) Q_12(W)
6.283 3.142 0.25 0.5 1000 700 38674.82

The simple EXCEL worksheet shown above uses the VBA Function for Q12 for a general, two-surface enclosure, written earlier (available in 'User Defined' category of Functions).

See the Formula bar for the Function entered for Q12 in cell H8.

Brain power
By 2020, wind could provide one-tenth of our planet's electricity needs. Already today, SKF's innovative know-how is crucial to running a large proportion of the world's wind turbines.
Up to 25 % of the generating costs relate to maintenance. These can be reduced dramatically thanks to our systems for on-line condition monitoring and automatic lubrication. We help make it more economical to create cleaner, cheaper energy out of thin air.
By sharing our experience, expertise, and creativity, industries can boost performance beyond expectations.
Therefore we need the best employees who can meet this challenge!
The Power of Knowledge Engineering
Plug into The Power of Knowledge Engineering.
Visit us at www.skf.com/knowledge
SKF

Download free eBooks at bookboon.com

Click on the ad to read more

Note the advantage of this EXCEL spreadsheet: Above worksheet can be used as a *template* to solve any two-surface enclosure problem. Simply enter the relevant quantities from cell B8 to G8, and Q12 is immediately up-dated in cell H8.

(b) To plot Q12 against ε1, all other conditions remaining the same:

First, set up a Table as shown:



In the above, note that Q12 is calculated in cell C12 using the VBA Function. Take care to enter epsilon1 with *relative reference*, all other quantities are with *absolute reference*, so that when we drag-copy from cell C12 to cell C20, Q12 values are suitably calculated and the Table is filled up. See below:



Download free eBooks at bookboon.com



(c) Now, plot Q12 vs T1, all other conditions remaining the same:

First, set up a Table as shown:



Download free eBooks at bookboon.com

In the above, note that Q12 is calculated in cell C25 using the VBA Function. Take care to enter T1 with *relative reference*, all other quantities are *with absolute reference*, so that when we drag-copy from cell C25 to cell C35, Q12 values are suitably calculated and the Table is filled up. See below:



	A	B	C	D	E	F	G
23							
24		T_1 (K)	Q_12 (W/m^2)				
25		800	8626.637				
26		850	14347.510				
27		900	21172.159				
28		950	29234.184				
29		1000	38674.817				
30		1050	49642.925				
31		1100	62295.008				
32		1150	76795.201				
33		1200	93315.275				
34		1250	112034.632				
35		1300	133140.310				

Are you looking for
an affordable MBA education?
Join **American** LIGS University today!

- tuition starting at **$155 / month**
- Interactive **Online education**
- study **without** leaving your home
- programs in **English** or **Russian**

visit www.ligsuniversity.com to find out more!

Download free eBooks at bookboon.com

Click on the ad to read more

Now, plot the results:



==========

Prob.5.C.1.17. Determine the rate of heat loss by radiation from a steel tube of outside dia 70 mm and 3 m long at a temp of 227 C if the tube is located within a square brick conduit of 0.3 m side and at 27 C. Take for steel ε1 = 0.79 and for brick, ε2 = 0.93. [P.U. 1998]

EXCEL Solution:

We have: 1 is inner surface and 2 is outer surface:

Length = 3 m

T1 = 227 + 273 = 500 K

T2 = 27 + 273 = 300 K

ε1 = 0.79

ε2 = 0.93

A1 = π * 0.07 * 3 = 0.659734 m^2

A2 = Perimeter * Length = (0.3 * 4) * 3 = 3.6 m^2

F12 = 1, since surface 1 is completely enclosed in 2.

Download free eBooks at bookboon.com

Now, use the EXCEL Template prepared while solving the previous Problem.

Entering the above values of data, we get:


H8
=Q_12_Two_surface_enclosure(B8,C8,D8,E8,F8,G8,E6)
1. General two-surface enclosure:
Using VBA Function
Stefan_const = 5.67E-08 ViewFactor_12 = 1
Area_1 (m2) Area_2 (m2) epsilon_1 epsilon_2 Temp_1 (K) Temp_2 (K) Q_12(W)
0.659734 3.6 0.79 0.93 500 300 1590.272

i.e. Q12 = 1590.27 W …. Ans.

Again, note the advantage of working with EXCEL spreadsheet:

Variation of Q12 with epsilon1 and T1, in Tables and plots are immediately up-dated, as shown below:

epsilon1	Q_12 (W/m^2)
0.1	203.213
0.2	405.868
0.3	607.965
0.4	809.509
0.5	1010.500
0.6	1210.941
0.7	1410.834
0.8	1610.182
0.9	1808.987



Download free eBooks at bookboon.com

And:

T_1 (K)	Q_12 (W/m^2)
800	11737.023
850	15022.987
900	18942.941
950	23573.620
1000	28996.146
1050	35296.026
1100	42563.150
1150	50891.796
1200	60380.623
1250	71132.678
1300	83255.393



==========

Prob.5.C.1.18. Two very large plates are maintained at T1 = 600 K and T2 = 400 K. Emissivities are: epsilon1 = 0.5 and epsilon2 = 0.9. Determine the net radiation heat transfer between the plates.

(b) Also, plot Q12 as e1 varies from 0.1 to 0.9, all other conditions remaining the same.

Download free eBooks at bookboon.com

Click on the ad to read more

(c) And, plot Q12 as T1 varies from 500 K to 1000 K, all other conditions remaining the same.[Ref:2]



Fig. Two infinitely large parallel plates

EXCEL Solution:

We shall use the VBA Function written above for Q12 for, infinite, parallel plates (available in 'User Defined' category of Functions).

Set up the EXCEL worksheet as shown:

C55 =Q_12_Infinite_large_parallel_plates(C47,C48,C49,C50,C51)

	A	B	C	D	E	F	G
45							
46		Data:					
47		A	1	m^2			
48		epsilon1	0.5				
49		epsilon2	0.9				
50		T_1	600	K			
51		T_2	400	K			
52							
53		Use the VBA Function to find Q12 for parallel plates:					
54							
55		Q_12 =	2793.221053	W/m2...Ans.			

Note that Q12 is calculated in cell C55 and the VBA Function used can be seen in the Formula bar.

Download free eBooks at bookboon.com

Thus: Q12 = 2793.22 W/m^2 …. Ans.

(b) Also, plot Q12 as ε1 varies from 0.1 to 0.9, all other conditions remaining the same:

First, set up a Table as shown:



In the above, note that Q12 is calculated in cell C60 using the VBA Function. Take care to enter epsilon1 with *relative reference*, all other quantities are with *absolute reference*, so that when we drag-copy from cell C60 to cell C68, Q12 values are suitably calculated and the Table is filled up. See below:



Download free eBooks at bookboon.com

Now, plot the results:





Download free eBooks at bookboon.com

Click on the ad to read more

(c) And, plot Q12 as T1 varies from 500 K to 1000 K, all other conditions remaining the same:

First, set up a Table as shown below:



T1 (K)	Q12 (W/m^2)
500	991.0563158
550	
600	
650	
700	
750	
800	
850	
900	
950	
1000	

In the above, note that Q12 is calculated in cell C77 using the VBA Function. Take care to enter T1 with *relative reference*, all other quantities are with *absolute reference*, so that when we drag-copy from cell C77 to cell C87, Q12 values are suitably calculated and the Table is filled up. See below:



T1 (K)	Q12 (W/m^2)
500	991.0563158
550	1770.103125
600	2793.221053
650	4106.739967
700	5761.018421
750	7810.443651
800	10313.43158
850	13332.42681
900	16933.90263
950	21188.36102
1000	26170.33263

Download free eBooks at bookboon.com

Now, plot the results:



==========

Prob.5.C.1.19. Consider a water tank of size: 2 m (L) × 1 m (W) × 1m (H), at a temperature of 30 C, which radiates from its sides and sides to surroundings at 5 C. Emissivity of tank surfaces is 0.9. Calculate the rate of heat radiation from the tank to the surroundings.

(b) Investigate the effect of emissivity of tank surface on the heat radiation rate. Let e vary from 0.1 to 0.9.

EXCEL Solution:

This is the case of a small object in large surroundings.

Use the VBA Function written earlier.

Download free eBooks at bookboon.com

Following is the worksheet:



C103 | =Q_12_small_object_in_large_cavity(C98,C101,C99,C100)

	A	B	C	D	E	F
94		Data:				
95		L	2	m		
96		W	1	m		
97		H	1	m		
98		A	8	m^2		
99		T_1	303	K		
100		T_2	278	K		
101		epsilon1	0.9			
102						
103		Q_12 =	1002.668	W...Ans.		

Q12 is calculated in cell C103 using the VBA Function for a small object in large surroundings, written earlier. See the Formula bar for the VBA Function entered in cell C103.

Thus: Q12 = 1002.67 W … Ans.

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

(b) Investigate the effect of emissivity of tank surface on the heat radiation rate. Let epsilon1 vary from 0.1 to 0.9:

First, set up a Table as shown:



In the above, note that Q12 is calculated in cell C108 using the VBA Function. Take care to enter epsilon1 with *relative reference*, all other quantities are with *absolute reference*, so that when we drag-copy from cell C108 to cell C116, Q12 values are suitably calculated and the Table is filled up. See below:



Download free eBooks at bookboon.com

Now, plot the results:



==========

Prob.5.C.1.20. Three thin-walled, 3 m long, hollow cylinders of radii 5 cm, 10 cm and 15 cm are arranged concentrically. T1 = 1000 K and T3 = 300 K. Assuming epsilon1 = epsilon2 = epsilon3 = 0.05 and vacuum in the spaces between the cylinders, calculate the steady state temp of cylindrical surface 2, and the heat flow rate.

EXCEL Solution:



Fig.Prob.5.C.1.20

We shall use the condition that in steady state, Q12 = Q23 to calculate the temp. T2.

VBA Function for infinite, concentric cylinders is already written and we use it to calculate Q12 and Q23.

Download free eBooks at bookboon.com

We also use Goal Seek in EXCEL to find T2 such that Q12 = Q23.

Following is the worksheet:



In the above worksheet, **we have started with a trial value for T2 (= 400 K).**

Calculate Q12 and Q23 using the VBA Functions for Infinitely long, concentric cylinders, written earlier.

The Wake
the only emission we want to leave behind
Low-speed Engines Medium-speed Engines Turbochargers Propellers Propulsion Packages PrimeServ
The design of eco-friendly marine power and propulsion solutions is crucial for MAN Diesel & Turbo. Power competencies are offered with the world's largest engine programme – having outputs spanning from 450 to 87,220 kW per engine. Get up front!
Find out more at www.mandieselturbo.com
Engineering the Future – since 1758.
MAN Diesel & Turbo
MAN

Download free eBooks at bookboon.com

Click on the ad to read more

Formula bar shows the Function entered for Q12 in cell C140.

In steady state, Q12 should be equal to Q23. i.e. (Q12 – Q23)^2 = 0.i.e. cell C142 should be equal to zero. But, now it is not equal to zero since we have started with an arbitrary, trial value for T2.

To find the correct value of T2:

Use Goal Seek to set (Q12 – Q23)^2 = 0, by changing T2, i.e. cell C138:

To apply Goal Seek: Go to: Data – What If analysis – Goal Seek:



Click on Goal Seek. We get following screen. Fill it up as shown:



Now, click OK and we get:



Goal Seek has found a solution.

Download free eBooks at bookboon.com

Again click OK to see value of T2 in cell C138:



Therefore:

In steady state, T2 = 775.443 K …. Ans.

Q12 = Q23 = 1156.49 W …. Ans.

==========

5.C.2 Radiation energy exchange in 3-surface enclosures:

Prob. 5.C.2.1. Write Mathcad Functions for a general three-surface enclosures.

Recollect the schematic and Radiation network for a general 3-surface enclosure (shown below).

Here, for the 3 surfaces, area (a1, A2, A3), Temperatures (T1, T2, T3) and emissivities (eps1, eps2, eps3) are given. View Factors F12, F3 and F23 are either given or calculated. We have to *find out the three Radiosities, and the rate of heat transfers.*

The procedure is:

i) *Apply Kirchoff's Law* to the three nodes to get three algebraic equations. Here, it is important to assume that the (heat) current flow is ***into*** the node. The signs adjust themselves while solving for Radiosities.

ii) Now, we write a Function to solve for the Radiosities J1, J2 and J3 with 'Solve Block' of Mathcad.

iii) Then, we use this Function in another Mathcad Function to get the values of heat transferred from each surface and between any two surfaces.

Download free eBooks at bookboon.com



Fig.(a)



Fig.(b)

Fig. Prob.5.C.2.1

See the light!
The sooner you realize we are right, the sooner your life will get better!

A bit over the top? Yes we know!

We are just that sure that we can make your media activities more effective.

Get "Bookboon's Free Media Advice"
Email kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

Writing Kirchoff's Law to Nodes J1, J2:

$$\frac{Eb1 - J1}{R1} + \frac{J2 - J1}{R12} + \frac{J3 - J1}{R13} = 0 \quad \text{....for node J1}$$

$$\frac{Eb2 - J2}{R2} + \frac{J1 - J2}{R12} + \frac{J3 - J2}{R23} = 0 \quad \text{....for node J2}$$

$$\frac{Eb3 - J3}{R3} + \frac{J1 - J3}{R13} + \frac{J2 - J3}{R23} = 0 \quad \text{....for node J3}$$

Now, write a Function to solve for J1, J2 and J3 using 'Solve Block' of Mathcad:

$J1 := 1000 \quad J2 := 1000 \quad J3 := 1000$ ...Guess values of Radiosities

Given

$$\frac{Eb1 - J1}{R1} + \frac{J2 - J1}{R12} + \frac{J3 - J1}{R13} = 0 \quad \text{....for node J1}$$

$$\frac{Eb2 - J2}{R2} + \frac{J1 - J2}{R12} + \frac{J3 - J2}{R23} = 0 \quad \text{....for node J2}$$

$$\frac{Eb3 - J3}{R3} + \frac{J1 - J3}{R13} + \frac{J2 - J3}{R23} = 0 \quad \text{....for node J3}$$

$Radiosities(Eb1, Eb2, Eb3, R1, R2, R3, R12, R13, R23) := Find(J1, J2, J3)$

Download free eBooks at bookboon.com

Use the above Function in another Function to calculate the heat transfers:

```
HTransfer_Three_surface_enclosure(A1,A2,A3,T1,T2,T3,eps1,eps2,eps3,F12,F13,F23) :=
R1 ← (1 − eps1)/(A1·eps1)
R2 ← (1 − eps2)/(A2·eps2)
R3 ← (1 − eps3)/(A3·eps3)
R12 ← 1/(A1·F12)
R13 ← 1/(A1·F13)
R23 ← 1/(A2·F23)
Eb1 ← 5.67·10^−8·T1^4
Eb2 ← 5.67·10^−8·T2^4
Eb3 ← 5.67·10^−8·T3^4
M ← Radiosities(Eb1,Eb2,Eb3,R1,R2,R3,R12,R13,R23)
J1 ← M_0
J2 ← M_1
J3 ← M_2
Q12 ← (J1 − J2)/R12
Q13 ← (J1 − J3)/R13
Q23 ← (J2 − J3)/R23
Q1 ← (Eb1 − J1)/R1
Q2 ← (Eb2 − J2)/R2
Q3 ← (Eb3 − J3)/R3
HTransfer ← ("Q12(W)" "Q13(W)" "Q23(W)" "Q1(W)" "Q2(W)" "Q3(W)")
            (Q12     Q13     Q23     Q1     Q2     Q3   )
```

In the above program:

Inputs: Areas, Temps, emissivities and View Factors, as shown above.

Ouputs: Q1, Q2, Q3 (i.e. heat transfer to/from each surface) and Q12, Q13, Q23 (i.e. net heat transfer between respective surfaces)

On the LHS we have the Function statement.

On RHS:

Lines 1,2,3: calculate the three 'surface resistances'

Lines 4,5,6: calculate the three 'space resistances'

Lines 7,8,9: calculate the Emissive powers of three surfaces

Download free eBooks at bookboon.com

Line 10: use the Function, written above, to get three Radiosities J1, J2 and J3 in vector M

Lines 11,12,13: extract the values of J1,J2 and J3

Lines 14,15,16: calculate the various heat transfers

Line 17: return the calculated values in a Matrix

Let us work out a problem using the above Function:

Prob. 5.C.2.2. Consider a cylindrical furnace with R = 1 m, L = 1.25 m as shown. Emissivities and temperatures of surfaces 1, 2 and 3 are: eps1 = 0.8, eps2 = 0.3, eps3 = 0.9, T1 = 750 K, T2 = 450 K and T3 = 400 K respectively. Determine the net rate of radiation to / from each surface.

(b) If surface 3 is black, what are the values of Q1, Q2 and Q3?

(c) For the case (a) plot the variation of Q13 as emissivity of surface 3 varies from 0.1 to 1.

Mathcad Solution:

This is a general, three-surface enclosure, for which the electrical network and the Mathcad Function are written above.



Download free eBooks at bookboon.com

Data:

R := 1 m L := 1.25 m eps1 := 0.8 eps2 := 0.3 eps3 := 0.9

T1 := 750 K T2 := 450 K T3 := 400 K

Calculations:

$A1 := \pi \cdot R^2$ i.e. A1 = 3.142 m^2

$A2 := \pi \cdot R^2$ i.e. A2 = 3.142 m^2

$A3 := 2\pi \cdot R \cdot L$ i.e. A3 = 7.854 m^2

Now, we need View Factors: F12, F13 and F23:

Use the Mathcad Function for View factors for parallel disks, already written:

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

Recollect:

...View factor for coaxial parallel disks:

Define:

$$R_i = \frac{r_i}{L} \qquad R_j = \frac{r_j}{L} \qquad S(R_i, R_j) := 1 + \frac{1 + R_j^2}{R_i^2}$$

$$F_{ij}(R_i, R_j) := \frac{1}{2}\cdot\left[S(R_i, R_j) - \left[S(R_i, R_j)^2 - 4\cdot\left(\frac{R_j}{R_i}\right)^2\right]^{\frac{1}{2}}\right]$$ **...View factor for coaxial parallel disks**

Then, with the above notations:

$$R_i := \frac{R}{L} \qquad R_j := \frac{R}{L}$$

$$F12 := F_{ij}(R_i, R_j)$$

i.e. $F12 = 0.307$ **....View factor from top surface 1 to bottom surface 2**

And,

$F11 + F12 + F13 = 1$ **.... by summation rule for surface 1**

But, $F11 := 0$ ...since surface 1 is Flat

Therefore: $F13 := 1 - F12$

i.e. $F13 = 0.693$ **....View factor from top surface 1 to side surfaces 3**

And, by symmetry: $F23 := F13$

Now, use the Mathcad Function for general, three-surface enclosure:

HTransfer_Three_surface_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F23) =

"Q12(W)"	"Q13(W)"	"Q23(W)"	"Q1(W)"	"Q2(W)"	"Q3(W)"
9.7203×10^3	2.8247×10^4	6.3252×10^3	3.7968×10^4	-3.3951×10^3	-3.4573×10^4

Download free eBooks at bookboon.com

i.e.

$Q1 := HTransfer\_Three\_surface\_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F23)_{1,3}$

or: $Q1 = 3.797 \times 10^{4}$ **W.... heat *leaving* surface 1 .... Ans.**

And:

$Q2 := HTransfer\_Three\_surface\_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F23)_{1,4}$

or: $Q2 = -3.395 \times 10^{3}$ **W.... heat *into* surface 2.... Ans.**

$Q3 := HTransfer\_Three\_surface\_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F23)_{1,5}$

or: $Q3 = -3.457 \times 10^{4}$ **W.... heat *into* surface 3....Ans.**

Check: algebraic sum of Q1+Q2+Q3 should be equal to zero:

i.e. $Q1 + Q2 + Q3 = -1.455 \times 10^{-11}$ **..very nearly equal to zero...Checks.**

Note: In the results of the above Function, heat transfer between surfaces, i.e. Q12, Q13 and Q23 are also available.

(b) If the surface 3 is black, i.e. eps3 = 1:

We have, for surface 3, eps3 = 1. However, if we put eps3 = 1, looking at the Function, we see that R3 will be 0/0, i.e. indeterminate.

To overcome this problem, we write: eps3 = 0.9999, i.e. almost equal to 1, and we get sufficiently accurate results:

So, we write: $eps3 := 0.9999$

Now, use the Mathcad Function for general, three-surface enclosure:

$$HTransfer\_Three\_surface\_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F23) = \begin{pmatrix} "Q12(W)" & "Q13(W)" & "Q23(W)" & "Q1(W)" & "Q2(W)" & "Q3(W)" \\ 9.886 \times 10^{3} & 2.913 \times 10^{4} & 6.834 \times 10^{3} & 3.902 \times 10^{4} & -3.052 \times 10^{3} & -3.596 \times 10^{4} \end{pmatrix}$$

i.e.

$Q1 := HTransfer\_Three\_surface\_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F23)_{1,3}$

or: $Q1 = 3.902 \times 10^{4}$ **W.... heat *leaving* surface 1 .... Ans.**

Download free eBooks at bookboon.com

And:

Q2 := HTransfer_Three_surface_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F2

or: $Q2 = -3.052 \times 10^{3}$ **W.... heat *into* surface 2.... Ans.**

Q3 := HTransfer_Three_surface_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F23

or: $Q3 = -3.596 \times 10^{4}$ **W.... heat *into* surface 3....Ans.**

Check: algebraic sum of Q1+Q2+Q3 should be equal to zero:

i.e. $Q1 + Q2 + Q3 = -7.385 \times 10^{-9}$ **..very nearly equal to zero...Checks.**

Note: In the results of the above Function, heat transfer between surfaces, i.e. Q12, Q13 and Q23 are also available.



Download free eBooks at bookboon.com

Click on the ad to read more

(c) For the case (a), plot the variation of Q1 and Q13 as emissivity of surface 3 varies from 0.1 to 1:

Define the relevant quantities as functions of eps3:

Then:

$$Q1(eps3) := HTransfer\_Three\_surface\_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F23)_{1,3}$$

$$Q12(eps3) := HTransfer\_Three\_surface\_enclosure(A1, A2, A3, T1, T2, T3, eps1, eps2, eps3, F12, F13, F23)_{1,0}$$

$eps3 := (0.1 \quad 0.2 \quad 0.3 \quad 0.4 \quad 0.5 \quad 0.6 \quad 0.7 \quad 0.8 \quad 0.9 \quad 0.999)$ **...define a vector of eps3 values**

(**Note** that we have put eps3 = 0.999 instead of 1, to avoid dividing 0 by 0, as explained earlier).

Compute the Table:

$eps3^T =$

	0
0	0.1
1	0.2
2	0.3
3	0.4
4	0.5
5	0.6
6	0.7
7	0.8
8	0.9
9	0.999

$\left(\overrightarrow{Q1(eps3)}\right)^T =$

	0
0	$1.828 \cdot 10^4$
1	$2.299 \cdot 10^4$
2	$2.66 \cdot 10^4$
3	$2.948 \cdot 10^4$
4	$3.181 \cdot 10^4$
5	$3.374 \cdot 10^4$
6	$3.537 \cdot 10^4$
7	$3.677 \cdot 10^4$
8	$3.797 \cdot 10^4$
9	$3.901 \cdot 10^4$

$\left(\overrightarrow{Q12(eps3)}\right)^T =$

	0
0	$6.61 \cdot 10^3$
1	$7.353 \cdot 10^3$
2	$7.925 \cdot 10^3$
3	$8.378 \cdot 10^3$
4	$8.747 \cdot 10^3$
5	$9.053 \cdot 10^3$
6	$9.311 \cdot 10^3$
7	$9.53 \cdot 10^3$
8	$9.72 \cdot 10^3$
9	$9.884 \cdot 10^3$

Plot the graphs:

$i := 0..9$

Download free eBooks at bookboon.com





==========

Download free eBooks at bookboon.com

Prob. 5.C.2.3. Two parallel plates, 0.5 m × 1 m each, are spaced 0.5 m apart. The plates are at temperatures of 1000 C and 500 C and their emissivities are 0.2 and 0.5 respectively. The plates are located in a large room, the walls of which are at 27 C. The surfaces of the plates facing each other only exchange heat by radiation. Determine the rates of heat lost by each plate and heat gain of the walls by radiation. Use radiation network for solution. Assume shape factor between parallel plates: F12 = F21 = 0.285. [M.U. 1996]

(b) In addition, plot Q1 and Q12 against ε1, for $0.1 < \varepsilon 1 < 0.9$.

**Who is your target group?
And how can we reach them?**

At Bookboon, you can segment the exact right audience for your advertising campaign.

Our eBooks offer in-book advertising spot to reach the right candidate.

Contact us to hear more
kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more



Fig.(a)



Fig.(b)

Fig. Prob.5.C.2.3

Mathcad Solution:

This type of problem is very popular with examiners in the University Question Papers.

Let the plate surfaces be designated as 1 and 2, and the surroundings as 3.

The schematic fig for this three surface enclosure and the Radiation network is shown in the Fig.(a) and (b) below.

We shall first solve this problem in the usual way, from fundamentals.

Download free eBooks at bookboon.com

Then, we shall verify the results using the Mathcad Function for general, three-surface enclosure written earlier.

Since the area A_3 of the room is very large, we can take the surface resistance of A_3 as equal to zero.

i.e. $\frac{1-\varepsilon_3}{A_3 \cdot \varepsilon_3} = 0$

This means that Eb3 = J3, **i.e. a large room is equivalent to a black surface.**

Data:

$A_1 := 0.5$ m^2...area of surface 1 $A_2 := 0.5$ m^2...area of surface 2

$T_1 := 1000 + 273$ K...temp. of surface 1 $T_2 := 500 + 273$ K...temp. of surface 2

$T_3 := 27 + 273$ K...temp. of surface 3 (i.e. room)

$\varepsilon_1 := 0.2$ ..emissivity of surface 1 $\varepsilon_2 := 0.5$ ..emissivity of surface 2

$F_{12} := 0.285$ ...view factor of surface 1 w.r.t. surface 2

$F_{21} := 0.285$ ...view factor of surface 2 w.r.t. surface 1

$\sigma := 5.67 \cdot 10^{-8}$ W/(m^2.K)...Stefan-Boltzmann const.

Calculations:

Now, $F_{11} + F_{12} + F_{13} = 1$ ...by summation rule

But, $F_{11} = 0$ ...since surface 1 is flat and can not 'see' itself.

Therefore, $F_{12} + F_{13} = 1$

And, $F_{13} := 1 - F_{12}$

i.e. $F_{13} = 0.715$ ...view factor of surface 1 w.r.t. surface 3

Similarly, $F_{23} := 0.715$ ...view factor of surface 2 w.r.t. surface 3

Download free eBooks at bookboon.com

Resistances:

$$R_1 := \frac{1-\varepsilon_1}{A_1 \cdot \varepsilon_1} \quad \text{i.e.} \quad R_1 = 8 \quad m^{-2}\text{....surface resistance of surface 1}$$

$$R_2 := \frac{1-\varepsilon_2}{A_2 \cdot \varepsilon_2} \quad \text{i.e.} \quad R_2 = 2 \quad m^{-2}\text{....surface resistance of surface 2}$$

$$R_{12} := \frac{1}{A_1 \cdot F_{12}} \quad \text{i.e.} \quad R_{12} = 7.018 \quad m^{-2}\text{....space resistance between surfaces 1 and 2}$$

$$R_{13} := \frac{1}{A_1 \cdot F_{13}} \quad \text{i.e.} \quad R_{13} = 2.797 \quad m^{-2}\text{....space resistance between surfaces 1 and 3}$$

$$R_{23} := \frac{1}{A_2 \cdot F_{23}} \quad \text{i.e.} \quad R_{23} = 2.797 \quad m^{-2}\text{....space resistance between surfaes 2 and 3}$$

Heat lost by each surface:

$$Q_1 = \frac{E_{b1} - J_1}{R_1} \quad = \text{heat lost by surface 1}$$

and, $$Q_2 = \frac{E_{b2} - J_2}{R_2} \quad = \text{heat lost by surface 2}$$

And, heat gain by surface 3:

$$Q_3 = Q_{13} + Q_{23}$$

i.e. $$Q_3 = \frac{J_1 - J_3}{R_{13}} + \frac{J_2 - J_3}{R_{23}}$$

Therefore, the problem reduces to calculating the radiosities, J_1, J_2 and J_3.

Download free eBooks at bookboon.com

To calculate the radiosities J_1 and J_2, apply Kirchoff's law of electric circuits to nodes J_1 and J_2:

Node J1: $$\frac{E_{b1} - J_1}{R_1} + \frac{J_2 - J_1}{R_{12}} + \frac{E_{b3} - J_1}{R_{13}} = 0$$ ....eqn. (a)

Node J2: $$\frac{J_1 - J_2}{R_{12}} + \frac{E_{b3} - J_2}{R_{23}} + \frac{E_{b2} - J_2}{R_2} = 0$$ ....eqn. (b)

Emissive powers:

$E_{b1} := \sigma \cdot T_1^4$ i.e. $E_{b1} = 1.489 \times 10^5$ W/m^2....for surface 1

$E_{b2} := \sigma \cdot T_2^4$ i.e. $E_{b2} = 2.024 \times 10^4$ W/m^2....for surface 2

$E_{b3} := \sigma \cdot T_3^4$ i.e. $E_{b3} = 459.27$ W/m^2....for surface 3

Note that: $J_3 := E_{b3}$ ...for the large room

Brain power
By 2020, wind could provide one-tenth of our planet's electricity needs. Already today, SKF's innovative know-how is crucial to running a large proportion of the world's wind turbines.
Up to 25 % of the generating costs relate to maintenance. These can be reduced dramatically thanks to our systems for on-line condition monitoring and automatic lubrication. We help make it more economical to create cleaner, cheaper energy out of thin air.
By sharing our experience, expertise, and creativity, industries can boost performance beyond expectations.
Therefore we need the best employees who can meet this challenge!
The Power of Knowledge Engineering
Plug into The Power of Knowledge Engineering.
Visit us at www.skf.com/knowledge
SKF

Download free eBooks at bookboon.com

Click on the ad to read more

To get J_1 and J_2, solve eqns. (a) and (b) simultaneously. To do this, we shall use **'Solve block'** of Mathcad.

First, choose trial (or, guess) values for J_1 and J_2. Then, immediately after 'Given', write the constraints, viz. eqns. (a) and (b). Now, type 'Find (J_1,J_2) = ', and the result appears immediately:

$J_1 := 100 \quad J_2 := 100$ ....trial values

Given

$$\frac{E_{b1} - J_1}{R_1} + \frac{J_2 - J_1}{R_{12}} + \frac{E_{b3} - J_1}{R_{13}} = 0$$

$$\frac{J_1 - J_2}{R_{12}} + \frac{E_{b3} - J_2}{R_{23}} + \frac{E_{b2} - J_2}{R_2} = 0$$

$$\text{Find}(J_1, J_2) = \begin{pmatrix} 3.3476 \times 10^4 \\ 1.5057 \times 10^4 \end{pmatrix}$$

i.e. $J_1 := 3.3476 \cdot 10^4$ W/m^2

and, $J_2 := 1.5057 \cdot 10^4$ W/m^2

Therefore,

Heat lost by each surface:

$$Q_1 := \frac{E_{b1} - J_1}{R_1}$$

i.e. $Q_1 = 1.443 \times 10^4$ **W = heat lost by surface 1...Ans.**

and, $$Q_2 := \frac{E_{b2} - J_2}{R_2}$$

i.e. $Q_2 = 2.594 \times 10^3$ **W = heat lost by surface 2...Ans.**

Download free eBooks at bookboon.com

Now, heat lost by both surfaces 1 and 2 is *gained* by the surroundings; so, heat gained by surroundings = $Q_3 = Q_1 + Q_2$

i.e. $Q_3 := Q_1 + Q_2$

i.e. $Q_3 = 1.702 \times 10^4$ **W = heat gained by surface 3...Ans.**

Verify:

We have: $Q_3 := \left(\frac{J_1 - J_3}{R_{13}} + \frac{J_2 - J_3}{R_{23}} \right)$

i.e. $Q_3 = 1.702 \times 10^4$ **W = heat gained by surface 3...verified.**

Now, let us solve the above problem using the Mathcad Function:

We have the data:

$A_1 := 0.5$ m^2...area of surface 1 $A_2 := 0.5$ m^2...area of surface 2

$T_1 := 1000 + 273$ K...temp. of surface 1 $T_2 := 500 + 273$ K...temp. of surface 2

$T_3 := 27 + 273$ K...temp. of surface 3 (i.e. room)

$\varepsilon_1 := 0.2$ ..emissivity of surface 1 $\varepsilon_2 := 0.5$ ..emissivity of surface 2

$F_{12} := 0.285$ ...view factor of surface 1 w.r.t. surface 2

$F_{21} := 0.285$ ...view factor of surface 2 w.r.t. surface 1

and:

$F_{13} := 0.715$ ...view factor of surface 1 w.r.t. surface 3

For a very large, (black) surrouding, we write:

$A_3 := 10^6$ m^2.... i.e. a very large value

$\varepsilon_3 := 0.9999$ ...for a Black body, emissivity = 1, but we take it as 0.9999 to avoid division by zero, as explained earlier.

Download free eBooks at bookboon.com

Then, applying the Mathcad Function for a general, three-surface enclosure:

$$\text{HTransfer\_Three\_surface\_enclosure}(A_1, A_2, A_3, T_1, T_2, T_3, \varepsilon_1, \varepsilon_2, \varepsilon_3, F_{12}, F_{13}, F_{23}) =$$

"Q12(W)"	"Q13(W)"	"Q23(W)"	"Q1(W)"	"Q2(W)"	"Q3(W)"
2.625×10^3	1.18×10^4	5.219×10^3	1.443×10^4	2.594×10^3	-1.702×10^4

i.e. $Q1 = 1.443 \cdot 10^3$ **W....Ans.**

$Q2 = 2.594 \cdot 10^3$ **W....Ans.**

$Q3 = -1.702 \cdot 10^3$ **W...Ans....*negative sign* indicates that heat is gained by the surface 3, i.e. the surroundings.**

i.e. We get practically the same results, as obtained earlier.

Note how easy it is to solve this problem with the Mathcad Function.

Also, note that we have obtained the values for other heat transfer quantities, i.e. Q12 between surfaces 1 and 2, Q13 between surfaces 1 and 3, and Q23 between surfaces 2 and 3.

Are you looking for **an affordable MBA education?**

Join **American** LIGS University today!

- tuition starting at **$155 / month**
- Interactive **Online education**
- study **without** leaving your home
- programs in **English** or **Russian**

visit www.ligsuniversity.com to find out more!

Download free eBooks at bookboon.com

Click on the ad to read more

In addition:

Plot the variation of Q1, Q12 as e1 varies from 0.1 to 0.9:

$\varepsilon_1 := 0.1, 0.2 .. 0.9$ ....define a range variable

Write Q1, Q12 as functions of ε1:

$Q1(\varepsilon_1) := \text{HTransfer\_Three\_surface\_enclosure}(A_1, A_2, A_3, T_1, T_2, T_3, \varepsilon_1, \varepsilon_2, \varepsilon_3, F_{12}, F_{13}, F_{23})_{1,3}$

$Q12(\varepsilon_1) := \text{HTransfer\_Three\_surface\_enclosure}(A_1, A_2, A_3, T_1, T_2, T_3, \varepsilon_1, \varepsilon_2, \varepsilon_3, F_{12}, F_{13}, F_{23})_{1,0}$

Now, compute the Table:

ε_1 =	$Q1(\varepsilon_1)$ =	$Q12(\varepsilon_1)$ =
0.1	$7.244 \cdot 10^3$	794.817
0.2	$1.443 \cdot 10^4$	$2.625 \cdot 10^3$
0.3	$2.155 \cdot 10^4$	$4.439 \cdot 10^3$
0.4	$2.862 \cdot 10^4$	$6.239 \cdot 10^3$
0.5	$3.562 \cdot 10^4$	$8.023 \cdot 10^3$
0.6	$4.257 \cdot 10^4$	$9.793 \cdot 10^3$
0.7	$4.946 \cdot 10^4$	$1.155 \cdot 10^4$
0.8	$5.629 \cdot 10^4$	$1.329 \cdot 10^4$
0.9	$6.307 \cdot 10^4$	$1.502 \cdot 10^4$

Download free eBooks at bookboon.com

And, plot the results:



==========

Prob. 5.C.2.4. Two parallel plates of size 1 m × 1 m are spaced 0.5 m apart and are located in a very large room, the walls of which are maintained at a temp of 27 C. One plate is maintained at a temp of 900 C and the other at 400 C. Their emissivities are 0.2 and 0.5 respectively. If the plates exchange heat between themselves and surroundings, find the net heat transfer to each plate and to the room. Consider only the plate surfaces facing each other. [VTU – M.Tech. – Dec. 2009–Jan. 2010](b) In addition, plot Q1 and Q12 against ε1, for $0.1 < \varepsilon 1 < 0.9$.

Mathcad Solution:

This problem is identical to the previous problem.

Download free eBooks at bookboon.com

We shall quickly solve it using the Mathcad Function for general, three-surface enclosure:

We have the data:

$A_1 := 1$ m^2...area of surface 1 $A_2 := 1$ m^2...area of surface 2 $L := 0.5$ m

$T_1 := 900 + 273$ K...temp. of surface 1 $T_2 := 400 + 273$ K...temp. of surface 2

$T_3 := 27 + 273$ K...temp. of surface 3 (i.e. room)

$\varepsilon_1 := 0.2$ ..emissivity of surface 1 $\varepsilon_2 := 0.5$ ..emissivity of surface 2

For a very large, (black) surrouding, we write:

$A_3 := 10^6$ m^2.... i.e. a very large value

$\varepsilon_3 := 0.9999$ ...for a Black body, emissivity = 1, but we take it as 0.9999 to avoid division by zero, as explained earlier.

Download free eBooks at bookboon.com

Click on the ad to read more

Now, we need the View factors F12, F13 and F23:

We can use the graphs, or use the Mathcad Function for ***View Factor between parallel, coaxial plates***, written earlier.

Let us recollect the Mathcad Function:

Geometry:



$$\text{F12\_parallel\_rectangles}(X,Y,L) := \left| \begin{array}{l} XX \leftarrow \frac{X}{L} \\ YY \leftarrow \frac{Y}{L} \\ A \leftarrow \frac{2}{\pi \cdot XX \cdot YY} \\ B \leftarrow \ln\left[\sqrt{\frac{\left(1+XX^2\right)\cdot\left(1+YY^2\right)}{1+XX^2+YY^2}}\right] \\ C \leftarrow XX\cdot\left(1+YY^2\right)^{\frac{1}{2}}\cdot\operatorname{atan}\left[\frac{XX}{\left(1+YY^2\right)^{\frac{1}{2}}}\right] \\ D \leftarrow YY\cdot\left(1+XX^2\right)^{\frac{1}{2}}\cdot\operatorname{atan}\left[\frac{YY}{\left(1+XX^2\right)^{\frac{1}{2}}}\right] \\ E \leftarrow XX\cdot\operatorname{atan}(XX) \\ F \leftarrow YY\cdot\operatorname{atan}(YY) \\ F_{12} \leftarrow A\cdot(B+C+D-E-F) \end{array} \right.$$

Download free eBooks at bookboon.com

Then: $F12 := F12\_parallel\_rectangles(1,1,0.5)$

i.e. $F12 = 0.415$ **...View Factor from surface 1 to surface 2**

Also, from **Summation rule** for surface 1:

$F11 + F12 + F13 = 1$

But, $F11 := 0$ ..since it is a Flat surface

Therefore: $F13 := 1 - F12$

i.e. $F13 = 0.585$ **...View Factor from surface 1 to surface 3**

Then, by symmetery: $F23 := F13$ **...View Factor from surface 2 to surface 3**

Now, invoke the Mathcad Function to get various heat transfers:

$HTransfer\_Three\_surface\_enclosure(A_1, A_2, A_3, T_1, T_2, T_3, \varepsilon_1, \varepsilon_2, \varepsilon_3, F12, F13, F23) =$

"Q12(W)"	"Q13(W)"	"Q23(W)"	"Q1(W)"	"Q2(W)"	"Q3(W)"
5.891×10^3	1.4592×10^4	6.2961×10^3	2.0483×10^4	405.1572	-2.0888×10^4

i.e. $Q1 = 20483$ **W....heat leaving surface 1....Ans.**

$Q2 = 405.1572$ **W....heat leaving surface 2....Ans.**

$Q3 = -20888$ **W....heat coming *into* surface 3....Ans....**
..... negative ign indicates heat in to the surface.

(b) In addition, plot Q1 and Q12 against ε1, for 0.1 < ε1 < 0.9:

$\varepsilon_1 := 0.1, 0.2 .. 0.9$ ....define a range variable

Write Q1, Q12 as functions of ε1:

Download free eBooks at bookboon.com

$$Q1(\varepsilon_1) := \text{HTransfer\_Three\_surface\_enclosure}(A_1, A_2, A_3, T_1, T_2, T_3, \varepsilon_1, \varepsilon_2, \varepsilon_3, F12, F13, F23)_{1,3}$$

$$Q12(\varepsilon_1) := \text{HTransfer\_Three\_surface\_enclosure}(A_1, A_2, A_3, T_1, T_2, T_3, \varepsilon_1, \varepsilon_2, \varepsilon_3, F12, F13, F23)_{1,0}$$

Now, compute the Table:

ε_1 =	$Q1(\varepsilon_1)$ =	$Q12(\varepsilon_1)$ =
0.1	$1.0337 \cdot 10^4$	$2.2377 \cdot 10^3$
0.2	$2.0483 \cdot 10^4$	$5.891 \cdot 10^3$
0.3	$3.0442 \cdot 10^4$	$9.4772 \cdot 10^3$
0.4	$4.022 \cdot 10^4$	$1.2998 \cdot 10^4$
0.5	$4.9822 \cdot 10^4$	$1.6456 \cdot 10^4$
0.6	$5.9253 \cdot 10^4$	$1.9851 \cdot 10^4$
0.7	$6.8517 \cdot 10^4$	$2.3187 \cdot 10^4$
0.8	$7.7618 \cdot 10^4$	$2.6464 \cdot 10^4$
0.9	$8.656 \cdot 10^4$	$2.9684 \cdot 10^4$



Download free eBooks at bookboon.com

Click on the ad to read more

And, plot the results:



==========

Prob. 5.C.2.5. Consider ***two special cases*** of 3-surface enclosures, viz.

i. Two black surfaces, connected by a third refractory surface, and
ii. Two gray surfaces, surrounded by a third re-radiating surface

Download free eBooks at bookboon.com

Let us write Mathcad Functions for both the above cases:

Case 1: Two black surfaces connected by a reradiating surface: ex: top and bottom surfaces of a cylindrical furnce and its reradiating walls: (Q_R=0, E_{bR} = J_R)



Fig.(a)



Fig.(b)

Fig. (a) shows the radiation network for this case. The radiation network is drawn very easily by *remembering the usual principles*: for a black surface, the surface resistance is zero, i.e. E_b = J. For a re-radiating surface too, E_b = J; further, for a re-radiating surface, Q = 0. Between two given surfaces, the radiosity potentials are connected by the respective space resistances, as shown. The system reduces to a series-parallel circuit of resistances as shown in Fig. (b).

Q_{12} is the net radiant heat transferred between surfaces 1 and 2.

TR is the temp of re-radiating surface.

$$Q_{12} = \sigma \cdot \left(T_1^4 - T_2^4\right) \cdot \left[A_1 \cdot F_{12} + \frac{1}{\left(\frac{1}{A_1 \cdot F_{1R}} + \frac{1}{A_2 \cdot F_{2R}}\right)}\right] \quad \text{.....(13.66)}$$

Download free eBooks at bookboon.com

$$
\begin{aligned}
&\text{Q12\_TwoBlack\_OneRerad}(A1, A2, F12, F1R, F2R, T1, T2) := \\
&\quad R12 \leftarrow \frac{1}{A1 \cdot F12} \\
&\quad R1R \leftarrow \frac{1}{A1 \cdot F1R} \\
&\quad R2R \leftarrow \frac{1}{A2 \cdot F2R} \\
&\quad Eb1 \leftarrow 5.67 \cdot 10^{-8} \cdot T1^{4} \\
&\quad Eb2 \leftarrow 5.67 \cdot 10^{-8} \cdot T2^{4} \\
&\quad Rtot \leftarrow \left(\frac{1}{R12} + \frac{1}{R1R + R2R} \right)^{-1} \\
&\quad Q12 \leftarrow \frac{Eb1 - Eb2}{Rtot} \\
&\quad JR \leftarrow \frac{\frac{Eb1}{R1R} + \frac{Eb2}{R2R}}{\frac{1}{R1R} + \frac{1}{R2R}} \\
&\quad Q1R \leftarrow (Eb1 - JR) \cdot \left(\frac{1}{R1R} + \frac{1}{R12 + R2R} \right) \\
&\quad Q2R \leftarrow (Eb2 - JR) \cdot \left(\frac{1}{R2R} + \frac{1}{R12 + R2R} \right) \\
&\quad TR \leftarrow \left(\frac{JR}{5.67 \cdot 10^{-8}} \right)^{0.25} \\
&\quad \begin{pmatrix} \text{"Q12(W)"} & \text{"Q1R(W)"} & \text{"Q2R(W)"} & \text{"TR(K)"} \\ Q12 & Q1R & Q2R & TR \end{pmatrix}
\end{aligned}
$$

Case 2. Two gray surfaces surrounded by a third reradiating surface: ex: top and bottom surfaces of a cylindrical furnce and its reradiating walls, or an equilateral duct etc.:

Note: For reradiating surface 3, $Q_3 = 0$, $E_{b3} = J_3$

Download free eBooks at bookboon.com



Fig.(a)



Fig.(b)

Here, we have:

$$Q_3 = 0$$

i.e. $$\frac{E_{b3} - J_3}{\left(\frac{1-\varepsilon_3}{A_3 \cdot \varepsilon_3}\right)} = 0$$

i.e.

$$E_{b3} = J_3$$

i.e. once the radiosity of the re-radiating surface is known, its temperature can easily be calculated, since $E_{b3} = \sigma . T_3^4$. Further, note that T_3 is independent of the emissivity of surface 3.

Download free eBooks at bookboon.com

```
Q12_TwoGray_OneRerad(A1, A2, F12, F13, F23, eps1, eps2, T1, T2) :=
    R12 ← 1/(A1·F12)
    R13 ← 1/(A1·F13)
    R23 ← 1/(A2·F23)
    R1 ← (1 − eps1)/(A1·eps1)
    R2 ← (1 − eps2)/(A2·eps2)
    Eb1 ← 5.67·10^−8·T1^4
    Eb2 ← 5.67·10^−8·T2^4
    Q3 ← 0
    Rtot ← R1 + (1/(1/R12 + 1/(R13 + R23))) + R2
    Q1 ← (Eb1 − Eb2)/Rtot
    Q2 ← −Q1
    J1 ← Eb1 − Q1·R1
    J2 ← Eb2 + Q1·R2
    J3 ← ((J1/R13 + J2/R23)/(1/R13 + 1/R23))
    T3 ← (J3/(5.67·10^−8))^0.25
    ("Q1(W)"  "Q2(W)"  "Q3(W)"  "T3(K)")
     (Q1      Q2       Q3       T3   )
```

Prob. 5.C.2.6. Two black discs, each of 500 mm dia, are placed directly opposite at a distance 1 m apart. The discs are maintained at 1000 K and 500 K respectively. Calculate the hat flow between the discs if they are connected by a cylindrical refractory surface. [P.U.]

(b) Also, plot Q12 against T1.

Download free eBooks at bookboon.com

Mathcad Solution:



Data:

R := 0.5 m L := 1 m eps1 := 1 eps2 := 1

T1 := 1000 K T2 := 500 K

Calculations:

$A1 := \pi \cdot R^2$ i.e. A1 = 0.7854 m^2

$A2 := \pi \cdot R^2$ i.e. A2 = 0.7854 m^2

$A3 := 2\pi \cdot R \cdot L$ i.e. A3 = 3.1416 m^2

Now, we need View Factors: F12, F13 and F23:

Use the Mathcad Function for View factors for parallel disks, already written:

...View factor for coaxial parallel disks:

Define:

$$R_i = \frac{r_i}{L} \qquad R_j = \frac{r_j}{L} \qquad S(R_i, R_j) := 1 + \frac{1 + R_j^2}{R_i^2}$$

$$F_{ij}(R_i, R_j) := \frac{1}{2} \cdot \left[S(R_i, R_j) - \left[S(R_i, R_j)^2 - 4 \cdot \left(\frac{R_j}{R_i} \right)^2 \right]^{\frac{1}{2}} \right]$$ ...View factor for coaxial parallel disks

Download free eBooks at bookboon.com

Then, with the above notations:

$$R_i := \frac{R}{L} \qquad R_j := \frac{R}{L}$$

$$F12 := F_{ij}(R_i, R_j)$$

i.e. $F12 = 0.1716$ **....View factor from top surface 1 to bottom surface 2**

And,

$F11 + F12 + F1R = 1$ **.... by summation rule for surface 1**

But, $F11 := 0$ ...since surface 1 is Flat

Therefore: $F1R := 1 - F12$

i.e. $F1R = 0.8284$ **....View factor from top surface 1 to side surfaces 3**

By symmetry: $F2R := F1R$

Now, use the Mathcad Function for two black surfaces, connected by a re-radiating surface:

$$Q12\_TwoBlack\_OneRerad(A1, A2, F12, F1R, F2R, T1, T2) = \begin{pmatrix} "Q12(W)" & "Q1R(W)" & "Q2R(W)" & "TR(K)" \\ 2.4456 \times 10^4 & 2.026 \times 10^4 & -2.026 \times 10^4 & 853.7382 \end{pmatrix}$$

i.e.

$Q12 = 24456$ **W....Net radn. between surfaces 1 and 2 .... Ans.**

$TR = 853.74$ **K....temp. of Rearadiating surface .... Ans.**

(b) Also, plot Q12, TR against T1 as T1 varies from 600 K to 1300 K:

$T1 := 600, 650 .. 1300$ ....define a range variable

$Q12(T1) := Q12\_TwoBlack\_OneRerad(A1, A2, F12, F1R, F2R, T1, T2)_{1,0}$ ...define Q12 as a function of T1

$TR(T1) := Q12\_TwoBlack\_OneRerad(A1, A2, F12, F1R, F2R, T1, T2)_{1,3}$ ...define TR as a function of T1

Download free eBooks at bookboon.com

Compute the Table:

T1 =	Q12(T1) =	TR(T1) =
600	$1.7504 \cdot 10^3$	556.704
650	$3.0262 \cdot 10^3$	589.1821
700	$4.6329 \cdot 10^3$	623.677
750	$6.6235 \cdot 10^3$	659.744
800	$9.0545 \cdot 10^3$	697.0292
850	$1.1987 \cdot 10^4$	735.2581
900	$1.5485 \cdot 10^4$	774.2199
950	$1.9617 \cdot 10^4$	813.7541
1000	$2.4456 \cdot 10^4$	853.7382
1050	$3.0078 \cdot 10^4$	894.0787
1100	$3.6563 \cdot 10^4$	934.7034
1150	$4.3995 \cdot 10^4$	975.5566
1200	$5.2462 \cdot 10^4$	$1.0166 \cdot 10^3$
1250	$6.2057 \cdot 10^4$	$1.0578 \cdot 10^3$
1300	$7.2875 \cdot 10^4$	$1.0991 \cdot 10^3$

be > your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

And, plot the results:





==========

Prob. 5.C.2.7. Solve the above Problem if the emissivities of top and bottom disks are 0.8 and 0.4 respectively. Rest of the data are the same.

Mathcad Solution:

This is the case of two gray surfaces surrounded by a re-radiating surface.

So, we shall use the Mathcad Function written above.

Download free eBooks at bookboon.com

Data:

$R := 0.5\ m$ $L := 1\ m$ $eps1 := 0.8$ $eps2 := 0.4$

$T1 := 1000\ K$ $T2 := 500\ K$

Calculations:

$A1 := \pi \cdot R^2$ i.e. $A1 = 0.7854$ m^2

$A2 := \pi \cdot R^2$ i.e. $A2 = 0.7854$ m^2

$A3 := 2\pi \cdot R \cdot L$ i.e. $A3 = 3.1416$ m^2

And: $F12 := 0.1716$ $F1R := 0.8284$ $F2R := F1R$ ..calculated in previous problem

Now, we use the Mathcad Function for two gray surfaces surrounded by a re-radiating surface:

$$Q12\_TwoGray\_OneRerad(A1, A2, F12, F1R, F2R, eps1, eps2, T1, T2) = \begin{pmatrix} "Q1(W)" & "Q2(W)" & "Q3(W)" & "T3(K)" \\ 1.2076 \times 10^4 & -1.2076 \times 10^4 & 0 & 914.9328 \end{pmatrix}$$

i.e.

$Q1 = 12076$ **W....Net radn. at surface 1 .... Ans.**

$Q2 = -Q1 = -12076$ **W....Net radn. at surface 2 ..negative sign indicates heat flow *into* the surface.. Ans.**

$TR = 914.93$ **K....temp. of Rearadiating surface .... Ans.**

(b) Also, plot Q1 and T3 (i.e. temp of re-radiating surface) as T1 varies from 600 K to 1300 K, rest of the conditions being the same:

Define Q1 as a function of T1:

$$Q1(T1) := Q12\_TwoGray\_OneRerad(A1, A2, F12, F1R, F2R, eps1, eps2, T1, T2)_{1,0}$$

Define T3 as a function of T1:

$$T3(T1) := Q12\_TwoGray\_OneRerad(A1, A2, F12, F1R, F2R, eps1, eps2, T1, T2)_{1,3}$$

$T1 := 600, 650 .. 1300$ ....define a range variable

Download free eBooks at bookboon.com

Compute the Table:

T1 =	Q1(T1) =	T3(T1) =
600	864.346	573.5056
650	$1.4943 \cdot 10^3$	613.2966
700	$2.2877 \cdot 10^3$	654.4171
750	$3.2707 \cdot 10^3$	696.5168
800	$4.4712 \cdot 10^3$	739.3428
850	$5.9191 \cdot 10^3$	782.7127
900	$7.6464 \cdot 10^3$	826.4946
950	$9.6869 \cdot 10^3$	870.5917
1000	$1.2076 \cdot 10^4$	914.9328
1050	$1.4852 \cdot 10^4$	959.4648
1100	$1.8055 \cdot 10^4$	$1.0041 \cdot 10^3$
1150	$2.1725 \cdot 10^4$	$1.049 \cdot 10^3$
1200	$2.5906 \cdot 10^4$	$1.0939 \cdot 10^3$
1250	$3.0644 \cdot 10^4$	$1.1388 \cdot 10^3$
1300	$3.5986 \cdot 10^4$	$1.1839 \cdot 10^3$

And, plot the results:



Download free eBooks at bookboon.com



==========

The Wake
the only emission we want to leave behind
Low-speed Engines Medium-speed Engines Turbochargers Propellers Propulsion Packages PrimeServ
The design of eco-friendly marine power and propulsion solutions is crucial for MAN Diesel & Turbo.
Power competencies are offered with the world's largest engine programme – having outputs spanning from 450 to 87,220 kW per engine. Get up front!
Find out more at www.mandieselturbo.com
Engineering the Future – since 1758.
MAN Diesel & Turbo
MAN

Download free eBooks at bookboon.com

Click on the ad to read more

Prob. 5.C.2.8. Two co-axial cylinders of 0.4 m and 1 m dia. are 1 m long. The annular top and bottom surfaces are well insulated and act as re-radiating surfaces. The inner surface is at 1000 K and has an emissivity of 0.6. The outer surface is maintained at 400 K and its emissivity is 0.4.

i) Determine the heat exchange between the surfaces
ii) If the annular base surfaces are open to the surroundings at 300 K, determine the radiant heat exchange.

If the outer cylinder is surface 2, take F21= 0.25 and F22= 0.27. [M.U. Dec. 1998]

Mathcad Solution:



Fig.(a)



Fig.(b)

Fig.Prob.5.C.2.8

See Fig. above. Let the inner surface be denoted by 1, outer surface by 2, and the two annular surfaces by 3. Then, surfaces 1, 2 and 3 form an enclosure. And, the radiation network will look as shown in the fig.(b).

Download free eBooks at bookboon.com

Data:

$D_1 := 0.4$ m. $D_2 := 1$ m. $L := 1$ m..

$T_1 := 1000$ K...temp. of inner surface (1) $T_2 := 400$ K...temp. of outer surface (2)

$\varepsilon_1 := 0.6$ ..emissivity of surface 1 $\varepsilon_2 := 0.4$ ..emissivity of surface 2

$F_{21} := 0.25$ ...view factor of surface 2 w.r.t. surface 1

$F_{22} := 0.27$ ...view factor of surface 2 w.r.t. itself

$\sigma := 5.67 \cdot 10^{-8}$ W/(m^2.K)...Stefan-Boltzmann const.

Calculations:

Areas:

$A_1 := \pi \cdot D_1 \cdot L$ i.e. $A_1 = 1.2566$ m^2....surface area of inner cylinder 1

$A_2 := \pi \cdot D_2 \cdot L$ i.e. $A_2 = 3.1416$ m^2....surface area of outer cylinder 2

To find F_{12}:

$F_{11} := 0$ ...since surface 1 is convex, and does not 'see' itself.

Then, $F_{12} := \frac{A_2}{A_1} \cdot F_{21}$ ...by reciprocity

i.e. $F_{12} = 0.625$ ..view factor from surface 1 to surface 2

Also, $F_{11} + F_{12} + F_3 = 1$ ....by summation rule

i.e. $F_{13} := 1 - (F_{11} + F_{12})$

i.e. $F_{13} = 0.375$ ..view factor from surface 1 to surface 3

Also, $F_{21} + F_{22} + F_{23} = 1$ ...by summaion rule

i.e. $F_{23} := 1 - (F_{21} + F_{22})$

i.e. $F_{23} = 0.48$ ..view factor from surface 2 to surface 3

Download free eBooks at bookboon.com

Case(i): When both the annular surfaces act as re-radiating surfaces:

Now, we use the Mathcad Function for two gray surfaces surrounded by a re-radiating surface:

$$Q12\_TwoGray\_OneRerad(A_1, A_2, F_{12}, F_{13}, F_{23}, e_1, e_2, T_1, T_2) = \begin{pmatrix} \text{"Q1(W)"} & \text{"Q2(W)"} & \text{"Q3(W)"} & \text{"T3(K)"} \\ 2.936 \times 10^4 & -2.936 \times 10^4 & 0 & 785.4289 \end{pmatrix}$$

i.e. $Q1 = 2.936 \cdot 10^4$ **W....heat exchange between the surfaces...Ans.**

$T3 = 785.43$ **K....temp of re-radiating surface...Ans.**

Case(ii): When both the annular surfaces are open to surroundings at 300 K:

Now, $T_3 := 300$ K....temp. of surroundings

Also: $A_3 := 10^6$ m^2.... area of surroundings....take a very large value

See the light!
The sooner you realize we are right, the sooner your life will get better!

A bit over the top? Yes we know!

We are just that sure that we can make your media activities more effective.

Get "Bookboon's Free Media Advice"
Email kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

$\varepsilon_3 := 0.9999$ ...emissivity of surroundings, equal to 1 for black surface, but take it as 0.9999 to avoid division by zero

Now, apply the Mathcad Function for general, three-surface enclosure:

$$\text{HTransfer\_Three\_surface\_enclosure}(A_1, A_2, A_3, T_1, T_2, T_3, \varepsilon_1, \varepsilon_2, \varepsilon_3, F_{12}, F_{13}, F_{23}) =$$

"Q12(W)"	"Q13(W)"	"Q23(W)"	"Q1(W)"	"Q2(W)"	"Q3(W)"
2.2486×10^4	1.6705×10^4	1.0283×10^4	3.9191×10^4	-1.2203×10^4	-2.6988×10^4

i.e. We get:

$Q1 := 3.9191 \cdot 10^4$ **W....net heat transfer from surface 1 ... Ans.**

$Q2 := -1.2203 \cdot 10^4$ **W....net heat transfer from surface 2 ... Ans.**

$Q3 := -2.6988 \cdot 10^4$ **W....net heat transfer from surface 3 ... Ans.**

Verify: $Q2 + Q3 = -3.9191 \times 10^4$ **..W**

i.e. heat leaving surface 1 (= Q1) is equal to heat received by surface 2 and the surroundings...verified.

While using the above Function, note that we have obtained other heat transfers too, i.e. Q12 between surfaces 1 and 2, Q13 between surfaces 1 and 3, and, Q23 between surfaces 2 and 3.

==========

Prob. 5.C.2.9. Two parallel plates, 0.5 m × 1 m each, are spaced 0.5 m apart. The plates are at temperatures of 1000 C and 500 C and their emissivities are 0.2 and 0.5 respectively. The plates are located in a large room, the walls of which are at 27 C. The surfaces of the plates facing each other only exchange heat by radiation. Determine the rates of heat lost by each plate and heat gain of the walls by radiation. Use radiation network for solution. Assume shape factor between parallel plates: $F_{12} = F_{21} = 0.285$. [M.U. 1996]

Download free eBooks at bookboon.com

(b) Also, plot Q1 and Q3 as epsilon1 varies from 0.1 to 0.9



Fig.(a)



Fig.(b)

Fig.Prob.5.C.2.9

This problem is the same as Prob.5.C.2.3, which was solved with Mathcad.

However, now we shall solve it with EES:

EES Solution:

The schematic fig. and the radiation network are shown in Fig (a) and (b) above.

We shall, first write an EES PROCEDURE to calculate the Emissive powers and Resistances involved, to reduce labour; then, we shall use that Procedure in a Main EES program to find out the Radiosities by applying the Kirchoff's Law to the three nodes J1, J2 and J3 and solve the resulting three equations simultaneously to get J1, J2 and J3. Then, the heat transfers are easily calculated by applying the Ohm's Law between any two given radiosity potentials.

Download free eBooks at bookboon.com

The EES Procedure is given below. Read the comments in the program:

```
$UnitSystem SI Pa J K

PROCEDURE
HTrans_Three_surface_enclosure(A_1,A_2,A_3,T_1,T_2,T_3,eps_1,eps_2,eps_3,F_12,F_13,F_23:Eb_
1,Eb_2,Eb_3,R_1,R_2,R_3,R_12,R_13,R_23)

{
Inputs: A1, A2 ,…etc

Outputs: Emissive powers: Eb_1,Eb_2,Eb_3 (W/m^2), and
         Surface and Space resistances: R_1, R_2, R_3, R_12, R_13, R_23 (1/m^2)
}
"Radiation Heat transfer in Three-Zone enclosure:"
"Note: For a insulated/re-radiating surface: Q_i = 0, and J_i = Eb_i (= sigma * T_i^4)"
"For a black surface: R_i = 0; so, J_i = Eb_i "

sigma := 5.67e-08 "[W/m^2-K^4]….Stefan Boltzmann const."
```

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

```
Eb_1 := sigma * T_1^4
Eb_2 := sigma * T_2^4
Eb_3 := sigma * T_3^4

R_1 := (1 – eps_1)/(A_1 * eps_1)        "surface resist of surface 1"
R_2 := (1 – eps_2)/(A_2 * eps_2)        "surface resist of surface 2"
R_3 := (1 – eps_3)/(A_3 * eps_3)        "surface resist of surface 2"

R_12 := 1/(A_1 * F_12)                  "space resist bet surfaces 1 and 2"
R_13 := 1/(A_1 * F_13)                  "space resist bet surfaces 1 and 3"
R_23 := 1/(A_2 * F_23)                  "space resist bet surfaces 2 and 3"

END

"=========================================================================="
```

Now, to solve the above problem:

"Data:"

```
A_1 = 0.5 [m^2]
A_2 = 0.5 [m^2]
A_3 = 1e10 [m^2] "…very large room"

T_1 = 1273 [K]
T_2 = 773 [K]
T_3 = 300 [K]

eps_1 = 0.2 "emissivity of plate 1"
eps_2 = 0.5 "emissivity of plate 2"
eps_3 = 0.9999 "…emissivity of surroundings = 1, taken as 0.9999 to avoid division by zero"

F_12 = 0.285 "…View Factor from surface 1 to 2… by data"
F_21 = 0.285 "…View Factor from surface 2 to 1… by data"
F_11 = 0 "…since surface 1 is flat"
"F_11 + F_12 + F_13 = 1 … by Summation rule for surface 1"

"Therefore:"

F_13 = 1- F_12 "…View Factor from surface 1 to 3"
```

Download free eBooks at bookboon.com

"Similarly, for surface 2, F_22 = 0, and F_21 + F_22 + F_23 = 1 by Summation rule for surface 2, and we get:"

F_23 = 1- F_21 "…View Factor from surface 2 to 3"

"Now, calculate various Emissive powers and Resistances, using the EES PROCEDURE:"

CALL HTrans_Three_surface_enclosure(A_1,A_2,A_3,T_1,T_2,T_3,eps_1,eps_2,eps_3,F_12,F_13,F_23:Eb_1,Eb_2,Eb_3,R_1,R_2,R_3,R_12,R_13,R_23)

"Kirchoff's Law for Nodes J_1, J_2 and J_3:"

"For J_1:" (Eb_1 – J_1)/R_1 + (J_2 – J_1)/R_12 + (J_3 – J_1)/R_13 = 0
"For J_2:" (Eb_2 – J_2)/R_2 + (J_1 – J_2)/R_12 + (J_3 – J_2)/R_23 = 0
"For J_3:" (Eb_3 – J_3)/R_3 + (J_1 – J_3)/R_13 + (J_2 – J_3)/R_23 = 0

"Net heat transfer from each surface:"

Q_1 = (Eb_1 – J_1)/R_1
Q_2 = (Eb_2 – J_2)/R_2
Q_3 = (Eb_3 – J_3)/R_3

"Net heat transfer between surface 1 and 2:"

Q_12 = (J_1 – J_2)/R_12

"Net heat transfer between surface 1 and 3:"

Q_13 = (J_1 – J_3)/R_13

"Net heat transfer between surface 2 and 3:"

Q_23 = (J_2 – J_3)/R_23

"Check : Q_1 + Q_2 + Q_3 = 0 "

SumQ1Q2Q3 = Q_1 + Q_2 + Q_3

Download free eBooks at bookboon.com

Results:

Main | HTrans_Three_surface_enclosure

Unit Settings: SI K Pa J mass deg

A_1 = 0.5 [m^2]	A_2 = 0.5 [m^2]	A_3 = 1.000E+10 [m^2]
Eb_1 = 148901 [W/m^2]	Eb_2 = 20244 [W/m^2]	Eb_3 = 459.3 [W/m^2]
eps_1 = 0.2	eps_2 = 0.5	eps_3 = 0.9999
F_{11} = 0 [-]	F_{12} = 0.285 [-]	F_{13} = 0.715 [-]
F_{21} = 0.285 [-]	F_{23} = 0.715 [-]	**J_1 = 33476** [W/m^2]
J_2 = 15057 [W/m^2]	**J_3 = 459.3** [W/m^2]	Q_1 = 14428 [W]
Q_{12} = 2625 [W]	Q_{13} = 11803 [W]	Q_2 = 2594 [W]
Q_{23} = 5219 [W]	Q_3 = -17022 [W]	R_1 = 8 [$1/m^2$]
R_{12} = 7.018 [$1/m^2$]	R_{13} = 2.797 [$1/m^2$]	R_2 = 2 [$1/m^2$]
R_{23} = 2.797 [$1/m^2$]	R_3 = 1.000E-14 [$1/m^2$]	SumQ1Q2Q3 = -0.0001729 [W]
T_1 = 1273 [K]	T_2 = 773 [K]	T_3 = 300 [K]

Main | HTrans_Three_surface_enclosure

Local variables in Procedure HTrans_Three_surface_enclosure (1 call, 0.00 sec)

A_1=0.5 [m^2]	A_2=0.5 [m^2]	A_3=1.000E+10 [m^2]
Eb_1 =148901 [W/m^2]	Eb_2 =20244 [W/m^2]	Eb_3 =459.3 [W/m^2]
eps_1=0.2	eps_2=0.5	eps_3=0.9999
F_{12}=0.285	F_{13}=0.715	F_{23}=0.715
R_1 =8 [$1/m^2$]	R_{12}=7.018 [$1/m^2$]	R_{13}=2.797 [$1/m^2$]
R_2 =2 [$1/m^2$]	R_{23}=2.797 [$1/m^2$]	R_3 =1.000E-14 [$1/m^2$]
σ =5.670E-08 [W/m^2K^4]	T_1=1273 [K]	T_2=773 [K]
T_3=300 [K]		

Thus:

Heat leaving surface 1 = Q1 = 14428 W …. Ans.

Heat leaving surface 2 = Q2 = 2594 W … Ans.

Heat received by surface 3, i.e. ambient = Q3 = -17022 W … Ans. (negative sign indicates that heat is going *into* the surface).

Also, check: Q1 + Q2 + Q3 = 0 (which is satisfied… see SumQ1Q2Q3 = -0.0001729 = almost zero)

In addition, values of radiosities J1, J2 and J3, and also the various resistances, and heat transfers between surfaces, viz. Q12, Q13 and Q23 are also calculated.

Download free eBooks at bookboon.com

Now, plot Q1 and Q3 as epsilon1 varies from 0.1 to 0.9:

First, produce the Parametric Table:

Table 1

1..9	1 eps_1	2 Q_1 [W]	3 Q_2 [W]	4 Q_3 [W]	5 SumQ1Q2Q3 [W]
Run 1	0.1	7244	3661	-10905	-0.001361
Run 2	0.2	14428	2594	-17022	0.0007215
Run 3	0.3	21552	1536	-23087	-0.0006374
Run 4	0.4	28616	486.5	-29102	-0.000599
Run 5	0.5	35622	-554.1	-35068	-0.001149
Run 6	0.6	42570	-1586	-40983	-0.0007688
Run 7	0.7	49460	-2610	-46851	0.0002317
Run 8	0.8	56295	-3625	-52670	-0.000083
Run 9	0.9	63073	-4632	-58442	0.0004825

Note in the above Table that:

i) **For eps1 = > 0.5, Q2 is –ve, i.e. surface 2 receives heat**

ii) **Q3 is the heat received by the ambient (-ve)**

iii) **Sum of Q1, Q2 and Q3 is equal to almost zero, as it should be**



Download free eBooks at bookboon.com

Click on the ad to read more

And, Plot the results:





==========

Prob. 5.C.2.10. A square room, 3 m × 3 m, has a floor heated to 27 C and has a ceiling at 10 C. Walls are perfectly insulated. Height of room is 2.5 m. Emissivity of all surfaces is 0.8. Determine:

i) Net heat transfer from the ceiling
ii) Net heat transfer between ceiling and floor, and
iii) Temp of the walls [M.U.]

(b) Also, plot the variation of Q1 and T3 as eps1 varies from 0.1 to 0.9:

Download free eBooks at bookboon.com

EES Solution:

This is a three-surface enclosure problem.

Important: Walls act as re-radiating surfaces, i.e. Eb_3 = J3, and Q_3 = 0.

Radiation network is shown below:



Fig.(b)

Let ceiling be designated as surface 1, floor as surface 2, and the surrounding walls as surface 3.

We shall use the EES PROCEDURE written above to calculate Emissive powers, various resistance etc.

We shall also use the EES Function written earlier *to determine the View Factor F_12 between the ceiling and the floor.*

"Data:"

A_1 = 9 [m^2]"….area of ceiling"
A_2 = 9 [m^2]"…area of floor"
A_3 = 30 [m^2] "…area of 4 walls"

T_1 = 283 [K]"…temp of ceiling, by data"
T_2 = 300 [K]"…temp of floor, by data"
{T_3 = …to be found out}

sigma = 5.67E-08 [W/m^2-K^4]"…Stefan – Boltzmann constant"

eps_1 = 0.8 "emissivity of ceiling, i.e. surface 1"
eps_2 = 0.8 "emissivity of floor, i.e. surface 2"
eps_3 = 0.8 "…emissivity of surrounding walls, i.e. surface 3"

Download free eBooks at bookboon.com

"Determine View Factors: F_12, F_13 etc."

"Use the EES Function written earlier for parallel rectangles to get F_12:"



"We have: for the ceiling and floors: X = 3 m, Y = 3 m, L = 2.5 m"

X = 3 [m]
Y = 3 [m]
L = 2.5 [m]

F_12 = F12_parallel_rectangles(X, Y, L) "…View Factor from surface 1 to 2…."

F_21 = F_12"…View Factor from surface 2 to 1… by symmetry"

F_11 = 0 "…since surface 1 is flat"

"F_11 + F_12 + F_13 = 1 … by Summation rule for surface 1"

"Therefore:"

F_13 = 1- F_12 "…View Factor from surface 1 to 3"

"Similarly, for surface 2, F_22 = 0 , and F_21 + F_22 + F_23 = 1 by Summation rule for surface 2, and we get:"

F_23 = 1- F_21 "…View Factor from surface 2 to 3"

"Now, calculate various Emissive powers and Resistances, using the EES PROCEDURE:"

CALL

HTrans_Three_surface_enclosure(A_1,A_2,A_3,T_1,T_2,T_3,eps_1,eps_2,eps_3,F_12,F_13,F_23:Eb_1,Eb_2,Eb_3,R_1,R_2,R_3,R_12,R_13,R_23)

Download free eBooks at bookboon.com

"Kirchoff's Law for Nodes J_1, J_2 and J_3:"

"For J_1:" (Eb_1 – J_1)/R_1 + (J_2 – J_1)/R_12 + (J_3 – J_1)/R_13 = 0
"For J_2:" (Eb_2 – J_2)/R_2 + (J_1 – J_2)/R_12 + (J_3 – J_2)/R_23 = 0
"For J_3:" (J_1 – J_3)/R_13 + (J_2 – J_3)/R_23 = 0

Eb_3 = J_3 "….since surface 3 is re-radiating"

"Also:"

Eb_3 = sigma * T3 ^4 "[W/m^2]…by definition of Eb"

"Net heat transfer from each surface:"

Q_1 = (Eb_1 – J_1)/R_1"[W]…net heat transfer from surface 1"

Q_2 = (Eb_2 – J_2)/R_2"[W]…net heat transfer from surface 2"

Q_3 = (Eb_3 – J_3)/R_3"[W]…net heat transfer from surface 3"

Who is your target group?
And how can we reach them?
At Bookboon, you can segment the exact right audience for your advertising campaign.
Our eBooks offer in-book advertising spot to reach the right candidate.

Contact us to hear more
kbm@bookboon.com
bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com
Download free eBooks at bookboon.com
Click on the ad to read more

"Net heat transfer between surface 1 and 2:"

Q_12 = (J_1 – J_2)/R_12 "[W]"

"Net heat transfer between surface 1 and 3:"

Q_13 = (J_1 – J_3)/R_13 "[W]"

"Net heat transfer between surface 2 and 3:"

Q_23 = (J_2 – J_3)/R_23 "[W]"

"Check : Q_1 + Q_2 + Q_3 = 0"

SumQ1Q2Q3 = Q_1 + Q_2 + Q_3

Results:

Main | HTrans_Three_surface_enclosure | F12_parallel_rectangles

Unit Settings: SI K Pa J mass rad

$A_1 = 9$ [m^2]	$A_2 = 9$ [m^2]	$A_3 = 30$ [m^2]
$Eb_1 = 363.7$ [W/m^2]	$Eb_2 = 459.3$ [W/m^2]	$Eb_3 = 411.5$ [W/m^2]
$eps_1 = 0.8$	$eps_2 = 0.8$	$eps_3 = 0.8$
$F_{11} = 0$	$F_{12} = 0.2508$	$F_{13} = 0.7492$
$F_{21} = 0.2508$	$F_{23} = 0.7492$	$J_1 = 375.1$ [W/m^2]
$J_2 = 447.9$ [W/m^2]	$J_3 = 411.5$ [W/m^2]	$L = 2.5$ [m]
$Q_1 = -409.8$ [W]	$Q_{12} = -164.4$ [W]	$Q_{13} = -245.5$ [W]
$Q_2 = 409.8$ [W]	$Q_{23} = 245.5$ [W]	$Q_3 = 4.744E-15$ [W]
$R_1 = 0.02778$ [$1/m^2$]	$R_{12} = 0.443$ [$1/m^2$]	$R_{13} = 0.1483$ [$1/m^2$]
$R_2 = 0.02778$ [$1/m^2$]	$R_{23} = 0.1483$ [$1/m^2$]	$R_3 = 0.008333$ [$1/m^2$]
$\sigma = 5.670E-08$ [W/m^2K^4]	SumQ1Q2Q3 = 6.119E-13 [W]	T3 = 291.9
$T_1 = 283$ [K]	$T_2 = 300$ [K]	$T_3 = 291.9$ [K]
X = 3 [m]	Y = 3 [m]	

Thus:

i) **Net heat transfer from surface 1 = Q1 = -409.8 W …. Ans…. negative sign indicates heat coming *in to* the surface.**

ii) **Net heat transfer between ceiling and floor = Q12 = -164.4 W ….Ans.…again, negative sign indicates heat coming *in to* the surface 1.**

iii) **Temp of re-radiating walls = T3 = 291.9 K … Ans.**

Note: Sum of Q1, Q2 and Q3 = 0, as it should be.

Download free eBooks at bookboon.com

Plot Plot (b) Plot the variation of Q1 and T3 as eps1 varies from 0.1 to 0.9:

First, compute the Parametric Table:

Table 1 | Table 2

1..9	1 eps_1	2 Q_1 [W]	3 T_3 [K]
Run 1	0.1	-79.29	298.5
Run 2	0.2	-147.1	297.2
Run 3	0.3	-205.7	296
Run 4	0.4	-256.9	295
Run 5	0.5	-301.9	294.1
Run 6	0.6	-342	293.3
Run 7	0.7	-377.7	292.5
Run 8	0.8	-409.8	291.9
Run 9	0.9	-438.9	291.3

Now, plot the results:



Download free eBooks at bookboon.com



==========

Brain power
By 2020, wind could provide one-tenth of our planet's electricity needs. Already today, SKF's innovative know-how is crucial to running a large proportion of the world's wind turbines.
Up to 25 % of the generating costs relate to maintenance. These can be reduced dramatically thanks to our systems for on-line condition monitoring and automatic lubrication. We help make it more economical to create cleaner, cheaper energy out of thin air.
By sharing our experience, expertise, and creativity, industries can boost performance beyond expectations.
Therefore we need the best employees who can meet this challenge!
The Power of Knowledge Engineering
Plug into The Power of Knowledge Engineering.
Visit us at www.skf.com/knowledge
SKF

Download free eBooks at bookboon.com

Click on the ad to read more

Prob. 5.C.2.11. In a cylindrical furnace with R = 0.75 m, L = 2 m as shown. Emissivities and temperatures of surfaces 1, 2 and 3 are: eps1 = 0.65, eps2 = 0.55, eps3 = 0.7, T1 = 800 K, T2 = 600 K and T3 = 1400 K respectively. Assume surface 3 to be re-radiating. Determine the net rate of radiation to / from each surface.

(b) If surface 3 is black, what are the values of Q1, Q2 and Q3?

(c) For the case (a) plot the variation of Q3 as emissivity of surface 3 varies from 0.1 to 1.

EES Solution:

This is a general, three-surface enclosure, for which the electrical network is shown below:





Fig.(a)



Fig.(b)

$$R_1 = \frac{1-\varepsilon 1}{A_1 \cdot \varepsilon 1}$$

$$R_2 = \frac{1-\varepsilon 2}{A_2 \cdot \varepsilon 2}$$

$$R_{12} = \frac{1}{A_1 \cdot F_{12}}$$

$$R_{13} = \frac{1}{A_1 \cdot F_{13}}$$

$$R_{23} = \frac{1}{A_2 \cdot F_{23}}$$

Download free eBooks at bookboon.com

Writing Kirchoff's Law to Nodes J1, J2 and J3:

$$\frac{Eb1 - J1}{R1} + \frac{J2 - J1}{R12} + \frac{J3 - J1}{R13} = 0 \quad \text{....for node J1}$$

$$\frac{Eb2 - J2}{R2} + \frac{J1 - J2}{R12} + \frac{J3 - J2}{R23} = 0 \quad \text{....for node J2}$$

$$\frac{Eb3 - J3}{R3} + \frac{J1 - J3}{R13} + \frac{J2 - J3}{R23} = 0 \quad \text{....for node J3}$$

While writing the above equations, remember to consider all heat currents as flowing *in to* the respective node.

First, get the Emissive powers and various resistances using the EES Function written earlier.

Then, solve simultaneously the three equations obtained by applying the Kirchoff's Law to the three Nodes, written above.

To get the View Factors F12, F13 and F23 use the EES Function for two parallel disks, written earlier.



Following is the EES program:

"Data:"

R = 0.75 [m]
L = 2 [m]

A_1 = pi * R^2 "[m^2]…area of top disk"
A_2 = A_1 "[m^2]…area ofbottom disk"
A_3 = 2 * pi * R * L "[m^2] …area of walls"

T_1 = 800 [K]"…temp of top disk"
T_2 = 600 [K]"…temp of bottom disk"
T_3 =1400 [K]"….temp of walls"

Download free eBooks at bookboon.com

sigma = 5.67E-08 [W/m^2-K^4]"…Stefan – Boltzmann constant"

eps_1 = 0.65 "emissivity of surface 1"
eps_2 = 0.55 "emissivity of surface 2"
eps_3 = 0.7 "…emissivity of surface 3"

"Determine View Factors: F_12, F_13 etc."

"Use the EES Function written earlier for parallel disks to get F_12:

i.e. F_12 = F12_parallel_disks(r_1, r_2, L)"

"We have: for the top and bottom disks, in the above Function: r_1 = R, r_2 = R = 0.75 m, L = 2 m"

F_12 = F12_parallel_disks(R, R, L) "…View factor from top disk to bottom disk"

F_21 = F_12 "…by symmetry"

"F_11 + F_12 + F_13 = 1 … by Summation rule for surface 1"

Download free eBooks at bookboon.com

Click on the ad to read more

"Therefore:"

F_13 = 1- F_12 "…View Factor from surface 1 to 3"

"Similarly, for surface 2, F_22 = 0 , and F_21 + F_22 + F_23 = 1 by Summation rule for surface 2, and we get:"

F_23 = 1- F_21 "…View Factor from surface 2 to 3"

"Now, calculate various Emissive powers and Resistances, using the EES PROCEDURE:"

CALL HTrans_Three_surface_enclosure(A_1,A_2,A_3,T_1,T_2,T_3,eps_1,eps_2,eps_3,F_12,F_13,F_23:Eb_1,Eb_2,Eb_3,R_1,R_2,R_3,R_12,R_13,R_23)

"Kirchoff's Law for Nodes J_1, J_2 and J_3:"

"For J_1:" (Eb_1 – J_1)/R_1 + (J_2 – J_1)/R_12 + (J_3 – J_1)/R_13 = 0

"For J_2:" (Eb_2 – J_2)/R_2 + (J_1 – J_2)/R_12 + (J_3 – J_2)/R_23 = 0

"For J_3:" (Eb_3 – J_3)/R_3 + (J_1 – J_3)/R_13 + (J_2 – J_3)/R_23 = 0

"Net heat transfer from each surface:"

Q_1 = (Eb_1 – J_1)/R_1 "[W]"

Q_2 = (Eb_2 – J_2)/R_2 "[W]"

Q_3 = (Eb_3 – J_3)/R_3 "[W]"

"Net heat transfer between surface 1 and 2:"

Q_12 = (J_1 – J_2)/R_12

"Net heat transfer between surface 1 and 3:"

Q_13 = (J_1 – J_3)/R_13

"Net heat transfer between surface 2 and 3:"

Q_23 = (J_2 – J_3)/R_23

"Check: Q_1 + Q_2 + Q_3 = 0 "

SumQ1Q2Q3 = Q_1 + Q_2 + Q_3

Download free eBooks at bookboon.com

Results:

Main | HTrans_Three_surface_enclosure | F12_parallel_disks

Unit Settings: SI K Pa J mass rad

A_1 = 1.767 [m^2]	A_2 = 1.767 [m^2]	A_3 = 9.425 [m^2]
Eb_1 = 23224 [W/m^2]	Eb_2 = 7348 [W/m^2]	Eb_3 = 217819 [W/m^2]
eps_1 = 0.65	eps_2 = 0.55	eps_3 = 0.7
F_{12} = 0.1111	F_{13} = 0.8889	F_{21} = 0.1111
F_{23} = 0.8889	**J_1 = 81136** [W/m^2]	**J_2 = 88578** [W/m^2]
J_3 = 201198 [W/m^2]	L = 2 [m]	Q_1 = -190056 [W]
Q_{12} = -1461 [W]	Q_{13} = -188594 [W]	Q_2 = -175443 [W]
Q_{23} = -176904 [W]	Q_3 = 365499 [W]	R = 0.75 [m]
R_1 = 0.3047 [$1/m^2$]	R_{12} = 5.093 [$1/m^2$]	R_{13} = 0.6366 [$1/m^2$]
R_2 = 0.463 [$1/m^2$]	R_{23} = 0.6366 [$1/m^2$]	R_3 = 0.04547 [$1/m^2$]
σ = 5.670E-08 [W/m^2K^4]	SumQ1Q2Q3 = 0.0122 [W]	T_1 = 800 [K]
T_2 = 600 [K]	T_3 = 1400 [K]	

Thus:

Net heat transfer from surface 1 = Q1 = -190056 W … negative sign indicates heat flowing *in to* the surface 1… Ans.

Net heat transfer from surface 2 = Q2 = -175443 W … negative sign indicates heat flowing *in to* the surface 2… Ans.

Net heat transfer from surface 3 = Q3 = 365499 W … heat flowing *from* the surface 3… Ans.

Also, SumQ1Q2Q3 = 0.0122, i.e. almost equal to zero, as it should be.

(b) If surface 3 is black, what are the values of Q1, Q2 and Q3?

Now, eps3 = 1.

Download free eBooks at bookboon.com

In EES data, enter: eps3 = 0.9999 to avoid division by zero.

Press F2 to calculate, and we get:

Unit Settings: SI K Pa J mass rad

$A_1 = 1.767$ [m^2]	$A_2 = 1.767$ [m^2]	$A_3 = 9.425$ [m^2]
$Eb_1 = 23224$ [W/m^2]	$Eb_2 = 7348$ [W/m^2]	$Eb_3 = 217819$ [W/m^2]
$eps_1 = 0.65$	$eps_2 = 0.55$	$eps_3 = 0.9999$
$F_{12} = 0.1111$	$F_{13} = 0.8889$	$F_{21} = 0.1111$
$F_{23} = 0.8889$	**J_1 = 86574** [W/m^2]	**J_2 = 95496** [W/m^2]
J_3 = 217814 [W/m^2]	$L = 2$ [m]	$Q_1 = -207904$ [W]
$Q_{12} = -1752$ [W]	$Q_{13} = -206152$ [W]	$Q_2 = -190385$ [W]
$Q_{23} = -192137$ [W]	$Q_3 = 398289$ [W]	$R = 0.75$ [m]
$R_1 = 0.3047$ [1/m^2]	$R_{12} = 5.093$ [1/m^2]	$R_{13} = 0.6366$ [1/m^2]
$R_2 = 0.463$ [1/m^2]	$R_{23} = 0.6366$ [1/m^2]	$R_3 = 0.00001061$ [1/m^2]
$\sigma = 5.670E\text{-}08$ [W/m^2-K^4]	SumQ1Q2Q3 = 0.0002028 [W]	$T_1 = 800$ [K]
$T_2 = 600$ [K]	$T_3 = 1400$ [K]	

Download free eBooks at bookboon.com

Click on the ad to read more

i.e.

Net heat transfer from surface 1 = Q1 = -207904 W … negative sign indicates heat flowing *in to* the surface 1… Ans.

Net heat transfer from surface 2 = Q2 = -190385 W … negative sign indicates heat flowing *in to* the surface 2… Ans.

Net heat transfer from surface 3 = Q3 = 398289 W … heat flowing *from* the surface 3… Ans.

Also, SumQ1Q2Q3 = 0.0002028, i.e. almost equal to zero, as it should be.

(c) For the case (a), plot the variation of Q3 as emissivity of surface 3 varies from 0.1 to 1:

First, prepare the Parametric Table:

Table 1 | Table 2 | Table 3

1..10	1 eps_3	2 Q_1 [W]	3 Q_2 [W]	4 Q_3 [W]	5 SumQ1Q2Q3 [W]	6 Q_{13} [W]
Run 1	0.1	-66271	-71811	138082	-0.00002081	-66825
Run 2	0.2	-109093	-107661	216754	-2.050E-09	-108950
Run 3	0.3	-136752	-130818	267570	-6.125E-10	-136159
Run 4	0.4	-156091	-147008	303099	1.051E-10	-155183
Run 5	0.5	-170373	-158965	329338	2.337E-10	-169232
Run 6	0.6	-181352	-168157	349509	-6.355E-11	-180033
Run 7	0.7	-190056	-175443	365499	-1.197E-10	-188594
Run 8	0.8	-197124	-181361	378485	3.075E-11	-195548
Run 9	0.9	-202979	-186263	389242	1.459E-10	-201308
Run 10	0.9999	-207904	-190385	398289	-4.741E-09	-206152

In the above Table, in addition to Q3, we have also obtained Q1, Q2, Q13 and SumQ1Q2Q3. Note that SumQ1Q2Q3 is almost equal to zero, in all cases.

As said earlier, negative sign indicates that heat is flowing ***in to*** the surface.

Download free eBooks at bookboon.com

Plot the result:



==========

Prob. 5.C.2.12. A long duct of equilateral triangular section, of side w = 0.75 m, shown in Fig. Ex. 13.28, has its surface 1 at 700 K, surface 2 at 1000 K, and surface 3 is insulated. Further, surface 1 has an emissivity of 0.8 and surface 2 is black. Determine the rate at which energy must be supplied to surface 2 to maintain these operating conditions.

(b) Plot the variation of Q1 and T3 as epsilon1 varies from 0.1 to 0.9.

EES Solution:

Since the duct is very long, end effects can be neglected, and this is a ***three-surface enclosure*** problem.

Surface 1 is gray, surface 2 is black and surface 3 is insulated.

Download free eBooks at bookboon.com

Radiation network is shown in Fig.(b) below:



Fig.(a)



Fig.(b)



Download free eBooks at bookboon.com

Click on the ad to read more

We use the EES Function written earlier to calculate Emissive powers and resistances.

T3 is unknown, but is calculated from the relations: Eb3 = J3 = σ.T3^4, where σ is the Stefan-Boltzmann constant.

EES code is given below:

"Data:"

L = 1 [m]"…assumed length of duct"
W = 0.75 [m]"…side of equilateral triangle"
A_1 = W * L "[m^2]….area of side 1"
A_2 = A_1"[m^2]…area ofside 2"
A_3 = A_1 "[m^2] …area of side 3"

T_1 = 700 [K]"…temp of ceiling, by data"
T_2 = 1000 [K]"…temp of floor, by data"

{T_3 = …to be found out}

sigma = 5.67E-08 [W/m^2-K^4]"…Stefan – Boltzmann constant"

eps_1 = 0.8 "emissivity of surface 1"
eps_2 = 0.9999 "emissivity of surface 2 …. black"
eps_3 = 0.9999 "…emissivity of surface 3 …. "

"View Factors: F_12, F_13 etc."

"F_11 + F_12 + F_13 = 1 … by Summation rule for surface 1"

"But, "

F_11 = 0 "…since surface 1 is flat;

Also, F_12 = F_13, by symmetry."

"Therefore:"

F_12 = 0.5 "…View Factor from surface 1 to 2"

F_13 = 0.5 "…View Factor from surface 1 to 3"

Download free eBooks at bookboon.com

"Similarly, for surface 2, F_22 = 0 , and F_21 + F_22 + F_23 = 1 by Summation rule for surface 2, and we get:"

F_23 = 0.5 "…View Factor from surface 2 to 3"

"Now, calculate various Emissive powers and Resistances, using the EES PROCEDURE:"

CALL
HTrans_Three_surface_enclosure(A_1,A_2,A_3,T_1,T_2,T_3,eps_1,eps_2,eps_3,F_12,F_13,F_23:Eb_1,Eb_2,Eb_3,R_1,R_2,R_3,R_12,R_13,R_23)

"Kirchoff's Law for Nodes J_1:"

"For J_1:" (Eb_1 – J_1)/R_1 + (J_2 – J_1)/R_12 + (J_3 – J_1)/R_13 = 0

Eb_2 = J_2 "….since surface 2 is black"

Eb_3 = J_3 "….since surface 3 is insulated"

{Eb_3 = sigma * T_3 ^4 "[W/m^2]…by definition of Eb"}

"Net heat transfer from each surface:"

Q_1 = (Eb_1 – J_1)/R_1"[W]…net heat transfer from surface 1"

Q_2 = -Q_1"[W]…net heat transfer from surface 2"

Q_3 = 0 "[W]…net heat transfer from surface 3"

"Net heat transfer between surface 1 and 2:"

Q_12 = (J_1 – J_2)/R_12 "[W]"

"Net heat transfer between surface 1 and 3:"

Q_13 = (J_1 – J_3)/R_13 "[W]"

"Net heat transfer between surface 2 and 3:"

Q_23 = (J_2 – J_3)/R_23 "[W]"

Download free eBooks at bookboon.com

"Check: Q_1 + Q_2 + Q_3 = 0"

SumQ1Q2Q3 = Q_1 + Q_2 + Q_3

"=="

Results:

Unit Settings: SI K Pa J mass rad

$A_1 = 0.75$ [m^2]
$Eb_1 = 13614$ [W/m^2]
$eps_1 = 0.8$
$F_{11} = 0$
$F_{23} = 0.5$
$J_3 = 38558$ [W/m^2]
$Q_{12} = -13606$ [W]
$Q_{23} = 6803$ [W]
$R_{12} = 2.667$ [1/m^2]
$R_{23} = 2.667$ [1/m^2]
SumQ1Q2Q3 = 7.727E-07 [W]
$T_3 = 908.1$ [K]

$A_2 = 0.75$ [m^2]
$Eb_2 = 56700$ [W/m^2]
$eps_2 = 0.9999$
$F_{12} = 0.5$
$J_1 = 20417$ [W/m^2]
$L = 1$ [m]
$Q_{13} = -6803$ [W]
$Q_3 = 0$ [W]
$R_{13} = 2.667$ [1/m^2]
$R_3 = 0.0001333$ [1/m^2]
$T_1 = 700$ [K]
$W = 0.75$ [m]

$A_3 = 0.75$ [m^2]
$Eb_3 = 38558$ [W/m^2]
$eps_3 = 0.9999$
$F_{13} = 0.5$
$J_2 = 56700$ [W/m^2]
$Q_1 = -20409$ [W]
$Q_2 = 20409$ [W]
$R_1 = 0.3333$ [1/m^2]
$R_2 = 0.0001333$ [1/m^2]
$\sigma = 5.670E-08$ [W/m^{2}K^4]
$T_2 = 1000$ [K]

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

Thus:

Net heat transfer from surface 1 = Q1 = -20409 W … negative sign indicates heat coming *into* the surface … Ans.

Net heat transfer from surface 2 = Q2 = 20409 W … positive sign indicates heat *leaving* the surface … Ans.

Temp of insulated surface 3 = T3 = 908.1 K … ans.

Note that as a check: SumQ1Q2Q3 = 0…is satisfied.

(b) Plot the variation of Q1 and T3 as epsilon1 varies from 0.1 to 0.9:

First, compute the Parametric Table:

Table 1 | Table 2 | Table 3 | Table 4

1..9	1 eps_1	2 Q_1 [W]	3 T_3 [K]
Run 1	0.1	-3127	987.5
Run 2	0.2	-6059	975.4
Run 3	0.3	-8813	963.5
Run 4	0.4	-11405	951.9
Run 5	0.5	-13849	940.6
Run 6	0.6	-16157	929.6
Run 7	0.7	-18341	918.7
Run 8	0.8	-20409	908.1
Run 9	0.9	-22372	897.7

Download free eBooks at bookboon.com

Note: Negative sign for Q1 denotes heat flowing *into* the surface 1.

Now, plot the results:





Note: The four problems solved above with EES cover the important variations of the three-surface enclosure problem.

==========

Download free eBooks at bookboon.com

Prob. 5.C.2.13. A furnace is in the shape of a frustum of a cone with base (i.e. surface 1) diameter of 2 m, top (i.e. surface 2) diameter of 1 m, and height 1.5 m. The curved surface (i.e. surface 3) has an emissivity of eps3 = 0.65 and is maintained at T3 = 1600 K. Emissivities and temperatures of surfaces 1, 2 are: eps1 = 0.6, eps2 = 0.7, T1 = 700 K, T2 = 1200 K respectively. Determine the net rate of radiation to / from each surface.

(b) If surface 3 is black, what are the values of Q1, Q2 and Q3?

(c) For the case (a) plot the variation of Q13 as emissivity of surface 3 varies from 0.1 to 1.

The Wake
the only emission we want to leave behind
Low-speed Engines Medium-speed Engines Turbochargers Propellers Propulsion Packages PrimeServ
The design of eco-friendly marine power and propulsion solutions is crucial for MAN Diesel & Turbo.
Power competencies are offered with the world's largest engine programme – having outputs spanning
from 450 to 87,220 kW per engine. Get up front!
Find out more at www.mandieselturbo.com
Engineering the Future – since 1758.
MAN Diesel & Turbo
MAN

Download free eBooks at bookboon.com

Click on the ad to read more

EXCEL Solution:

This is a general, three-surface enclosure, for which the schematic fig and the Radiation network are shown below:



Fig.5.C.2.13

In the above fig., base and top are circles whose area is calculated as (π * R^2).

Area of frustum of a cone: $A3 = \pi \cdot (R\_1 + R\_2) \cdot \sqrt{(R\_2 - R\_1)^2 + L^2}$

Download free eBooks at bookboon.com

Now, let us prepare an EXCEL template to solve general, three surface enclosure problem.

Here, in the worksheet, we will first have a portion where we calculate View Factors, say for the three important geometries, viz. parallel rectangles, coaxial parallel discs and perpendicular rectangles with a common edge.

Recollect that we have already written EXCEL – VBA Functions for View factors for these geometries. See Problems 5B.11, 5B.12 and 5B.13.

Then, in the template, we will calculate the Emissive powers and various 'surface resistances' and 'space resistances'. Then, we will solve the three equations obtained by writing the Kirchoff's Law for the three nodes, to obtain the radiosities J1, J2 and J3. We shall use the EXCEL Solver to do this. Knowing J1, J2 and J3, the heat flows from a given surface or between any two surfaces are easily calculated.

Following is the worksheet:

First, a template for View Factors:



Download free eBooks at bookboon.com

=F_ij_Coaxial_parallel_discs(M78/M76,M77/M78)

F	G	H	I	J	K	L	M	N
		(a) Aligned, parallel rectangles:				(b) Coaxial, parallel disks:		
		X =	1			r_i =	0.75	
		Y =	1			r_j =	0.75	
		L =	1			L =	2	
		F_ij =	0.1998249			F_ij =	0.111111	
		(c) Perpendicular rectangles with a common edge:						
		X =	1					
		Y =	1					
		Z =	1					
		F_ij =	0.2000438					

Note in the above that in a corner of the worksheet, there is a template to calculate the View Factors for the aforesaid three geometries using the VBA Functions already written. For example, View factor for Coaxial, parallel disks is calculated in cell M79, using the VBA Function. The Function entered can be seen in the Formula bar. If we change the values of r_i, r_j or L in cells M76, M77 and M78 respectively, immediately the View factor in cell M79 will change. Similarly, we can find out the View factors for other two geometries by entering data in respective cells.

Let us remind ourselves the radiation network for the three surface enclosure (given above) and the equations obtained by applying the Kirchoff's Law to the three Nodes:

$$\text{Node } J_1: \quad \frac{E_{b1}-J_1}{R_1}+\frac{J_2-J_1}{R_{12}}+\frac{J_3-J_1}{R_{13}}=0 \qquad \text{.....(13.63,a)}$$

$$\text{Node } J_2: \quad \frac{E_{b2}-J_2}{R_2}+\frac{J_1-J_2}{R_{12}}+\frac{J_3-J_2}{R_{23}}=0 \qquad \text{.....(13.63,b)}$$

$$\text{Node } J_3: \quad \frac{E_{b3}-J_3}{R_3}+\frac{J_1-J_3}{R_{13}}+\frac{J_2-J_3}{R_{23}}=0 \qquad \text{.....(13.63,c)}$$

Solving these three eqns. simultaneously, we get J_1, J_2 and J_3.

Download free eBooks at bookboon.com

And, when the three Radiosities, viz. J1, J2 and J3 are obtained by solving the above three equations, the various heat flows are calculated as follows:

Once the magnitudes of the radiosities are known, expressions for net heat flows between the surfaces are:

$$Q_{12} = \frac{J_1 - J_2}{R_{12}} = \frac{J_1 - J_2}{\frac{1}{A_1 \cdot F_{12}}} \qquad \text{....(13.64,a)}$$

$$Q_{13} = \frac{J_1 - J_3}{R_{13}} = \frac{J_1 - J_3}{\frac{1}{A_1 \cdot F_{13}}} \qquad \text{....(13.64,b)}$$

$$Q_{23} = \frac{J_2 - J_3}{R_{23}} = \frac{J_1 - J_2}{\frac{1}{A_2 \cdot F_{23}}} \qquad \text{....(13.64,c)}$$

See the light!
The sooner you realize we are right, the sooner your life will get better!

A bit over the top? Yes we know!

We are just that sure that we can make your media activities more effective.

Get "Bookboon's Free Media Advice"
Email kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

And, net heat flow from each surface is:

$$Q_1 = \frac{E_{b1} - J_1}{R_1} = \frac{E_{b1} - J_1}{\left(\frac{1-\varepsilon_1}{A_1 \cdot \varepsilon_1}\right)} \quad \text{.....(13.65,a)}$$

$$Q_2 = \frac{E_{b2} - J_2}{R_2} = \frac{E_{b2} - J_2}{\left(\frac{1-\varepsilon_2}{A_2 \cdot \varepsilon_2}\right)} \quad \text{.....(13.65,b)}$$

$$Q_3 = \frac{E_{b3} - J_3}{R_3} = \frac{E_{b3} - J_3}{\left(\frac{1-\varepsilon_3}{A_3 \cdot \varepsilon_3}\right)} \quad \text{.....(13.65,c)}$$

Next, In the EXCEL worksheet, enter data for the three surface enclosure problem, and name the cells:

A_3 | =PI()*(C78+C79)*SQRT((C79-C78)^2+C80^2)

	A	B	C	D	E	F
76		**Data:**				
77						
78		**R_1 =**	1	m		
79		**R_2 =**	0.5	m		
80		**L =**	1.5	m		
81		**sigma (W/m2.K^4):**	5.67E-08	W/m^2-K^4		
82						
83		**Areas (m2):**	A_1	A_2	A_3	
84			3.141592654	0.7853982	7.450941	
85						
86		**Emissivities:**	eps_1	eps_2	eps_3	
87			0.6	0.7	0.65	
88						
89		**View Factors:**	F_11	F_12	F_13	
90			0	0.072949	0.927051	
91			F_21	F_22	F_23	
92			0.291796	0	0.927051	
93			F_31	F_32	F_33	
94			0.390879022	0.0977198	0.511401	

Download free eBooks at bookboon.com

In the above, A_3 is the area of frustum and the equation entered in cell E84 can be seen in the Formula bar.

View Factors:

View factor F12 is determined with the template explained earlier, using the VBA Function for View Factor of parallel disks. See the Formula bar below:



This value of F_ij is transferred to cell D90 above. Other View factors are calculated using the View factor algebra:

$F_{11} + F_{12} + F_{13} = 1$ ...by Summation rule for surface 1

But, $F_{11} = 0$ ..for Flat surface 1

Therefore: $F_{13} = 1 - F_{12}$ ...View factor from surface 1 to 3

$A_1 \cdot F_{12} = A_2 \cdot F_{21}$ ....by reciprocity

Then: $F_{21} = \frac{A_1}{A_2} \cdot F_{12}$ ...View factor from surface 2 to 1

But, $F_{22} = 0$ ..for Flat surface 2

Therefore: $F_{23} = 1 - F_{21}$ ...View factor from surface 2 to 3

And:

$A_1 \cdot F_{13} = A_3 \cdot F_{31}$ ....by reciprocity

Then: $F_{31} = \frac{A_1}{A_3} \cdot F_{13}$ ...View factor from surface 3 to 1

And, by reciprocity: $A_2 \cdot F_{23} = A_3 \cdot F_{32}$

Therefore: $F_{32} = \frac{A_2}{A_3} \cdot F_{23}$ ...View factor from surface 3 to 2

And: $F_{33} = 1 - F_{31} - F_{32}$ ...using Summation rule for surface 3

Download free eBooks at bookboon.com

Using the above formulas, all View Factors are entered in the above part of worksheet.

Next, enter the Temp values, and continue the calculations:



In the above, Emissive powers E_b1 etc are calculated from:

$$E\_b = sigma \cdot T^4$$

See the formula bar above for the formula entered for E_b1 in cell C102.

Similarly, surface resistances R_1, R_2 and R_3 and space resistances R_12, R_13 and R_23 are calculated with the formulas given above in Fig.5.C.2.13.

Next, important step to calculate Radiosities J1, J2 and J3:



Download free eBooks at bookboon.com

In the above, first, put guess values of 1000 each for J1, J2 and J3.

Then, for Nodes 1, 2 and 3 enter the corresponding equations, obtained by applying Kirchoff's Law, given earlier.

See the Formula bar in the above screen shot for formula entered for Node 1, in cell C114. Similarly, formulas are entered for Nodes 2 and 3 in cells C115 and C116.

Sum of the squares of C114 to C116 should be zero, but, in this case since J1, J2 and J3 are assumed values, the sum of squares is not zero.

Apply Solver to make C117 zero by changing J1, J2 and J3. (i.e. cells C11, D111 and E111.)

To do this: Go to Data – Solver:



Click on Solver. We get the following window. Fill it up as shown:



Download free eBooks at bookboon.com

Click Solve. We get following message:



be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

Solver has found a solution. Click OK to keep the solution. We get:



	A	B	C	D	E	F
109						
110		Radiosities (W/m2):	J_1	J_2	J_3	
111			133193.6206	172619	323575.7	.....Ans.
112						
113		Apply Kirchoff's Law at each Node:				
114		Node J1:	2.93716E-06			
115		Node J2:	2.48438E-06			
116		Node J3:	-5.9306E-05			
117		Sum_diff^2=	3.53202E-09			
118						
119		Apply Solver to make Sumdiff^2 a minimum, by varying J_1, J_2, and J_3:				

Observe that values of J1, J2 and J3 are shown in the respective cells.

Sum_diff^2 is almost equal to zero.

And, results of equations at Nodes 1, 2 and 3 are almost equal to zero.

Next, continue the calculations for heat transfers:



	A	B	C	D	E	F
112						
113		Apply Kirchoff's Law at each Node:				
114		Node J1:	2.93716E-06			
115		Node J2:	2.48438E-06			
116		Node J3:	-5.9306E-05			
117		Sum_diff^2=	3.53202E-09			
118						
119		Apply Solver to make Sumdiff^2 a minimum, by varying J_1, J_2, and J_3:				
120						
121		Q_betwn_surfaces (W):	Q_12	Q_13	Q_23	
122			-9035.35191	-554471.89	-109912	.....Ans.
123						
124		Qnet_from_surfaces (W):	Q_1	Q_2	Q_3	
125			-563507.241	-100876.84	664384.1	.....Ans.
126						
127		Check: Q1 + Q2 + Q3 = 0	SumQ1Q2Q3 =		0.0	...Verified.

Download free eBooks at bookboon.com

In the above heat transfers from/to each surface (Q_1, Q_2 and Q_3), and also between surfaces (Q_12, Q_13, Q_23) are calculated using formulas given earlier. For ex. see in the Formula bar, the formula entered to calculate Q_1 in cell C125.

Negative sign for a heat transfer indicates heat coming ***in to*** the surface.

As a check: Sum of Q1, Q2 and Q3 should be zero.

Thus:

Q1 = -563507.24 W, Q2 = -100876.84 W and Q3 = 664384.1 W … Ans.

(b) If surface 3 is black, what are the values of Q1, Q2 and Q3?

Now, simply change eps3 = 0.9999. Remember not to put eps3 = 1, to avoid division by zero, as explained earlier.

Then, all other related quantities will change in the worksheet.



Download free eBooks at bookboon.com

Click on the ad to read more

	A	B	C	D	E
85					
86		Emissivities:	eps_1	eps_2	eps_3
87			0.6	0.7	0.9999
88					
89		View Factors:	F_11	F_12	F_13
90			0	0.072949	0.927051
91			F_21	F_22	F_23
92			0.291796	0	0.927051
93			F_31	F_32	F_33
94			0.390879022	0.0977198	0.511401
95					
96					
97					
98		Temps. (K)	T_1	T_2	T_3
99			700	1200	1600
100					
101		E_b (W/m2)	E_b1	E_b2	E_b3
102			1.36E+04	1.18E+05	3.72E+05
103					
104		Resistances(m^-2):	R_1	R_2	R_3
105			0.212206591	0.5456741	1.34E-05
106					
107			R_12	R_13	R_23
108			4.363457843	0.3433575	1.37343

However, J1, J2 and J3, do not change o their own:

110		Radiosities (W/m2):	J_1	J_2	J_3	
111			133193.6206	172619	323575.7	.....Ans.
112						
113		Apply Kirchoff's Law at each Node:				
114		Node J1:	0			
115		Node J2:	0			
116		Node J3:	3576430614			
117		Sum_diff^2=	1.27909E+19			
118						
119		Apply Solver to make Sumdiff^2 a minimum, by varying J_1, J_2, and J_3:				

Observe that Sum_diff^2 is not zero now.

Download free eBooks at bookboon.com

Apply Solver to get correct values of J1, J2 and J3.

(Remember that for a black body Eb_3 should be equal to J3. Since we have taken eps3 = 0.9999, Eb_3 is not *exactly* equal to, but *almost* equal to J3).

109					
110	Radiosities (W/m2):	J_1	J_2	J_3	
111		151403.3259	186642.71	371578.7	.....Ans.
112					
113	Apply Kirchoff's Law at each Node:				
114	Node J1:	-5.7975E-07			
115	Node J2:	-3.4051E-09			
116	Node J3:	0.000318623			
117	Sum_diff^2=	1.01521E-07			
118					
119	Apply Solver to make Sumdiff^2 a minimum, by varying J_1, J_2, and J_3:				
120					
121	Q_betwn_surfaces (W):	Q_12	Q_13	Q_23	
122		-8076.02333	-641242.43	-134653	.....Ans.
123					
124	Qnet_from_surfaces (W):	Q_1	Q_2	Q_3	
125		-649318.456	-126576.64	775895.1	.....Ans.
126					
127	Check: Q1 + Q2 + Q3 = 0	SumQ1Q2Q3 =		0.0	...Verified.

We get:

Q1 = -649318.46 W, Q2 = -126576.64 W, Q3 = 775895.1 W …. Ans.

(c) For the case (a) plot the variation of Q3, Q13 as emissivity of surface 3 varies from 0.1 to 0.9:

Now, change eps3 = 0.65 to go back to case (a).

Download free eBooks at bookboon.com

First, prepare a Table as shown below:

G152

	A	B	C	D	E
128					
129		**Plot Q3, Q_13 against eps3:**			
130					
131		eps_3	Q_3 (W)	Q_13 (W)	SumQ1Q2Q3
132		0.1			
133		0.2			
134		0.3			
135		0.4			
136		0.5			
137		0.6			
138		0.7			
139		0.8			
140		0.9			
141		0.99			
142		0.9999			
143					

Who is your target group? And how can we reach them?

At Bookboon, you can segment the exact right audience for your advertising campaign.

Our eBooks offer in-book advertising spot to reach the right candidate.

Contact us to hear more
kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

Now, write a VBA program to do the following:

Copy the first value of eps3 from this Table to cell E87 in the Data section.

Then, all other values except J1, J2, J3 and the heat transfers, will change.

Apply the Solver to get J1, J2 and J3.

Immediately all heat transfers will get updated.

Then, copy Q_3, Q_13 and also SumQ1Q2Q3 (to check that it is zero) to the respective places in the Table.

Repeat these steps for the next value of eps3, etc.

Following is the VBA program, operated by a control button:

```
Sub Macro1()
'
' Macro1 Macro
' Finds J1, J2 and J3 making Sumdiff^2 minimum
'
' Keyboard Shortcut: Ctrl+Shift+J

Dim i As Integer

For i = 0 To 10 'start of For ... Next loop

    Range("E87") = Cells(132 + i, 2) 'copy the first value of eps3 from the Table to cell E87

    'Following part of the code applies Solver to minimise cell C117 by changing cells C111:E111

    '-------------------------------------------------

    SolverOk SetCell:="$C$117", MaxMinVal:=2, ValueOf:="0", ByChange:= _
        "$C$111:$E$111"
    SolverSolve UserFinish:=True
    SolverFinish KeepFinal:=1

    '-------------------------------------------------

    Cells(132 + i, 3) = Range("E125") 'copies up-dated value of Q_3 to its place in Table

    Cells(132 + i, 4) = Range("D122") 'copies up-dated value of Q_13 to its place in Table

    Cells(132 + i, 5) = Range("E127") 'copies up-dated value of SUMQ1Q2Q3 to its place in Table

 Next i

End Sub
```

Read the comments in the above program.

Download free eBooks at bookboon.com

Now, press the command button and the Solver is applied for each value of eps3:


Apply Kirchoff's Law at each Node:
Node J1: 1.31084E-07
Node J2: 8.31787E-08
Node J3: 1.74704E-06
Sum_diff^2= 3.07627E-12
Apply Solver to make Sumdiff^2 a minimum, by varying J_1, J_2, and J_3:
Click to
Apply Solver to find:
J1, J2 and J3
Q_betwn_surfaces (W): Q_12 Q_13 Q_23
-8076.023329 -641242.433 -134652.664 .....Ans.
Qnet_from_surfaces (W): Q_1 Q_2 Q_3
-649318.4563 -126576.641 775895.097 .....Ans.
Check: Q1 + Q2 + Q3 = 0 SumQ1Q2Q3 = 0.0 ...Verified.

And, the Table gets filled up:

eps_3	Q_3 (W)	Q_13 (W)	SumQ1Q2Q3
0.1	203869.841	-196129.975	0
0.2	345299.485	-306181.229	1.04774E-09
0.3	449165.229	-387002.724	0
0.4	528678.165	-448874.465	0
0.5	591504.376	-497761.693	0
0.6	642397.878	-537363.671	1.39698E-09
0.7	684463.429	-570096.318	0
0.8	719814.651	-597604.316	1.28057E-09
0.9	749940.300	-621046.116	-3.25963E-09
0.99	773483.421	-639365.825	3.48082E-08
0.9999	775895.097	-641242.433	1.96125E-06

Download free eBooks at bookboon.com

Now, plot the results in EXCEL:



Brain power
By 2020, wind could provide one-tenth of our planet's electricity needs. Already today, SKF's innovative know-how is crucial to running a large proportion of the world's wind turbines.
Up to 25 % of the generating costs relate to maintenance. These can be reduced dramatically thanks to our systems for on-line condition monitoring and automatic lubrication. We help make it more economical to create cleaner, cheaper energy out of thin air.
By sharing our experience, expertise, and creativity, industries can boost performance beyond expectations.
Therefore we need the best employees who can meet this challenge!
The Power of Knowledge Engineering
Plug into The Power of Knowledge Engineering.
Visit us at www.skf.com/knowledge
SKF

Download free eBooks at bookboon.com

Click on the ad to read more



Note: negative sign for Q_13 indicates heat flowing *in to* the surface 1 from surface 3.

==========

Prob. 5.C.2.14. Two parallel plates of size 1 m × 1 m are spaced 0.5 m apart and are located in a very large room, the walls of which are maintained at a temp of 27 C. One plate is maintained at a temp of 900 C and the other at 400 C. Their emissivities are 0.2 and 0.5 respectively. If the plates exchange heat between themselves and surroundings, find the net heat transfer to each plate and to the room. Consider only the plate surfaces facing each other. [VTU – M.Tech. – Dec. 2009–Jan. 2010]

(b) In addition, plot Q1 and Q12 against ε1, for $0.1 < \varepsilon 1 < 0.9$.

This is the same as Prob. 5.C.2.4. which was solved with Mathcad earlier.

Now, let us solve it with EXCEL:

Use the Template prepared in the previous Problem.

Use A3 = Area of the room as very large, say 1E06 m^2, and the emissivity as 0.99 (black body).

Download free eBooks at bookboon.com

Next, In the EXCEL worksheet, enter data for the three surface enclosure problem, and name the cells:

	A	B	C	D	E
76		**Data:**			
77					
78		**X =**	1	m	
79		**Y =**	1	m	
80		**L =**	0.5	m	
81		sigma (W/m2.K^4):	5.67E-08	W/m^2-K^4	
82					
83		Areas (m2):	A_1	A_2	A_3
84			1	1	1.00E+06
85					
86		Emissivities:	eps_1	eps_2	eps_3
87			0.2	0.5	0.99
88					
89		View Factors:	F_11	F_12	F_13
90			0	0.4152533	0.5847467
91			F_21	F_22	F_23
92			0.4152533	0	0.5847467
93			F_31	F_32	F_33
94			5.84747E-07	5.84747E-07	0.999998831

In the above, A_3 is the area of the room, taken as 1E06 m^2 (i.e. very large).

View Factors:

View factor F12 is determined with the template explained earlier, using the VBA Function for View Factor of parallel plates. See the Formula bar below:

=F_ij_Aligned_parallel_rectangles(I77/I79,I78/I79)

E	F	G	H	I	J	K
			(a) Aligned, parallel rectangles:			
			X =	1		
			Y =	1		
			L =	0.5		
			F_ij =	0.4152533		

Download free eBooks at bookboon.com

This value of F_ij is transferred to cell D90 above. Other View factors are calculated using the View factor algebra:

Next, enter the Temp values, and continue the calculations:



In the above, Emissive powers E_b1 etc and Resistances are calculated:

Next, important step to calculate Radiosities J1, J2 and J3:



In the above, first, put guess values of 1000 each for J1, J2 and 459 for J3 (since Eb_3 = J3 for black body).

Download free eBooks at bookboon.com

Then, for Nodes 1, 2 and 3 enter the corresponding equations, obtained by applying Kirchoff's Law, given earlier.

See the Formula bar in the above screen shot for formula entered for Node 1, in cell C114. Similarly, formulas are entered for Nodes 2 and 3 in cells C115 and C116.

Sum of the squares of C114 to C116 should be zero, but, in this case since J1, J2 and J3 are assumed values, the sum of squares is not zero.

Apply Solver to make C117 zero by changing J1, J2 and J3. (i.e. cells C11, D111 and E111.)

To do this: Go to Data – Solver:



Download free eBooks at bookboon.com

Click on the ad to read more

Click on Solver. We get the following window. Fill it up as shown:



Click Solve. We get following message:



Solver has found a solution. Click OK to keep the solution. We get:

C117 =SUMSQ(C114:C116)

	A	B	C	D	E	F
109						
110		Radiosities (W/m2):	J_1	J_2	J_3	
111			25413.00192	11226.54648	459.270211	.....Ans.
112						
113		Apply Kirchoff's Law at each Node:				
114		Node J1:	-1.19329E-06			
115		Node J2:	1.46201E-06			
116		Node J3:	-2.51734E-06			
117		Sum_diff^2=	9.89843E-12			
118						
119		Apply Solver to make Sumdiff^2 a minimum, by varying J_1, J_2, and J_3:				

Download free eBooks at bookboon.com

Observe that values of J1, J2 and J3 are shown in the respective cells.

Sum_diff^2 is almost equal to zero.

And, results of equations at Nodes 1, 2 and 3 are almost equal to zero.

Next, continue the calculations for heat transfers:



C125 =(E_b1-J_1)/R_1

	A	B	C	D	E	F
112						
113		Apply Kirchoff's Law at each Node:				
114		Node J1:	-1.19329E-06			
115		Node J2:	1.46201E-06			
116		Node J3:	-2.51734E-06			
117		Sum_diff^2=	9.89843E-12			
118						
119		Apply Solver to make Sumdiff^2 a minimum, by varying J_1, J_2, and J_3:				
120						
121		Q_betwn_surfaces (W):	Q_12	Q_13	Q_23	
122			5890.97244	14591.61227	6296.129264	.....Ans.
123						
124		Qnet_from_surfaces (W):	Q_1	Q_2	Q_3	
125			20482.58471	405.1568258	-20887.74154	.....Ans.
126						
127		Check: Q1 + Q2 + Q3 = 0	SumQ1Q2Q3 =		0.0	...Verified.

In the above heat transfers from/to each surface (Q_1, Q_2 and Q_3), and also between surfaces (Q_12, Q_13, Q_23) are calculated using formulas given earlier. For ex. see in the Formula bar, the formula entered to calculate Q_1 in cell C125.

Negative sign for a heat transfer indicates heat coming ***in to*** the surface.

As a check: Sum of Q1, Q2 and Q3 should be zero.

Thus:

Q1 = 20482.58 W, Q2 = 405.16 W and Q3 = -20887.74 W … Ans.

Note: Results match with those obtained with Mathcad earlier.

Download free eBooks at bookboon.com

(b) In addition, plot Q1 and Q12 against ε1, for 0.1 < ε1 < 0.9:

First, set up a Table as follows:



	A	B	C	D	E
130					
131		eps_1	Q_1 (W)	Q_12 (W)	SumQ1Q2Q3
132		0.1			
133		0.2			
134		0.3			
135		0.4			
136		0.5			
137		0.6			
138		0.7			
139		0.8			
140		0.9			

Now, write a VBA program to do the following:

Copy the first value of eps1 from this Table to cell C87 in the Data section.

Download free eBooks at bookboon.com

Click on the ad to read more

Then, all other values except J1, J2, J3 and the heat transfers, will change.

Apply the Solver to get J1, J2 and J3.

Immediately all heat transfers will get up-dated.

Then, copy Q_1, Q_12 and also SumQ1Q2Q3 (to check that it is zero) to the respective places in the Table.

Repeat these steps for the next value of eps1, etc.

Following is the VBA program, operated by a control button:

```
Sub Macro1()
'
' Macro1 Macro
' Finds J1, J2 and J3 making Sumdiff^2 minimum
'
' Keyboard Shortcut: Ctrl+Shift+J

Dim i As Integer

For i = 0 To 8 'start of For ... Next loop

    Range("C87") = Cells(132 + i, 2) 'copy the first value of eps1 from the Table to cell C87

    'Following part of the code applies Solver to minimise cell C117 by changing cells C111:E111

    '-------------------------------------------------

    SolverOk SetCell:="$C$117", MaxMinVal:=2, ValueOf:="0", ByChange:= _
        "$C$111:$E$111"
    SolverSolve UserFinish:=True
    SolverFinish KeepFinal:=1

    '-------------------------------------------------

    Cells(132 + i, 3) = Range("C125") 'copies up-dated value of Q_1 to its place in Table

    Cells(132 + i, 4) = Range("C122") 'copies up-dated value of Q_12 to its place in Table

    Cells(132 + i, 5) = Range("E127") 'copies up-dated value of SUMQ1Q2Q3 to its place in Table

 Next i

End Sub
```

Read the comments in the above program.

Download free eBooks at bookboon.com

Now, press the command button and the Solver is applied for each value of eps1:

Apply Kirchoff's Law at each Node:				
Node J1:	-1.71713E-09			
Node J2:	-2.13731E-09			
Node J3:	-1.09903E-08			
Sum_diff^2=	1.28304E-16			
Apply Solver to make Sumdiff^2 a minimum, by varying J_1, J_2, and J_3:				
Q_betwn_surfaces (W):	Q_12	Q_13	Q_23	
	29684.3372	56875.95647	15075.40191	.....Ans.
Qnet_from_surfaces (W):	Q_1	Q_2	Q_3	
	86560.29367	-14608.9353	-71951.35838	.....Ans.
Check: Q1 + Q2 + Q3 = 0	SumQ1Q2Q3 =		0.0	...Verified.

And, the Table gets filled up:

eps_1	Q_1 (W)	Q_12 (W)	SumQ1Q2Q3
0.1	10337.014	2237.752367	6.2355E-09
0.2	20482.572	5890.97896	1.437E-08
0.3	30441.943	9477.163321	1.1154E-08
0.4	40220.207	12998.13416	-1.01427E-08
0.5	49822.259	16455.65428	6.80302E-09
0.6	59252.819	19851.42351	-2.82307E-09
0.7	68516.441	23187.08151	6.0827E-09
0.8	77617.519	26464.21038	-1.47847E-08
0.9	86560.294	29684.3372	-1.4843E-08

Note that for each case, SumQ1Q2Q3 = 0 is satisfied.

Download free eBooks at bookboon.com

Now, plot the results:





Download free eBooks at bookboon.com

Click on the ad to read more



==========

Prob. 5.C.2.15. A cylindrical shaped furnace is 1 m dia and 1.2 m high. The top surface, having an emissivity of 0.7 emits a uniform heat flux of 7 kW/m^2. The bottom surface with an emissivity of 0.4 is maintained at 350 K. The sides are insulated and function as reradiating surfaces. Determine the heat transfer to bottom surface and also the temperature of top and sides.

(b) Also, plot Q1, T1 and T3 against J1, as J1 varies from 300 to 1100 W/m^2, other conditions remaining the same.



Fig.Prob.5.C.2.15 (a)

Download free eBooks at bookboon.com



Fig.Prob.5.C.2.15 (b)

EXCEL Solution:

Note that in this case heat flux at the top is given and not its emissive power. So, the flux is to be taken as radiosity of the surface. i.e. J1 = 7000 W/m^2. The equivalent radiation circuit is shown in Fig. (b) above.

Recollect that the Kirchoff's eqns for a general three surface enclosure are:

$$\text{Node } J_1: \quad \frac{E_{b1}-J_1}{R_1}+\frac{J_2-J_1}{R_{12}}+\frac{J_3-J_1}{R_{13}}=0 \qquad \text{.....(13.63,a)}$$

$$\text{Node } J_2: \quad \frac{E_{b2}-J_2}{R_2}+\frac{J_1-J_2}{R_{12}}+\frac{J_3-J_2}{R_{23}}=0 \qquad \text{.....(13.63,b)}$$

$$\text{Node } J_3: \quad \frac{E_{b3}-J_3}{R_3}+\frac{J_1-J_3}{R_{13}}+\frac{J_2-J_3}{R_{23}}=0 \qquad \text{.....(13.63,c)}$$

Solving these three eqns. simultaneously, we get J_1, J_2 and J_3.

However, in the above case, J1 is known, and Eb1 is to be found out.

Also, for Node J3, since Eb3 = J3, the first term in eqn for Node J3 will be zero. Therefore, eps3 does not enter in to calculations. Anyway, we enter eps3 = 0.99.

So, apply the Solver to solve for Eb1, J2 and J3 from the above three eqns; have a trial values for Eb1, J2 and J3 to start with, say equal to 1000 each.

Once Eb1 is obtained, get T1 from Eb1 = sigma * T1^4.

And, when J3 is known, get T3 from Eb3 = J3 = sigma * T3^4.

Use the Template prepared for the three surface enclosure.

Download free eBooks at bookboon.com

Next, In the EXCEL worksheet, enter data for the three surface enclosure problem, and name the cells:

F_13 | =1-F_12

	A	B	C	D	E
76		**Data:**			
77					
78		R_1 =	0.5	m	
79		R_2 =	0.5	m	
80		L =	1.2	m	
81		sigma (W/m2.K^4):	5.67E-08	W/m^2-K^4	
82					
83		Areas (m2):	A_1	A_2	A_3
84			0.785398163	0.785398163	3.769911184
85					
86		Emissivities:	eps_1	eps_2	eps_3
87			0.7	0.4	0.99
88					
89		View Factors:	F_11	F_12	F_13
90			0	0.13108	0.86892
91			F_21	F_22	F_23
92			0.13108	0	0.86892
93			F_31	F_32	F_33
94			0.181025	0.181025	0.63795

In the above, A_3 is the area of the cylindrical surface = 2.π.R.L

Download free eBooks at bookboon.com

View Factors:

View factor F12 is determined with the template explained earlier, using the VBA Function for View Factor of parallel discs. See the Formula bar below:



be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

This value of F_ij is transferred to cell D90 above. Other View factors are calculated using the View factor algebra:

Next, enter the T2 = 350 K, For T1 and T3 enter the formulas and put Eb3 = J3.

For Eb1, J2, J3 enter trial values of say, 1000 each, and continue the calculations:



T_1 | =(E_b1/sigma)^0.25

	A	B	C	D	E
97					
98		Temps. (K)	T_1	T_2	T_3
99			364.4217046	350	364.4217046
100					
101		E_b (W/m2)	E_b1	E_b2	E_b3
102			1.00E+03	8.51E+02	1.00E+03
103					
104		Resistances(m^-2):	R_1	R_2	R_3
105			0.545674091	1.909859317	2.68E-03
106					
107			R_12	R_13	R_23
108			9.713453957	1.465312738	1.465312738
109					
110		Radiosities (W/m2):	J_1	J_2	J_3
111			7000	1000	1000

In the above, trial values for E_b1, J2, J3 are entered. T1, T3 in cells C99 and E99 are calculated as:

$$T1 := \left(\frac{Eb1}{\sigma}\right)^{0.25}$$

$$T3 := \left(\frac{J3}{\sigma}\right)^{0.25}$$

Download free eBooks at bookboon.com

Next, important step to calculate Eb1, J2 and J3:

Enter the three Nodal equations as shown:



For Nodes 1, 2 and 3 enter the corresponding equations, obtained by applying Kirchoff's Law, are entered. Eqn for Node J3 can be seen in the Formula bar above.

Sum of the squares of C114 to C116 should be zero, but, in this case since Eb1, J2 and J3 are assumed values, the sum of squares is not zero.

Apply Solver to make C117 zero by changing Eb1, J2 and J3. (i.e. cells C102, D111 and E111.)

To do this: Go to Data – Solver:



Download free eBooks at bookboon.com

Click on Solver. We get the following window. Fill it up as shown:



The Wake
the only emission we want to leave behind
Low-speed Engines Medium-speed Engines Turbochargers Propellers Propulsion Packages PrimeServ
The design of eco-friendly marine power and propulsion solutions is crucial for MAN Diesel & Turbo.
Power competencies are offered with the world's largest engine programme – having outputs spanning from 450 to 87,220 kW per engine. Get up front!
Find out more at www.mandieselturbo.com
Engineering the Future – since 1758.
MAN Diesel & Turbo
MAN

Download free eBooks at bookboon.com

Click on the ad to read more

Click Solve. We get following message:



Solver has found a solution. Click OK to keep the solution. We get:



Observe that values of Eb1, J2 and J3 are shown in the respective cells.

Download free eBooks at bookboon.com

Also, note that temps T1 and T3 are calculated.

Sum_diff^2 is almost equal to zero.

And, results of equations at Nodes 1, 2 and 3 are almost equal to zero.

Next, continue the calculations for heat transfers:



C125 =(E_b1-J_1)/R_1

	A	B	C	D	E	F
112						
113		Apply Kirchoff's Law at each Node:				
114		Node J1:	0			
115		Node J2:	-8.6402E-12			
116		Node J3:	-9.77707E-12			
117		Sum_diff^2=	1.70244E-22			
118						
119		Apply Solver to make Sumdiff^2 a minimum, by varying J_1, J_2, and J_3:				
120						
121		Q_betwn_surfaces (W):	Q_12	Q_13	Q_23	
122			342.5044978	1135.218982	-1135.218982	.....Ans.
123						
124		Qnet_from_surfaces (W):	Q_1	Q_2	Q_3	
125			1477.723479	-1477.72348	0	.....Ans.
126						
127		Check: Q1 + Q2 + Q3 = 0	SumQ1Q2Q3 =		0.0	...Verified.

In the above, heat transfers from/to each surface (Q_1, Q_2 and Q_3), and also between surfaces (Q_12, Q_13, Q_23) are calculated using formulas given earlier. For ex. see in the Formula bar, the formula entered to calculate Q_1 in cell C125.

Negative sign for a heat transfer indicates heat coming ***in to*** the surface.

As a check: Sum of Q1, Q2 and Q3 should be zero.

Thus:

Q1 = 1477.72 W, Q2 = -1477.72 W , Eb1 = 7810 W/m^2, T1 = 609.14 K, T3 = 553.88 K … Ans.

Download free eBooks at bookboon.com

(b) Plot Q1, T1 and T3 against J1, as J1 varies from 3000 to 11000 W/m^2:

First, set up a Table as follows:

	A	B	C	D	E	F
130						
131		J1 (W/m^2)	Q_1 (W)	T1 (K)	T3 (K)	SumQ1Q2Q3
132		3000				
133		4000				
134		5000				
135		6000				
136		7000				
137		8000				
138		9000				
139		10000				
140		11000				

Now, write a VBA program to do the following:

Copy the first value of J1 from this Table to cell C111 in the Data section.

See the light!
The sooner you realize we are right, the sooner your life will get better!
A bit over the top? Yes we know!
We are just that sure that we can make your media activities more effective.

Get "Bookboon's Free Media Advice"
Email kbm@bookboon.com
bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com
Download free eBooks at bookboon.com
Click on the ad to read more

Then, all related values will change.

Apply the Solver to get Eb1, J2 and J3.

Immediately T1, T3 and all heat transfers will get up-dated.

Then, copy Q_1, T_1, T_3 and also SumQ1Q2Q3 (to check that it is zero) to the respective places in the Table.

Repeat these steps for the next value of J1, etc.

Following is the VBA program, operated by a control button:

```
' Macro1 Macro
' Finds J1, J2 and J3 making Sumdiff^2 minimum
'
' Keyboard Shortcut: Ctrl+Shift+J

Dim i As Integer

For i = 0 To 8 'start of For ... Next loop

    Range("C111") = Cells(132 + i, 2) 'copy the first value of J1 from the Table to cell C111

    'Following part of the code applies Solver to minimise cell C117 by changing cells D111:E111
    'and cell C102

    '-------------------------------------------------

    SolverOk SetCell:="$C$117", MaxMinVal:=2, ValueOf:="0", ByChange:= _
        "$D$111:$E$111, $C$102"
    SolverSolve UserFinish:=True
    SolverFinish KeepFinal:=1

    '-------------------------------------------------

    Cells(132 + i, 3) = Range("C125") 'copies up-dated value of Q_1 to its place in Table

    Cells(132 + i, 4) = Range("C99") 'copies up-dated value of T1 to its place in Table

    Cells(132 + i, 5) = Range("E99") 'copies up-dated value of T3 to its place in Table

    Cells(132 + i, 6) = Range("E127") 'copies up-dated value of SUMQ1Q2Q3 to its place in Table

 Next i

End Sub
```

Read the comments in the above program.

Download free eBooks at bookboon.com

Now, press the command button and the Solver is applied for each value of J1 and the Table gets filled up:

	A	B	C	D	E	F
130						
131		J1 (W/m^2)	Q_1 (W)	T1 (K)	T3 (K)	SumQ1Q2Q3
132		3000	516.469	490.493	454.460	1.14824E-11
133		4000	756.783	528.186	485.419	-6.82121E-13
134		5000	997.096	559.193	511.381	-7.95808E-13
135		6000	1237.410	585.761	533.901	2.04636E-12
136		7000	1477.723	609.139	553.885	-2.50111E-12
137		8000	1718.037	630.098	571.914	2.27374E-13
138		9000	1958.351	649.153	588.383	6.82121E-13
139		10000	2198.664	666.663	603.574	3.18323E-12
140		11000	2438.978	682.893	617.699	-4.54747E-13

Note that in each case, SumQ1Q2Q3 = 0 is satisfied.

Now, plot the results:



Download free eBooks at bookboon.com





==========

Prob. 5.C.2.16. Consider a cubical furnace, 1 m × 1 m × 1 m size. One of the vertical surfaces is at T1 = 1000 K, eps1 = 0.8, and the base is at 400 K, eps2 = 0.4. All other sides and top surface are insulated and can be considered as re-radiating. Calculate the net heat transfer from the surface 1, and the equilibrium temp of the re-radiating surfaces.

(b) Also, plot Q1 and T3 as T1 varies from 600 K to 1400 K.

Download free eBooks at bookboon.com

EXCEL Solution:

This problem is similar to Prob.5.C.2.15.

The schematic and the radiation circuit are shown below:



Fig.Prob.5.C.2.16

be > your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

Now, instead of solving it with the template prepared earlier, **let us write VBA Functions for Q1 and temp of re-radiating surface, TR.**

Recollect that the formulas for this case are:

To get Q1:

$$Q_1 = -Q_2 = \frac{E_{b1} - E_{b2}}{R_{tot}}$$

where, R_{tot} is the total resistance, given by:

$$R_{tot} = R_1 + \left[\frac{1}{\frac{1}{R_{12}} + \frac{1}{(R_{13} + R_{23})}}\right] + R_2$$

i.e. $$R_{tot} = \left(\frac{1-\varepsilon_1}{A_1 \cdot \varepsilon_1}\right) + \frac{1}{\left[A_1 \cdot F_{12} + \frac{1}{\left(\frac{1}{A_1 \cdot F_{13}} + \frac{1}{A_2 \cdot F_{23}}\right)}\right]} + \left(\frac{1-\varepsilon_2}{A_2 \cdot \varepsilon_2}\right) \quad \text{....(13.67)}$$

To get TR, first get JR by applying Kirchoff's Law to Node J3:

Applying Kirchoff's Law at J_3:

$$\frac{J1 - JR}{\frac{1}{A1 \cdot F1R}} = -\frac{J2 - JR}{\frac{1}{A2 \cdot F2R}}$$

i.e. $$JR \cdot (A1 \cdot F1R + A2 \cdot F2R) = J1 \cdot A1 \cdot F1R + J2 \cdot A2 \cdot F2R$$

i.e. $$JR = \frac{J1 \cdot A1 \cdot F1R + J2 \cdot A2 \cdot F2R}{(A1 \cdot F1R + A2 \cdot F2R)}$$

Then: $$TR = \left(\frac{JR}{\sigma}\right)^{0.25}$$

where σ = Stefan Boltzmann constant.

Download free eBooks at bookboon.com

Following is the VBA Functions to calculate Q1 and TR, using the above equations:

To determine heat transfer from surface 1, Q1:

```
Function Q_1_ThreeZoneEnclosure_with_ReradiatingSurface(A_1 As Double, A_2 As Double, _
F_12 As Double, F_1R As Double, F_2R As Double, eps_1 As Double, eps_2 As Double, _
T_1 As Double, T_2 As Double) As Double

'Gives Q_1 = -Q_2 (W) for the two grey surfaces,Q_R = 0 for re-radiating surface

Dim sigma As Double, R_1 As Double, R_2 As Double, XX As Double, YY As Double
Dim Eb_1 As Double, Eb_2 As Double

sigma = 0.0000000567 'W/m2.K^4
Eb_1 = sigma * T_1 ^ 4 'W/m^2, Emissive power of surface 1
Eb_2 = sigma * T_2 ^ 4 'W/m^2, Emissive power of surface 2

R_1 = (1 - eps_1) / (eps_1 * A_1) 'surface resistance of surface 1
R_2 = (1 - eps_2) / (eps_2 * A_2) 'surface resistance of surface 2

XX = ((1 / (A_1 * F_1R)) + (1 / (A_2 * F_2R))) ^ (-1)
YY = 1 / (A_1 * F_12 + XX)

 Q_1_ThreeZoneEnclosure_with_ReradiatingSurface = (Eb_1 - Eb_2) / (R_1 + YY + R_2)
End Function
```

To determine temp of re-radiating surface, TR:

```
Function T_R_ThreeZoneEnclosure_with_ReradiatingSurface(A_1 As Double, A_2 As Double, _
F_12 As Double, F_1R As Double, F_2R As Double, eps_1 As Double, eps_2 As Double, _
T_1 As Double, T_2 As Double) As Double
'Gives T_R (K) ..temp of re-radiating surface

Dim sigma As Double, R_1 As Double, R_2 As Double, XX As Double, YY As Double
Dim Eb_1 As Double, Eb_2 As Double, Q_1 As Double, Q_2 As Double
Dim J_1 As Double, J_2 As Double, J_R As Double

sigma = 0.0000000567 'W/m2.K^4
Eb_1 = sigma * T_1 ^ 4 'W/m^2, Emissive power of surface 1
Eb_2 = sigma * T_2 ^ 4 'W/m^2, Emissive power of surface 2
R_1 = (1 - eps_1) / (eps_1 * A_1) 'surface resistance of surface 1
R_2 = (1 - eps_2) / (eps_2 * A_2) 'surface resistance of surface 2
Q_1 = Q_1_ThreeZoneEnclosure_with_ReradiatingSurface(A_1, A_2, F_12, F_1R, F_2R, eps_1, _
eps_2, T_1, T_2) 'W/m2
Q_2 = -Q_1 '...by heat balance
J_1 = Eb_1 - Q_1 * R_1 'W/m2, Radiosity of surface 1
J_2 = Eb_2 - Q_2 * R_2 'W/m2, Radiosity of surface 2

'Apply Kirchoff's Law at J_3:

'(J_1-J_R)/((1/(A_1*F_1R))) = -(J_2-J_R)/((1/(A_2*F_2R)))
'J_R*(A_1*F_1R+A_2*F_2R) = J_1*A_1*F_1R+J_2*A_2*F_2R

'Then, Radiosity of re-radiating surface 3 i.e. JR is given by:

J_R = (J_1 * A_1 * F_1R + J_2 * A_2 * F_2R) / (A_1 * F_1R + A_2 * F_2R)

T_R_ThreeZoneEnclosure_with_ReradiatingSurface = (J_R / sigma) ^ 0.25

End Function
```

Download free eBooks at bookboon.com

Now, let us solve the above problem using these VBA Functions:

First, use the template to determine the View Factors for perpendicular rectangles:



Thus, F12 = 0.2 and the other View Factors are determined using View Factor algebra, as explained earlier.



Download free eBooks at bookboon.com

Click on the ad to read more

Now, set up the EXCEL worksheet, enter data and name the cells.

F_21 | =F_12*A_1/A_2

	A	B	C	D	E
76		**Data:**			
77					
78		**X =**	1	m	
79		**Y =**	1	m	
80		**Z =**	1	m	
81		sigma (W/m2.K^4):	5.67E-08	W/m^2-K^4	
82					
83		Areas (m2):	A_1	A_2	A_3
84			1	1	4.00E+00
85					
86		Emissivities:	eps_1	eps_2	eps_3
87			0.8	0.4	0.999
88					
89		View Factors:	F_11	F_12	F_13
90			0	0.2	0.8
91			F_21	F_22	F_23
92			0.2	0	0.8
93			F_31	F_32	F_33
94			0.2	0.2	0.6

Note that eps3 does not enter into any calculations; so, we just fill up eps_3 = 0.999

Next, fill up the temperatures T1 and T2, given in data. T3 (i.e. temp of reradiating surface is to be found out later, after finding out J3).

	A	B	C	D
97				
98		Temps. (K)	T_1	T_2
99			1000	400

Download free eBooks at bookboon.com

Now, to get Q1 and T3:

Use the VBA Functions written above:



Note that the Function for Q1 can be seen in the Formula bar above.

Similarly, Function for T3 can be seen in the Formula bar in the screen shot given below:



Thus:

Q1 = net heat transfer from surface 1 = 16170.29 W …. Ans.

TR = temp of re-radiating surfaces = 911.75 K … Ans.

(b) Also, plot Q1 and T3 as T1 varies from 600 K to 1400 K.

First, prepare a Table as shown below:



Download free eBooks at bookboon.com

Formula bar shows the Function entered for Q1 in cell C132.

Note that reference to T1 is by 'relative reference' so that we can 'drag-copy' till the end of Table.

Similarly, for T3 also, refer to T1 by relative reference, as shown below:



Now, select cells C132 to D132 and drag-copy till the end of the Table, i.e. up to cell D140.

Who is your target group?
And how can we reach them?
At Bookboon, you can segment the exact right audience for your advertising campaign.
Our eBooks offer in-book advertising spot to reach the right candidate.
Contact us to hear more
kbm@bookboon.com
bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com
Download free eBooks at bookboon.com
Click on the ad to read more

Immediately, all calculations are made and the Table is filled up:

	A	B	C	D
130				
131		T1 (K)	Q_1 (W)	T3 (K)
132		600	1725.893	557.534
133		700	3559.654	644.077
134		800	6372.527	732.469
135		900	10463.224	821.836
136		1000	16170.287	911.751
137		1100	23872.083	1001.992
138		1200	33986.810	1092.434
139		1300	46972.493	1183.008
140		1400	63326.985	1273.670

Now, plot the results in EXCEL:



Download free eBooks at bookboon.com



Next, consider what happens if surface 1 is black:

i.e. put eps1 = 0.999.

Immediately the results up date themselves in the worksheet:

	A	B	C	D	E	F	G	H	I	J	K	L	M	N
76		**Data:**						(a) Aligned, parallel rectangles:				(b) Coaxial, parallel disks:		
77								X =	1			r_i =	0.5	
78		X =	1	m				Y =	1			r_j =	0.5	
79		Y =	1	m				L =	0.5			L =	1.2	
80		Z =	1	m				F_ij =	0.415253			F_ij =	0.13108	
81		sigma (W/m2.K^4):	5.67E-08	W/m^2-K^4										
82								(c) Perpendicular rectangles with a common edge:						
83		Areas (m2):	A_1	A_2	A_3			X =	1					
84			1	1	4.00E+00			Y =	1					
85								Z =	1					
86		Emissivities:	eps_1	eps_2	eps_3			F_ij =	0.200044					
87			0.999	0.4	0.999									
88														
89		View Factors:	F_11	F_12	F_13									
90			0	0.2	0.8									
91			F_21	F_22	F_23		Results:							
92			0.2	0	0.8									
93			F_31	F_32	F_33		Q1	17441.4	W .... Ans.					
94			0.2	0.2	0.6		TR	928.536	K...Ans.					

Download free eBooks at bookboon.com

Now, Q1 = 17441.4 W, TR = 928.54 K … Ans.

Compare these values with Q1 = 16170.29 W and TR = 911.75 K obtained with eps1 = 0.8 earlier.

Also, observe that the Table and plots have also updated themselves:

T1 (K)	Q_1 (W)	T3 (K)
600	1861.559	565.419
700	3839.465	654.591
800	6873.448	745.245
900	11285.701	836.674
1000	17441.375	928.536
1100	25748.582	1020.654
1200	36658.391	1112.932
1300	50664.832	1205.314
1400	68304.893	1297.764

And:



Download free eBooks at bookboon.com



==========

Download free eBooks at bookboon.com

5D Radiation shields

Recollect: [Ref: 1]

For two infinite, parallel plates 1 and 2, radiation shield 3, be placed between the plates:



Fig.13.37 Radiation shield between two parallel plates, and associated radiation network

When there is no shield, the radiation heat transfer between plates 1 and 2 is already shown to be:

Brain power
By 2020, wind could provide one-tenth of our planet's electricity needs. Already today, SKF's innovative know-how is crucial to running a large proportion of the world's wind turbines.
Up to 25 % of the generating costs relate to maintenance. These can be reduced dramatically thanks to our systems for on-line condition monitoring and automatic lubrication. We help make it more economical to create cleaner, cheaper energy out of thin air.
By sharing our experience, expertise, and creativity, industries can boost performance beyond expectations.
Therefore we need the best employees who can meet this challenge!
The Power of Knowledge Engineering
Plug into The Power of Knowledge Engineering.
Visit us at www.skf.com/knowledge
SKF

Download free eBooks at bookboon.com

Click on the ad to read more

$$Q_{12} = \frac{A \cdot \sigma \cdot \left(T_1^4 - T_2^4 \right)}{\frac{1}{\varepsilon_1} + \frac{1}{\varepsilon_2} - 1} \quad \text{....for infinitely large parallel plates.....(13.59)}$$

$$Q_{12\_one\_shield} = \frac{A \cdot \sigma \cdot \left(T_1^4 - T_2^4 \right)}{\left(\frac{1}{\varepsilon_1} + \frac{1}{\varepsilon_2} - 1 \right) + \left(\frac{1}{\varepsilon_{3\_1}} + \frac{1}{\varepsilon_{3\_2}} - 1 \right)} \quad \text{....(13.71)}$$

If there are N radiation shields, we have, for net radiation heat transfer:

$$Q_{12_{N\_shields}} = \frac{A \cdot \sigma \cdot \left(T_1^4 - T_2^4 \right)}{\left(\frac{1}{\varepsilon_1} + \frac{1}{\varepsilon_2} - 1 \right) + \left(\frac{1}{\varepsilon_{3\_1}} + \frac{1}{\varepsilon_{3\_2}} - 1 \right) + \ldots.. + \left(\frac{1}{\varepsilon_{N\_1}} + \frac{1}{\varepsilon_{N\_2}} - 1 \right)} \quad \text{...(13.72)}$$

If emissivities of all surfaces are equal, eqn. (13.72) becomes:

$$Q_{12_{N\_shields}} = \frac{A \cdot \sigma \cdot \left(T_1^4 - T_2^4 \right)}{(N+1) \cdot \left(\frac{1}{\varepsilon} + \frac{1}{\varepsilon} - 1 \right)} = \frac{1}{(N+1)} \cdot \left(Q_{12_{no\_shield}} \right) \quad \text{....(13.73)}$$

==========

Prob.5.D.1. Write Mathcad Functions for: radiation heat transfer and temp of radiation shield for:

i) Heat transfer between two infinite, parallel plates with no radiation shield,
ii) Heat transfer between two infinite, parallel plates with ***one radiation shield*** in between,
iii) Heat transfer between two infinite, parallel plates with ***N radiation shields*** in between, and
iv) Temp of radiation shield for the case of one radiation shield between two parallel plates.

Mathcad Solution:

Inputs:

A … area of plates, m^2

eps1, eps2 …emissivities of two plates

eps_s1, eps_s2 .. emissivities of radiation shield, on the surfaces looking towards plates 1 and 2 respectively

Download free eBooks at bookboon.com

T1, T2 … temps of two plates, Kelvin

Output:

Q12 … W

T_shield … Kelvin

1. **Infinite parallel plates with no shield:**

$$Q12\_plate\_no\_shield(A, eps1, eps2, T1, T2) := \frac{5.67 \cdot 10^{-8} \cdot A \cdot \left(T1^4 - T2^4\right)}{\left(\frac{1}{eps1} + \frac{1}{eps2} - 1\right)}$$

---

2. **Infinite parallel plates with one shield in between:**

$$Q12\_plate\_one\_shield(A, eps1, eps2, eps\_s1, eps\_s2, T1, T2) := \frac{5.67 \cdot 10^{-8} \cdot A \cdot \left(T1^4 - T2^4\right)}{\left(\frac{1}{eps1} + \frac{1}{eps2} - 1\right) + \left(\frac{1}{eps\_s1} + \frac{1}{eps\_s2} - 1\right)}$$

---

3. **To determine the equilibrium temperature of the radiation shield:**

We can use either of the conditions: Q12 = Q13 or Q12 = Q32.

$$Q_{12} = Q_{13} = \frac{A \cdot \sigma \cdot \left(T_1^4 - T_3^4\right)}{\frac{1}{\varepsilon_1} + \frac{1}{\varepsilon_3} - 1} \quad \ldots(13.76,a)$$

or,

$$Q_{12} = Q_{32} = \frac{A \cdot \sigma \cdot \left(T_3^4 - T_2^4\right)}{\frac{1}{\varepsilon_3} + \frac{1}{\varepsilon_2} - 1} \quad \ldots.(13.76,b)$$

Download free eBooks at bookboon.com

Function for temp of Shield:

$T3 := 500$ .K...trial value

Given

$$Q12\_plate\_one\_shield(A, eps1, eps2, eps\_s1, eps\_s2, T1, T2) = \frac{A \cdot 5.67 \cdot 10^{-8} \cdot \left(T1^4 - T3^4\right)}{\frac{1}{eps1} + \frac{1}{eps\_s1} - 1}$$

$$T\_shield(A, eps1, eps2, eps\_s1, eps\_s2, T1, T2) := Find(T3)$$

When there are N shields, all of emissivity eps_s1 and eps_s2 on either side, plates 1 and 2 having emissivities eps1 and eps2:

$$Q12\_plate\_N\_shields(N, A, eps1, eps2, eps\_s1, eps\_s2, T1, T2) := \frac{A \cdot 5.67 \cdot 10^{-8} \cdot \left(T1^4 - T2^4\right)}{\left(\frac{1}{eps1} + \frac{1}{eps2} - 1\right) + N \cdot \left(\frac{1}{eps\_s1} + \frac{1}{eps\_s2} - 1\right)}$$

Note: In the above Function, if we put N = 1, we get Q12 with one shield.

==========

Prob.5.D.2. Two large plates at 800 K and 600 K have emissivities of 0.5 and 0.8 respectively. A radiation shield having emissivity of 0.1 on the surface facing 800 K plate and 0.05 on the surface facing 600 K plate is placed between the two plates in parallel direction with respect to the plates. Calculate:

1) The radiation heat transfer between the two plates in presence of the radiation shield
2) The equilibrium temp of the shield
3) The rate of heat transfer between the two plates without the presence of radiation shield [VTU – July–Aug. 2004]

(b) In addition, if the emissivity on the surface facing 800 K plate (i.e. eps_s1) varies from 0.05 to 0.35, plot the heat transfer between the two plates (Q12) and the temp of radiation shield.

Download free eBooks at bookboon.com



Fig.(a)



Fig.(b)

Mathcad Solution:

Data:

A := 1 m^2

eps1 := 0.5 eps2 := 0.8 eps_s1 := 0.1 eps_s2 := 0.05

T1 := 800 K T2 := 600 K

Calculations:

Use the Mathcad Functions written above:

Heat transfer with one shield:

Q12_plate_one_shield(A, eps1, eps2, eps_s1, eps_s2, T1, T2) = 508.032 **W.....Ans.**

Temp of the radiation shield:

T_shield(A, eps1, eps2, eps_s1, eps_s2, T1, T2) = 746.8 **K.....Ans.**

Heat transfer with no shield:

Q12_plate_no_shield(A, eps1, eps2, T1, T2) = 7.056×10^3 **W.....Ans.**

Note that it is very convenient to make these calculations quickly with Mathcad Functions.

Download free eBooks at bookboon.com

(b) In addition, plot the heat transfer between the two plates (Q12) and the temp of radiation shield if the emissivity on the surface facing 800 K plate (i.e. eps_s1) varies from 0.05 to 0.35:

Write the relevant quantities as functions of eps_s1:

$$Q12(eps\_s1) := Q12\_plate\_one\_shield(A, eps1, eps2, eps\_s1, eps\_s2, T1, T2)$$

$$Temp\_shield(eps\_s1) := T\_shield(A, eps1, eps2, eps\_s1, eps\_s2, T1, T2)$$

$eps\_s1 := 0.05, 0.07 .. 0.35$ ....define a range variable

Download free eBooks at bookboon.com

Click on the ad to read more

eps_s1 =	Q12(eps_s1) =	Temp_shield(eps_s1)
0.05	384.873	718.869
0.07	446.762	733.303
0.09	490.589	743.032
0.11	523.254	750.041
0.13	548.54	755.336
0.15	568.693	759.477
0.17	585.132	762.806
0.19	598.797	765.54
0.21	610.336	767.826
0.23	620.209	769.766
0.25	628.752	771.433
0.27	636.218	772.881
0.29	642.798	774.15
0.31	648.641	775.272
0.33	653.863	776.271
0.35	658.56	777.166

Now, plot the results:



Download free eBooks at bookboon.com



==========

Prob.5.D.3. Consider two large parallel plates, one at 1000 K with emissivity 0.8 and the other at 300 K having emissivity of 0.6. A radiation shield is placed between them. The shield has emissivity of 0.1 on the side facing hot plate and 0.3 on the surface facing cold plate. Calculate the percentage reduction in radiation heat transfer as a result of radiation shield. [VTU – May 2007]

Mathcad Solution:

Data:

A := 1 m^2

eps1 := 0.8 eps2 := 0.6 eps_s1 := 0.1 eps_s2 := 0.3

T1 := 1000 K T2 := 300 K

Calculations:

Use the Mathcad Functions written above:

Heat transfer with no shield:

Q12_no_shield := Q12_plate_no_shield(A, eps1, eps2, T1, T2)

i.e. Q12_no_shield = 2.934×10^4 **W....Ans.**

Download free eBooks at bookboon.com

Heat transfer with one shield:

Q12_with_shield := Q12_plate_one_shield(A, eps1, eps2, eps_s1, eps_s2, T1, T2)

i.e. $Q12\_with\_shield = 3.947 \times 10^{3}$ **W....Ans.**

Therefore:

$$Percent\_reduction := \frac{Q12\_no\_shield - Q12\_with\_shield}{Q12\_no\_shield} \cdot 100$$

i.e. $Percent\_reduction = 86.55$ **%....percent reduction due to radiation shield ... Ans.**

==========

Prob.5.D.4. Two large plates at 800 C and 300 C have emissivities of 0.3 and 0.5 respectively. A radiation shield having emissivity of 0.05 on both sides is placed between the two plates. Calculate:

1) The heat transfer between the two plates without radiation shield
2) The equilibrium temp of the shield
3) The rate of heat transfer between the two plates with the presence of radiation shield
   [VTU – June 2012]

Mathcad Solution:

Data:

A := 1 m^2

eps1 := 0.3 eps2 := 0.5 eps_s1 := 0.05 eps_s2 := 0.05

T1 := 1073 K T2 := 573 K

Calculations:

Use the Mathcad Functions written above:

Heat transfer with no shield:

$Q12\_plate\_no\_shield(A, eps1, eps2, T1, T2) = 1.593 \times 10^{4}$ **W.....Ans.**

Download free eBooks at bookboon.com

Temp of the radiation shield:

$T\_shield(A, eps1, eps2, eps\_s1, eps\_s2, T1, T2) = 914.019$ **K.....Ans.**

Heat transfer with one shield:

$Q12\_plate\_one\_shield(A, eps1, eps2, eps\_s1, eps\_s2, T1, T2) = 1.593 \times 10^3$ **W.....Ans.**

(b) In addition, plot the heat transfer between the two plates (Q12) and the temp of radiation shield if the emissivities on either side of shield (i.e. eps_s1 and eps_s2) vary from 0.05 to 0.35:

Let eps_s = eps_s1 = eps_s2

Write the relevant quantities as functions of eps_s:

$Q12(eps\_s) := Q12\_plate\_one\_shield(A, eps1, eps2, eps\_s, eps\_s, T1, T2)$

$Temp\_shield(eps\_s) := T\_shield(A, eps1, eps2, eps\_s, eps\_s, T1, T2)$

Download free eBooks at bookboon.com

Click on the ad to read more

eps_s := 0.05, 0.07.. 0.35 ....define a range variable

eps_s =	Q12(eps_s) =	Temp_shield(eps_s)
0.05	$1.593 \cdot 10^3$	914.019
0.07	$2.164 \cdot 10^3$	911.814
0.09	$2.702 \cdot 10^3$	909.722
0.11	$3.209 \cdot 10^3$	907.734
0.13	$3.689 \cdot 10^3$	905.844
0.15	$4.143 \cdot 10^3$	904.043
0.17	$4.573 \cdot 10^3$	902.326
0.19	$4.982 \cdot 10^3$	900.686
0.21	$5.37 \cdot 10^3$	899.119
0.23	$5.74 \cdot 10^3$	897.621
0.25	$6.092 \cdot 10^3$	896.185
0.27	$6.429 \cdot 10^3$	894.809
0.29	$6.75 \cdot 10^3$	893.489
0.31	$7.056 \cdot 10^3$	892.222
0.33	$7.35 \cdot 10^3$	891.004
0.35	$7.632 \cdot 10^3$	889.832

Now, plot the results:



Download free eBooks at bookboon.com



==========

Prob.5.D.5. Two large plates have emissivities of 0.8 each. A radiation shield is place in between them. What should be its emissivity on either surface to reduce the radiation heat transfer between the surfaces by a factor of 10?

Mathcad Solution:

Data:

eps1 := 0.8 eps2 := 0.8

Let eps_s = eps_s1 = eps_s2 ...emissivity of shield

Calculations:

We have:

$$Q12\_plate\_no\_shield = \frac{5.67\cdot 10^{-8}\cdot A\cdot\left(T1^4 - T2^4\right)}{\left(\frac{1}{eps1} + \frac{1}{eps2} - 1\right)}$$

Download free eBooks at bookboon.com

$$Q12\_plate\_one\_shield = \frac{5.67\cdot 10^{-8}\cdot A\cdot\left(T1^4 - T2^4\right)}{\left(\frac{1}{eps1} + \frac{1}{eps2} - 1\right) + \left(\frac{1}{eps\_s} + \frac{1}{eps\_s} - 1\right)}$$

Taking their ratio:

$$\frac{Q12\_plate\_one\_shield}{Q12\_plate\_no\_shield} = \frac{\left(\frac{1}{eps1} + \frac{1}{eps2} - 1\right)}{\left[\left(\frac{1}{eps1} + \frac{1}{eps2} - 1\right) + \left(\frac{1}{eps\_s} + \frac{1}{eps\_s} - 1\right)\right]}$$

Then, since their ratio is 1/10 by data, we have:

$$\frac{\left(\frac{1}{eps1} + \frac{1}{eps2} - 1\right)}{\left[\left(\frac{1}{eps1} + \frac{1}{eps2} - 1\right) + \left(\frac{1}{eps\_s} + \frac{1}{eps\_s} - 1\right)\right]} = \frac{1}{10}$$



Download free eBooks at bookboon.com

Click on the ad to read more

Solving:

$$\left[\left(\frac{1}{eps1}+\frac{1}{eps2}-1\right)+\left(\frac{1}{eps\_s}+\frac{1}{eps\_s}-1\right)\right]=10\cdot\left(\frac{1}{eps1}+\frac{1}{eps2}-1\right)$$

i.e. $$\frac{2}{eps\_s}-1=10\cdot\left(\frac{1}{eps1}+\frac{1}{eps2}-1\right)-\left(\frac{1}{eps1}+\frac{1}{eps2}-1\right)$$

i.e. $$eps\_s:=\frac{2}{1+\left[10\cdot\left(\frac{1}{eps1}+\frac{1}{eps2}-1\right)-\left(\frac{1}{eps1}+\frac{1}{eps2}-1\right)\right]}$$

i.e. $eps\_s = 0.138$ **..required emissivity of shield to reduce heat transfer to one-tenth..Ans.**

==========

Prob.5.D.6. The net radiation from the surface of two parallel plates maintained at temperatures T1 and T2 is to be reduced by 79 times. Calculate the no. of screens to be placed between two surfaces to achieve this reduction in heat exchange, assuming the emissivity of screens as 0.05 and that of surfaces as 0.8. [M.U. 1997]

Mathcad Solution:

Data:

$eps1 := 0.8$ $eps2 := 0.8$ $eps\_s := 0.05$

Download free eBooks at bookboon.com

Calculations:

Let N be the no. of screens required.

N := 5 ... trial value

Given

$$\frac{\frac{1}{eps1}+\frac{1}{eps2}-1}{\left(\frac{1}{eps1}+\frac{1}{eps2}-1\right)+N\cdot\left(\frac{1}{eps\_s}+\frac{1}{eps\_s}-1\right)}=\frac{1}{79}$$

Find(N) = 3 **....No. of screens reqd.... Ans.**

==========

Prob.5.D.7. Two very large parallel plates with emissivities 0.3 and 0.7, exchange heat. Find the percentage reduction in radiation in heat transfer when *two* polished Aluminium radiation shields (ε_s = 0.4) are placed between them. [M.U. Dec. 2000]

Mathcad Solution:

Data:

eps1 := 0.3 eps2 := 0.7 eps_s := 0.4

Calculatiobs:

We have:

$$\frac{\frac{1}{eps1}+\frac{1}{eps2}-1}{\left(\frac{1}{eps1}+\frac{1}{eps2}-1\right)+2\cdot\left(\frac{1}{eps\_s}+\frac{1}{eps\_s}-1\right)}=0.32$$

i.e. by introducing 2 radiation shields, the heat transfer is reduced to 32% of that without the shields…..Ans.

==========

Download free eBooks at bookboon.com

Prob.5.D.8. Write Mathcad Functions for radiation heat transfer and temp of radiation shield for:

1) Heat transfer between two infinite, concentric cylinders with no radiation shield,
2) Heat transfer between two infinite, concentric cylinders with ***one radiation shield*** in between,
3) Heat transfer between two infinite, concentric cylinders with ***two radiation shields*** in between, and,
4) Temp of radiation shield for the case of ***one*** radiation shield between two concentric cylinders.

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.
Download free eBooks at bookboon.com
Click on the ad to read more

Recollect:

For concentric cylinders:



Fig.(a)



Fig.(b)

For concentric cylinders with no radiation shield:

$$Q_{12} = \frac{A_1 \cdot \sigma \cdot \left(T_1^4 - T_2^4\right)}{\frac{1}{\varepsilon_1} + \left(\frac{A_1}{A_2}\right) \cdot \left(\frac{1}{\varepsilon_2} - 1\right)}$$

....for infinitely long concentric cylinders.....(13.60)

where

$$\frac{A_1}{A_2} = \frac{r_1}{r_2}$$

Download free eBooks at bookboon.com

For concentric cylinders with one radiation shield in between:

$$Q_{12_{one\_shield}} = \frac{A_1 \cdot \sigma \cdot \left(T_1^4 - T_2^4\right)}{\frac{1}{\varepsilon_1} + \left(\frac{A_1}{A_2}\right)\cdot\left(\frac{1}{\varepsilon_2} - 1\right) + \left(\frac{A_1}{A_3}\right)\cdot\left(\frac{1}{\varepsilon_{3\_1}} + \frac{1}{\varepsilon_{3\_2}} - 1\right)}$$

...for concentric cylinders with one radiation shield...(13.77)

In eqn. (13.77), we have: $(A_1/A_2) = (r_1/r_2)$, and $(A_1/A_3) = (r_1/r_3)$.

Mathcad Solution:

Inputs:

R1, R2, R_shield …radii of inner cylinder, outer cylinder and the radiation shield placed between them

A1, A2 … surface areas of inner and outer cylinders, m^2

eps1, eps2 …emissivities of inner and outer cylinders facing each other

eps_s1, eps_s2 .. emissivities of radiation shield, on the surfaces looking towards inner cylinder 1 and outer cylinder 2 respectively

T1, T2 … temps of two cylinders, Kelvin

Output:

Q12 … W,

T_shield … Kelvin

1. Q12 for Long, concentric cylinders, with no radiation shield:

$$Q12\_Concentric\_cyl(R1, R2, L, eps1, eps2, T1, T2) := \frac{5.67\cdot10^{-8}\cdot(2\cdot\pi\cdot R1\cdot L)\cdot\left(T1^4 - T2^4\right)}{\frac{1}{eps1} + \left(\frac{R1}{R2}\right)\cdot\left(\frac{1}{eps2} - 1\right)}$$

Download free eBooks at bookboon.com

2. Q12 for Long, concentric cylinders, with one radiation shield:

$$Q12\_Concentric\_cyl\_One\_shield(R1,R2,R\_shield,L,eps1,eps2,eps\_s1,eps\_s2,T1,T2) :=$$

$$\frac{5.67\cdot10^{-8}\cdot(2\cdot\pi\cdot R1\cdot L)\cdot\left(T1^4-T2^4\right)}{\frac{1}{eps1}+\left(\frac{R1}{R2}\right)\cdot\left(\frac{1}{eps2}-1\right)+\left(\frac{R1}{R\_shield}\right)\cdot\left(\frac{1}{eps\_s1}+\frac{1}{eps\_s2}-1\right)}$$

---

3. Q12 for Long, concentric cylinders, with two radiation shields:

$$Q12\_Concentric\_cyl\_Two\_shields(R1,R2,R\_s1,R\_s2,L,eps1,eps2,eps\_s1,eps\_s2,T1,T2) :=$$

$$\frac{5.67\cdot10^{-8}\cdot(2\cdot\pi\cdot R1\cdot L)\cdot\left(T1^4-T2^4\right)}{\frac{1}{eps1}+\left(\frac{R1}{R2}\right)\cdot\left(\frac{1}{eps2}-1\right)+\left(\frac{R1}{R\_s1}\right)\cdot\left(\frac{1}{eps\_s1}+\frac{1}{eps\_s2}-1\right)+\left(\frac{R1}{R\_s2}\right)\cdot\left(\frac{1}{eps\_s1}+\frac{1}{eps\_s2}-1\right)}$$

The Wake
the only emission we want to leave behind
Low-speed Engines Medium-speed Engines Turbochargers Propellers Propulsion Packages PrimeServ
The design of eco-friendly marine power and propulsion solutions is crucial for MAN Diesel & Turbo. Power competencies are offered with the world's largest engine programme – having outputs spanning from 450 to 87,220 kW per engine. Get up front!
Find out more at www.mandieselturbo.com
Engineering the Future – since 1758.
MAN Diesel & Turbo
MAN

Click on the ad to read more

4. Temp. of radiation shield (T3), kept between concentric cylinders:

Equilibrium temp. of shield:

Let the equilibrium temp. of shield be T_3.

In steady state, we have:

$$Q_{12\_one\_shield} = Q_{13} = Q_{32}$$

Q_{12} with one shield is already calculated. Q_{13} or Q_{32} is calculated using eqn.for concentric cylinders with no shield.

Let us take: $Q_{12\_one\_shield} = Q_{13}$

i.e. $$Q_{12\_one\_shield} = \frac{A1 \cdot \sigma \cdot \left(T1^4 - T3^4\right)}{\frac{1}{\varepsilon_1} + \left(\frac{A1}{A3}\right) \cdot \left(\frac{1}{\varepsilon_{31}} - 1\right)}$$

Applying the above equation, we write, using the 'Solve block' of Mathcad:

T3 := 300 K....trial value

Given

$$\frac{\left(T1^4 - T2^4\right)}{\frac{1}{eps1} + \left(\frac{R1}{R2}\right) \cdot \left(\frac{1}{eps2} - 1\right) + \left(\frac{R1}{R\_shield}\right) \cdot \left(\frac{1}{eps\_s1} + \frac{1}{eps\_s2} - 1\right)} = \frac{\left(T1^4 - T3^4\right)}{\frac{1}{eps1} + \left(\frac{R1}{R\_shield}\right) \cdot \left(\frac{1}{eps\_s1} - 1\right)}$$

$$T_{shield}(R1, R2, R\_shield, eps1, eps2, eps\_s1, eps\_s2, T1, T2) := Find(T3)$$

Note: In the above, T_shield is written as a function of R1, R2,….T1, T2.

This will make it very convenient to calculate the temp of shield, and also to make parametric analysis and draw graphs.

==========

Download free eBooks at bookboon.com

Prob.5.D.9. Write Mathcad Functions for radiation heat transfer and temp of radiation shield for:

1) Heat transfer between two concentric spheres with no radiation shield,
2) Heat transfer between two concentric spheres with ***one radiation shield*** in between,
3) Heat transfer between two concentric spheres with ***two radiation shields*** in between, and,
4) Temp of radiation shield for the case of ***one*** radiation shield between two concentric spheres

Recollect:

For concentric spheres:



Fig.(a)



Fig.(b)

For concentric spheres with no radiation shield:

$$Q_{12} = \frac{A_1 \cdot \sigma \cdot \left(T_1^4 - T_2^4\right)}{\frac{1}{\varepsilon_1} + \left(\frac{A_1}{A_2}\right) \cdot \left(\frac{1}{\varepsilon_2} - 1\right)} \quad \cdots \text{ for concentric spheres}$$

Download free eBooks at bookboon.com

For concentric spheres with one radiation shield in between:

$$Q_{12_{one\_shield}} = \frac{A_1 \cdot \sigma \cdot \left(T_1^4 - T_2^4\right)}{\frac{1}{\varepsilon_1} + \left(\frac{A_1}{A_2}\right)\cdot\left(\frac{1}{\varepsilon_2} - 1\right) + \left(\frac{A_1}{A_3}\right)\cdot\left(\frac{1}{\varepsilon_{3\_1}} + \frac{1}{\varepsilon_{3\_2}} - 1\right)}$$

···· for concentric spheres with one radiation shield

In the above eqns. we have:

$$\frac{A_1}{A_2} = \left(\frac{r_1}{r_2}\right)^2 \quad \text{and,} \quad \frac{A_1}{A_3} = \left(\frac{r_1}{r_3}\right)^2$$

See the light!
The sooner you realize we are right, the sooner your life will get better!

A bit over the top? Yes we know!

We are just that sure that we can make your media activities more effective.

Get "Bookboon's Free Media Advice"
Email kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

Mathcad Solution:

Inputs:

R1, R2, R_shield …radii of inner cylinder, outer cylinder and the radiation shield placed between them

A1, A2 … surface areas of inner and outer cylinders, m^2

eps1, eps2 …emissivities of inner and outer cylinders facing each other

eps_s1, eps_s2 .. emissivities of radiation shield, on the surfaces looking towards inner cylinder 1 and outer cylinder 2 respectively

T1, T2 … temps of two cylinders, Kelvin

Output:

Q12 … W

Temp_shield … Kelvin

1. Q12 for concentric spheres, with no radiation shield:

$$Q12\_Concentric\_spheres(R1,R2,eps1,eps2,T1,T2) := \frac{5.67\cdot10^{-8}\cdot\left(4\cdot\pi\cdot R1^{2}\right)\cdot\left(T1^{4}-T2^{4}\right)}{\frac{1}{eps1}+\left(\frac{R1}{R2}\right)^{2}\cdot\left(\frac{1}{eps2}-1\right)}$$

---

2. Q12 for concentric spheres, with *one* radiation shield:

$$Q12\_Concentric\_sph\_One\_shield(R1,R2,R\_shield,eps1,eps2,eps\_s1,eps\_s2,T1,T2) :=$$

$$\frac{5.67\cdot10^{-8}\cdot\left(4\cdot\pi\cdot R1^{2}\right)\cdot\left(T1^{4}-T2^{4}\right)}{\frac{1}{eps1}+\left(\frac{R1}{R2}\right)^{2}\cdot\left(\frac{1}{eps2}-1\right)+\left(\frac{R1}{R\_shield}\right)^{2}\cdot\left(\frac{1}{eps\_s1}+\frac{1}{eps\_s2}-1\right)}$$

Download free eBooks at bookboon.com

3. Q12 for concentric spheres, with *two* radiation shields:

$$Q12\_Concentric\_sph\_Two\_shields(R1,R2,R\_s1,R\_s2,eps1,eps2,eps\_s1,eps\_s2,T1,T2) :=$$

$$\frac{5.67\cdot10^{-8}\cdot\left(4\cdot\pi\cdot R1^2\right)\cdot\left(T1^4 - T2^4\right)}{\frac{1}{eps1} + \left(\frac{R1}{R2}\right)^2\cdot\left(\frac{1}{eps2} - 1\right) + \left(\frac{R1}{R\_s1}\right)^2\cdot\left(\frac{1}{eps\_s1} + \frac{1}{eps\_s2} - 1\right) + \left(\frac{R1}{R\_s2}\right)^2\cdot\left(\frac{1}{eps\_s1} + \frac{1}{eps\_s2}\right)}$$

---

4. Temp of radiation shield (T3), kept between concentric spheres:

Equilibrium temp. of shield:

Let the equilibrium temp. of shield be T_3.

In steady state, we have:

$$Q_{12\_one\_shield} = Q_{13} = Q_{32}$$

Q_{12} with one shield is already calculated. Q_{13} or Q_{32} is calculated using eqn.for concentric spheres with no shield.

Let us take: $Q_{12\_one\_shield} = Q_{13}$

i.e. $$Q_{12\_one\_shield} = \frac{A1\cdot\sigma\cdot\left(T1^4 - T3^4\right)}{\frac{1}{\varepsilon_1} + \left(\frac{A1}{A3}\right)\cdot\left(\frac{1}{\varepsilon_{31}} - 1\right)}$$

Remember that now, surface area ratio, (A1/A3) = $(R1/R\_shield)^2$ for a sphere.

Applying the above equation, we write, using the 'Solve block' of Mathcad:

T3 := 300 K....trial value

Given

$$\frac{\left(T1^4 - T2^4\right)}{\frac{1}{eps1} + \left(\frac{R1}{R2}\right)^2\cdot\left(\frac{1}{eps2} - 1\right) + \left(\frac{R1}{R\_shield}\right)^2\cdot\left(\frac{1}{eps\_s1} + \frac{1}{eps\_s2} - 1\right)} = \frac{\left(T1^4 - T3^4\right)}{\frac{1}{eps1} + \left(\frac{R1}{R\_shield}\right)^2\cdot\left(\frac{1}{eps\_s1} - 1\right)}$$

$$Temp_{shield}(R1,R2,R\_shield,eps1,eps2,eps\_s1,eps\_s2,T1,T2) := Find(T3)$$

Download free eBooks at bookboon.com

Note: In the above, Temp_shield is written as a function of R1, R2,….T1, T2.

This will make it very convenient to calculate the temp of shield, and also to make parametric analysis and draw graphs.

==========

Prob.5.D.10. Two long, concentric cylinders have diameters of 40 and 80 mm. The inside cylinder is at 800 C and the outer cylinder is at 100 C. Inside and outside emissivities are 0.8 and 0.4. Calculate the percent reduction in heat transfer if a cylindrical shield of 60 mm dia and emissivity of 0.3 is placed between the cylinders. Also, calculate the equilibrium temp of the shield.

(b) Plot the percent reduction in heat transfer and the Shield temp as emissivity (on either side) of shield varies from 0.05 to 0.35.

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more



Fig.(a)

Mathcad Solution:

Let us use the Mathcad Functions written above in Prob.5.D.8.

Data:

R1 := 0.02 m R2 := 0.04 m R_shield := 0.03 m L := 1 m .... assumed

eps1 := 0.8 eps2 := 0.4 eps_s1 := 0.3 eps_s2 := 0.3

T1 := 1073 K T2 := 373 K

Calculations:

Heat transfer with no shield:

Q12_no_shield := Q12_Concentric_cyl(R1, R2, L, eps1, eps2, T1, T2)

i.e. Q12_no_shield = 4.653×10^3 **W .... Ans.**

Heat transfer with one radiation shield:

Q12_with_shield := Q12_Concentric_cyl_One_shield(R1, R2, R_shield, L, eps1, eps2, eps_s1, eps_s2, T1, T2)

i.e. Q12_with_shield = 1.611×10^3 **W .... Ans.**

Download free eBooks at bookboon.com

Therefore:

$$Percent\_reduction := \frac{Q12\_no\_shield - Q12\_with\_shield}{Q12\_no\_shield} \cdot 100$$

i.e. Percent_reduction = 65.385 **% .... reduction because of the shield....Ans.**

Equilibrium temp of the Shield:

$$T\_shield := T_{shield}(R1, R2, R\_shield, eps1, eps2, eps\_s1, eps\_s2, T1, T2)$$

i.e. T_shield = 911.835 **K = 638.835 C .... Ans.**

Plot the percent reduction in heat transfer and the Shield temp as emissivity (on either side) of shield varies from 0.05 to 0.35:

Write the relevant quantities as functions of eps_s:

Let: eps_s1 = eps_s2 = eps_s ....since emissivity on either side of shield is same

Then, we have:

$$Q12\_no\_shield := Q12\_Concentric\_cyl(R1, R2, L, eps1, eps2, T1, T2)$$ ..does not depend on eps_s

$$Q12\_with\_shield(eps\_s) := Q12\_Concentric\_cyl\_One\_shield(R1, R2, R\_shield, L, eps1, eps2, eps\_s, eps\_s, T1, T2)$$

$$Percent\_reduction(eps\_s) := \frac{Q12\_no\_shield - Q12\_with\_shield(eps\_s)}{Q12\_no\_shield} \cdot 100$$

$$T\_shield(eps\_s) := T_{shield}(R1, R2, R\_shield, eps1, eps2, eps\_s, eps\_s, T1, T2)$$

Download free eBooks at bookboon.com

Now, compute the Parametric Table and plot the graphs:

eps_s := 0.05, 0.07.. 0.35 .....define a range variable

eps_s =	Percent_reduction(eps_s)	T_shield(eps_s)
0.05	92.857	906.864
0.07	90.187	907.351
0.09	87.615	907.819
0.11	85.135	908.269
0.13	82.743	908.703
0.15	80.435	909.122
0.17	78.205	909.525
0.19	76.05	909.915
0.21	73.967	910.291
0.23	71.951	910.654
0.25	70	911.005
0.27	68.11	911.345
0.29	66.279	911.674
0.31	64.504	911.993
0.33	62.782	912.302
0.35	61.111	912.601



Download free eBooks at bookboon.com



==========

Prob.5.D.11. A spherical tank with diameter D1 = 40 cm, filled with a cryogenic fluid at T1 = 100 K, is placed inside a spherical container of diameter D2 = 60 cm, maintained at T2 = 300 K. Emissivities of inner and outer tanks are $\varepsilon 1 = 0.10$ and $\varepsilon 2 = 0.20$ respectively.



Download free eBooks at bookboon.com

Click on the ad to read more

1) Find the rate of heat loss into the inner vessel by radiation
2) If a spherical radiation shield of diameter D3 = 50 cm, with an emissivity **ε**3 = 0.05 on both surfaces is placed between the spheres, what is the new rate of heat loss?

[M.U. Jan. 2002]



Fig.(a)



Fig.(b)

Fig. Prob.5.D.11

Mathcad Solution:

Let us use the Mathcad Functions written above in Prob.5.D.9.

Data:

R1 := 0.2 m R2 := 0.3 m R_shield := 0.25 m

eps1 := 0.1 eps2 := 0.2 eps_s1 := 0.05 eps_s2 := 0.05

T1 := 100 K T2 := 300 K

Download free eBooks at bookboon.com

Calculations:

Heat transfer with no shield:

Q12_no_shield := Q12_Concentric_spheres(R1, R2, eps1, eps2, T1, T2)

i.e. Q12_no_shield = −19.359 **W ....negative sign indicates heat flow into the inner cylinder... Ans.**

Heat transfer with one radiation shield:

Q12_with_shield := Q12_Concentric_sph_One_shield(R1, R2, R_shield, eps1, eps2, eps_s1, eps_s2, T1, T2)

i.e. Q12_with_shield = −6.206 **W ..negative sign indicates heat flow into the inner cylinder.... Ans.**

Therefore:

$$\text{Percent\_reduction} := \frac{\text{Q12\_no\_shield} - \text{Q12\_with\_shield}}{\text{Q12\_no\_shield}} \cdot 100$$

i.e. Percent_reduction = 67.941 **% .... reduction because of the shield....Ans.**

Equilibrium temp of the Shield:

$$\text{T\_shield} := \text{Temp}_{\text{shield}}(\text{R1}, \text{R2}, \text{R\_shield}, \text{eps1}, \text{eps2}, \text{eps\_s1}, \text{eps\_s2}, \text{T1}, \text{T2})$$

i.e. T_shield = 264.919 **K = - 8.08 C .... Ans.**

Plot the percent reduction in heat transfer and the Shield temp as emissivity (on either side) of shield varies from 0.05 to 0.35:

Write the relevant quantities as functions of eps_s:

Let: eps_s1 = eps_s2 = eps_s ....since emissivity on either side of shield is same

Then, we have:

Download free eBooks at bookboon.com

$$Q12\_no\_shield := Q12\_Concentric\_spheres(R1, R2, eps1, eps2, T1, T2) \quad \text{..does not depend on eps\_s}$$

$$Q12\_with\_shield(eps\_s) := Q12\_Concentric\_sph\_One\_shield(R1, R2, R\_shield, eps1, eps2, eps\_s, eps\_s, T1, T2)$$

$$Percent\_reduction(eps\_s) := \frac{Q12\_no\_shield - Q12\_with\_shield(eps\_s)}{Q12\_no\_shield} \cdot 100$$

$$T\_shield(eps\_s) := Temp_{shield}(R1, R2, R\_shield, eps1, eps2, eps\_s, eps\_s, T1, T2)$$

Who is your target group? And how can we reach them?

At Bookboon, you can segment the exact right audience for your advertising campaign.

Our eBooks offer in-book advertising spot to reach the right candidate.

Contact us to hear more
kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

Now, compute the Parametric Table and plot the graphs:

eps_s := 0.05, 0.07.. 0.35 .....define a range variable

eps_s =	Percent_reduction(eps_s)	T_shield(eps_s)
0.05	67.941	264.919
0.07	59.972	267.637
0.09	53.558	269.765
0.11	48.284	271.478
0.13	43.872	272.886
0.15	40.127	274.066
0.17	36.907	275.067
0.19	34.109	275.928
0.21	31.656	276.677
0.23	29.487	277.334
0.25	27.556	277.915
0.27	25.826	278.432
0.29	24.266	278.896
0.31	22.854	279.315
0.33	21.568	279.694
0.35	20.393	280.039



Download free eBooks at bookboon.com



==========

Prob.5.D.12. Write EES Functions for radiation heat transfer without and with radiation shield for the cases of: (i) infinite, parallel plates (ii) infinite, concentric cylinders, and (iii) concentric spheres. Also write Functions to determine the equilibrium temp of the radiation shield.

EES Solutions:

Equations for these cases are already given earlier.

Now, the EES Functions:

In the following Functions:

Inputs:

In case of cylinders and spheres:

1…. denotes the inner cylinder / sphere, and]

2… denotes outer cylinder / sphere

R1 …. Radius of inner cylinder / sphere, (m)

R2 …. Radius of outer cylinder / sphere, (m)

R_shield …. Radius of radation shield placed between 1 and 2, (m)

Download free eBooks at bookboon.com

A … area of plates, (m^2)

eps1, eps2 …emissivities of two plates or cylinders or spheres

eps_s1, eps_s2 .. emissivities of radiation shield, on the faces looking towards surfaces 1 and 2 respectively

T1, T2 … temps of two plates or cylinders or spheres, (K)

Output:

Q12 … net heat transfer between surfaces 1 and 2, (W)

T_shield … equilibrium temp of shield, (K)

$UnitSystem SI Pa J C

FUNCTION Q12_parallel_plates(A,eps_1,eps_2,T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Brain power
By 2020, wind could provide one-tenth of our planet's electricity needs. Already today, SKF's innovative know-how is crucial to running a large proportion of the world's wind turbines.
Up to 25 % of the generating costs relate to maintenance. These can be reduced dramatically thanks to our systems for on-line condition monitoring and automatic lubrication. We help make it more economical to create cleaner, cheaper energy out of thin air.
By sharing our experience, expertise, and creativity, industries can boost performance beyond expectations.
Therefore we need the best employees who can meet this challenge!
The Power of Knowledge Engineering
Plug into The Power of Knowledge Engineering.
Visit us at www.skf.com/knowledge
SKF

Download free eBooks at bookboon.com

Click on the ad to read more

Q12_parallel_plates:=(A * sigma * (T1^4 – T2^4)) / (1/eps_1 + 1/eps_2 -1)

END

"----------"

FUNCTION Q12_parallel_plates_one_shield(A, eps_1, eps_2, eps_s1, eps_s2, T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Q12_parallel_plates_one_shield:=(A * sigma * (T1^4 – T2^4)) / ((1/eps_1 + 1/eps_2 -1) + (1 / eps_s1 + 1/eps_s2 -1))

END

"----------"

FUNCTION Temp_Shield_parallel_plates(A, eps_1, eps_2, eps_s1, eps_s2, T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Temp_Shield_parallel_plates:=(T1^4 – Q12_parallel_plates_one_shield(A, eps_1, eps_2, eps_s1, eps_s2, T1,T2) * (1 / eps_1 + 1 / eps_s1 – 1) / (A * sigma))^0.25

END

"----------"

FUNCTION Q12_parallel_plates_N_shields(A, N, eps_1, eps_2, eps_s1, eps_s2, T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Q12_parallel_plates_N_shields:=(A * sigma * (T1^4 – T2^4)) / ((1/eps_1 + 1/eps_2 -1) + N * (1 / eps_s1 + 1/eps_s2 -1))

END

"----------"

Download free eBooks at bookboon.com

FUNCTION Q12_concentric_cyl(R1, R2, L , eps_1, eps_2,T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Q12_concentric_cyl:=(2 * pi * R1 * L * sigma * (T1^4 – T2^4)) / (1/eps_1 + (R1 / R2) * (1/eps_2 -1))

END

"----------"

FUNCTION Q12_concentric_cyl_one_shield(R1, R2,R_shield, L , eps_1, eps_2, eps_s1, eps_s2, T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Q12_concentric_cyl_one_shield:=(2 * pi * R1 * L * sigma * (T1^4 – T2^4)) / (1/eps_1 + (R1 / R2) * (1/eps_2 -1)+ (R1 / R_shield) * (1/eps_s1 + 1/eps_s2 -1))

END

"----------"

FUNCTION Temp_Shield_concentric_cyl(R1, R2,R_shield, L , eps_1, eps_2, eps_s1, eps_s2, T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Temp_Shield_concentric_cyl:=(T1^4 – Q12_concentric_cyl_one_shield(R1, R2,R_shield, L, eps_1, eps_2, eps_s1, eps_s2, T1,T2) *(1/eps_1 + (R1 / R_shield) * (1/eps_s1 -1)) / (2 * pi * R1 * L * sigma))^0.25

END

"----------"

FUNCTION Q12_concentric_spheres(R1, R2, eps_1, eps_2,T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Q12_concentric_spheres :=(4 * pi * R1^2 * sigma * (T1^4 – T2^4)) / (1/eps_1 + (R1 / R2)^2 * (1/eps_2 -1))

END

"----------"

Download free eBooks at bookboon.com

FUNCTION Q12_concentric_sph_one_shield(R1, R2,R_shield, eps_1, eps_2, eps_s1, eps_s2, T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Q12_concentric_sph_one_shield:=(4 * pi * R1^2 * sigma * (T1^4 – T2^4)) / (1/eps_1 + (R1 / R2)^2 * (1/eps_2 -1)+ (R1 / R_shield)^2 * (1/eps_s1 + 1/eps_s2 -1))

END

"----------"

FUNCTION Temp_Shield_concentric_spheres(R1, R2,R_shield, eps_1, eps_2, eps_s1, eps_s2, T1,T2)

sigma:=5.67E-08 "[W/m^2-K^4]"

Temp_Shield_concentric_spheres:=(T1^4 – Q12_concentric_sph_one_shield(R1, R2,R_shield, eps_1, eps_2, eps_s1, eps_s2, T1,T2) *(1/eps_1 + (R1 / R_shield)^2 * (1/eps_s1 -1)) / (4 * pi * R1^2 * sigma))^0.25

END

=

Download free eBooks at bookboon.com

Click on the ad to read more

Now, let us use the above EES Functions to solve some problems:

Prob.5.D.13. Two very large parallel planes, with emissivities 0.3 and 0.8 exchange heat. Find the percentage reduction in heat transfer when a polished Aluminium shield (eps = 0.04) is placed between them. [VTU – May/June 2010]

EES Solution:

We have:

$$Q12_{parallel,plates} := \frac{A \cdot \sigma \cdot (T1^4 - T2^4)}{\frac{1}{eps_1} + \frac{1}{eps_2} - 1}$$

$$Q12_{parallel,plates,one,shield} := \frac{A \cdot \sigma \cdot (T1^4 - T2^4)}{\frac{1}{eps_1} + \frac{1}{eps_2} - 1 + \frac{1}{eps_{s1}} + \frac{1}{eps_{s2}} - 1}$$

Therefore, taking the ratio of Q12 with shield to that without shield:

$$Ratio = \frac{\frac{1}{eps_1} + \frac{1}{eps_2} - 1}{\frac{1}{eps_1} + \frac{1}{eps_2} - 1 + \frac{1}{eps_{s1}} + \frac{1}{eps_{s2}} - 1}$$

In EES data and this eqn for Ratio are entered:

"Data:"

eps_1 = 0.3
eps_2 = 0.8
eps_s1 = 0.04
eps_s2 = 0.04

Ratio = (1/eps_1 + 1/eps_2 – 1) / ((1/eps_1 + 1/eps_2 – 1) + (1/eps_s1 + 1/eps_s2 – 1))

And, Results:

Unit Settings: SI C Pa J mass deg

$eps_1 = 0.3$ $eps_2 = 0.8$ $eps_{s1} = 0.04$ $eps_{s2} = 0.04$ Ratio = 0.06815

i.e. Q12 with shield is 6.815% of that without shield…. Ans.

==========

Download free eBooks at bookboon.com

Prob.5.D.14. Two large parallel planes with emissivity 0.6 are at 900 K and 300 K. A radiation shield with one side polished and having emissivity of 0.05 and the other side unpolished with emissivity 0.4 is proposed to be used between them. Which side of the shield should face the hotter plane if the temp of the shield is to be kept minimum? Justify your answer. [VTU – June 2012]

(b) Also, for the case 1, plot Q12_with_shield and T_shield as eps_s1 (i.e. emissivity of shield surface facing the 900 K surface) varies from 0.05 to 0.4:



Fig.(a)

Fig.(b)

EES Solution:

We shall use the EES Functions written above:

"Data:"

A = 1"[m^2]"

eps_1 = 0.6
eps_2 = 0.6
eps_s1 = 0.05 "..facing surface 1"
eps_s2 = 0.4 "…. facing surface 2"

T1 = 900"[K]"

T2 = 300 "[K]"

"Let:

Case 1: polished surface of shield is facing the hot surface 1

Case 2: unpolished surface of shield is facing the hot surface 1"

Download free eBooks at bookboon.com

Q12 = Q12_parallel_plates(A,eps_1,eps_2,T1,T2)"….when there is no shield"

Q12_shield_case1 = Q12_parallel_plates_one_shield(A, eps_1, eps_2, eps_s1, eps_s2, T1,T2) "..polished surface facing hotter plate"

Q12_shield_case2=Q12_parallel_plates_one_shield(A,eps_1,eps_2,eps_s2,eps_s1,T1,T2)"..unpolished surface facing hotter plate"

T_shield_case1 = Temp_Shield_parallel_plates(A, eps_1, eps_2, eps_s1, eps_s2, T1,T2) "…for case 1"

T_shield_case2 = Temp_Shield_parallel_plates(A, eps_1, eps_2, eps_s2, eps_s1, T1,T2) "…for case 2"

Results:

Unit Settings: SI C Pa J mass deg

(Table 1, Run 8)

$A = 1$ [m^2]	$eps_1 = 0.6$	$eps_2 = 0.6$	$eps_{s1} = 0.4$
$eps_{s2} = 0.4$	$Q12 = 15746$ [W]	$Q12_{shield,case1} = 5801$ [W]	$Q12_{shield,case2} = 5801$ [W]
$T1 = 900$ [K]	$T2 = 300$ [K]	$T_{shield,case1} = 759.1$ [K]	$T_{shield,case2} = 759.1$ [K]

Download free eBooks at bookboon.com

Click on the ad to read more

Thus:

For case 1: Temp of shield = 554 K … Ans.

For case 2: Temp of shield = 868.9 K …. Ans.

Therefore, use option 1 for minimum temp of shield.

(b) Also, for case 1, plot Q12_with_shield and T_shield as eps_s1 (i.e. emissivity of shield surface facing the 900 K surface) varies from 0.05 to 0.4:

First, compute the Parametric Table:

Table 1

1..8	1 eps_{s1}	2 $Q12_{shield,case1}$ [W]	3 $T_{shield,case1}$ [K]
Run 1	0.05	1542	554
Run 2	0.1	2656	628.9
Run 3	0.15	3499	671.7
Run 4	0.2	4159	700.2
Run 5	0.25	4690	720.9
Run 6	0.3	5127	736.6
Run 7	0.35	5492	749
Run 8	0.4	5801	759.1

Next, plot the results:



Download free eBooks at bookboon.com



==========

Prob.5.D.15. Two parallel plates at T1 = 900 K and T2 = 500 K have emissivities eps1 = 0.6 and eps2 = 0.9 respectively. A radiation shield having an emissivity eps_s1 = 0.15 on one side and epas_s2 = 0.06 on the other side is placed between the plates. Calculate the heat transfer rate per sq. m. with and without radiation shield.

(b) Also. Find out the equilibrium temp of the shield (c) Plot Temp of shield as the emissivity eps_s1 of shield varies from 0.05 to 0.4.

EES Solution:

We shall use the EES Functions written above.

"Data:"

^ =Z=N≤xã { Oz≤

Éé ë| N=Z=MKS
Éé ë| O=Z=MKV
Éé ë| ëN=Z=MKNR=ÍKÑ-Åáå Ö=ëì êÑ-ÅÉ=N≤
Éé ë| ëO=Z=MKVS=ÍKÑ-Åáå Ö=ëì êÑ-ÅÉ=O≤

q N=Z=VMMÍxh z≤

q O=Z=RMMÍxh z≤

Download free eBooks at bookboon.com

"Calculations:"

Q12 = Q12_parallel_plates(A,eps_1,eps_2,T1,T2)"….when there is no shield"

Q12_shield_case1 = Q12_parallel_plates_one_shield(A, eps_1, eps_2, eps_s1, eps_s2, T1,T2) "..polished surface facing hotter plate"

T_shield = Temp_Shield_parallel_plates(A, eps_1, eps_2, eps_s1, eps_s2, T1,T2) "…equilibrium temp of shield"

Results:

Unit Settings: SI C Pa J mass deg

A = 1 [m^2]	eps_1 = 0.6	eps_2 = 0.9	eps_{s1} = 0.15
eps_{s2} = 0.06	Q12 = 18932 [W]	$Q12_{shield,case1}$ = 1396 [W]	T1 = 900 [K]
T2 = 500 [K]	T_{shield} = 830.4 [K]		



Download free eBooks at bookboon.com

Click on the ad to read more

Thus:

Q12 without shield = 18932 W/m^2 …. Ans.

Q12 with shield = 1396 W/m^2 … Ans.

Temp of shield = 830.4 K … Ans.

(b) Also, plot Q12_with_shield and T_shield as eps_s1 (i.e. emissivity of shield surface facing the 900 K surface) varies from 0.05 to 0.4:

First, compute the Parametric Table:

1..8	1 eps_{s1}	2 $Q12_{shield,case1}$ [W]	3 T_{shield} [K]
Run 1	0.05	898.9	757.1
Run 2	0.1	1226	807.6
Run 3	0.15	1396	830.4
Run 4	0.2	1500	843.5
Run 5	0.25	1570	852
Run 6	0.3	1620	858
Run 7	0.35	1658	862.4
Run 8	0.4	1688	865.8

And, plot the results:



Download free eBooks at bookboon.com



==========

"**Prob.5.D.16**. A cryogenic fluid flows in a pipe of 10 mm OD at a temp of 100 K. It is surrounded by another coaxial pipe of 13 mm OD. Space between the pipes is evacuated. The outer pipe is at 280 K. Emissivities of both surfaces is 0.3. (b) If a shield of emissivity of 0.05 on either face and dia of 11.5 mm is placed between the pipes, determine the percentage reduction in heat flow. Determine the radiant heat flow for a 3 m length. Also, calculate the equilibrium temp of the shield.

(c) Plot the Percentage reduction and the equilibrium temp of the shield as emissivity of shield varies from 0.05 to 0.3"



Fig.(a)

Download free eBooks at bookboon.com

EES Solution:

"Data:"

R1 = 0.005 "[m]"
R2 = 0.0065"[m]"
R_shield = 0.00575 "[m]"

L = 3 "[m]"

eps_1 = 0.3
eps_2 = 0.3
eps_s1 = 0.05
eps_s2 = 0.05
T1 = 100 "[K]"

T2 = 280 "[K]"

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

"Calculations:"

Q12 = Q12_concentric_cyl(R1, R2, L, eps_1, eps_2,T1,T2)

Q12_shield = Q12_concentric_cyl_one_shield(R1, R2,R_shield, L, eps_1, eps_2, eps_s1, eps_s2, T1,T2)

T_shield = Temp_Shield_concentric_cyl(R1, R2,R_shield, L, eps_1, eps_2, eps_s1, eps_s2, T1,T2)

PercentReduction = (Q12 – Q12_shield) * 100 / Q12

Results:

Unit Settings: SI C Pa J mass deg

$eps_1 = 0.3$	$eps_2 = 0.3$	$eps_{s1} = 0.05$
$eps_{s2} = 0.05$	$L = 3$ [m]	PercentReduction = 86.86 [%]
Q12 = -6.301 [W]	$Q12_{shield} = -0.8276$ [W]	R1 = 0.005 [m]
R2 = 0.0065 [m]	$R_{shield} = 0.00575$ [m]	T1 = 100 [K]
T2 = 280 [K]	$T_{shield} = 237.4$ [K]	

Thus:

Q12 without shield = -6.301 W.… negative sign indicates flow towards the inner pipe which is at a lower temp …. Ans.

Q12 with radiation shield = – 0.8276 W … negative sign indicates flow towards the inner pipe which is at a lower temp …. Ans.

Equilibrium temp of shield = T_shield = 237.4 K … Ans.

To plot the Percentage reduction and the equilibrium temp of the shield as emissivity of shield varies from 0.05 to 0.3:

Download free eBooks at bookboon.com

First, compute the Parametric Table, keeping both eps_s1 = eps_s2 = 0.05, 0.1, 0.15 ….. 0.4.

1..8	1 eps_{s1}	2 eps_{s2}	3 PercentReduction [%]	4 T_{shield} [K]
Run 1	0.05	0.05	86.86	237.4
Run 2	0.1	0.1	76.31	238.2
Run 3	0.15	0.15	67.65	238.8
Run 4	0.2	0.2	60.41	239.3
Run 5	0.25	0.25	54.27	239.7
Run 6	0.3	0.3	49	240.1
Run 7	0.35	0.35	44.43	240.4
Run 8	0.4	0.4	40.41	240.7

Now, plot the results:



Download free eBooks at bookboon.com



==========

The Wake
the only emission we want to leave behind
Low-speed Engines Medium-speed Engines Turbochargers Propellers Propulsion Packages PrimeServ
The design of eco-friendly marine power and propulsion solutions is crucial for MAN Diesel & Turbo.
Power competencies are offered with the world's largest engine programme – having outputs spanning
from 450 to 87,220 kW per engine. Get up front!
Find out more at www.mandieselturbo.com
Engineering the Future – since 1758.
MAN Diesel & Turbo
MAN

Download free eBooks at bookboon.com

Click on the ad to read more

"**Prob.5.D.17.** Two coaxial cylinders of diameters D1 = 0.1 m and D2 = 0.3 m and emissivities eps1 = 0.7 and eps2 = 0.4 are maintained at temps T1 = 800 K and T2 = 500 K respectively. A coaxial shield of diameter D3 = 0.2 m and emissivity eps_s on both its surfaces is placed between the cylinders. Determine eps_s if the radiation heat transfer between the cylinders is to be reduced to 15% of that without the radiation shield. What is the equilibrium temp of the shield at that time?"



Fig.(a)

EES Solution:

"Data:"

R1 = 0.05 "[m]"
R2 = 0.15"[m]"
R_shield = 0.1 "[m]"

L = 1 "[m]"

eps_1 = 0.7
eps_2 = 0.4

"Let: eps_s1 = eps_s2 = eps_s … emissivity of shield"

T1 = 800 "[K]"

T2 = 500 "[K]"

Download free eBooks at bookboon.com

"Calculations:"

Q12 = Q12_concentric_cyl(R1, R2, L , eps_1, eps_2,T1,T2) "….. heat transfer without radiation shield"

Q12_shield = Q12_concentric_cyl_one_shield(R1, R2,R_shield, L , eps_1, eps_2, eps_s, eps_s, T1,T2) "….heat transfer with shield"

Q12_shield = 0.15 * Q12 "….given condition that heat transfer with shield is 15% of that without shield"

T_shield = Temp_Shield_concentric_cyl(R1, R2,R_shield, L , eps_1, eps_2, eps_s, eps_s, T1,T2)

Results:

Unit Settings: SI C Pa J mass deg

eps_1 = 0.7	eps_2 = 0.4	eps_s = 0.0875	L = 1 [m]
Q12 = 3206 [W]	$Q12_{shield}$ = 480.9 [W]	R1 = 0.05 [m]	R2 = 0.15 [m]
R_{shield} = 0.1 [m]	T1 = 800 [K]	T2 = 500 [K]	T_{shield} = 692.7 [K]

Thus:

Q12 without shield = 3206 W …. Ans.

Q12 with shield = 480.9 W …. Ans.

Their ratio is = (480.9 * 100) / 3206 = 15% …. Verified

Emissivity of shield to achieve this = eps_s = 0.0875 …. Ans.

Temp of shield (eps_s = 0.0875) is: 692.7 K … Ans.

==========

"**Prob.5.D.18.** Liquid nitrogen (LN2) is stored in a dewar made of two concentric spheres, with the space between them evacuated. The inner sphere has an outer dia D1 = 1 m and for outer sphere the inner dia D2 = 1.2 m and emissivities eps1 = 0.2 and eps2 = 0.2. Temperatures are maintained at temps T1 = 78 K and T2 = 300 K respectively. A coaxial shield of diameter D3 = 1.1 m and emissivity eps_s = 0.05 on both its surfaces is placed between the two spheres. If the latent heat of vaporization of LN2 is 2 × 10^5 J/kg, determine:

a) the boil-off rate of liquid nitrogen when there is no shield,
b) the boil-off rate of liquid nitrogen when the shield is present. What is the equilibrium temp of the shield at that time?
c) Plot the variation of boil-off rate and the shield temp as emissivity of shield (on its either side) varies from 0.05 to 0.4."

Download free eBooks at bookboon.com



Fig.(a)

EES Solution:

"Data:"

R1 = 0.5 "[m]"
R2 = 0.6"[m]"
R_shield = 0.55 "[m]"

See the light!
The sooner you realize we are right, the sooner your life will get better!

A bit over the top? Yes we know!

We are just that sure that we can make your media activities more effective.

Get "Bookboon's Free Media Advice"
Email kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

eps_1 = 0.2

eps_2 = 0.2

eps_s1 = 0.05

eps_s2 = 0.05

T1 = 78 "[K]"

T2 = 300 "[K]"

h_fg = 2E05 [J/kg]

"Calculations:"

Q12 = Q12_concentric_spheres(R1, R2, eps_1, eps_2,T1,T2)"[W]…Q12 with no shield"

Q12_shield = Q12_concentric_sph_one_shield(R1, R2,R_shield, eps_1, eps_2, eps_s1, eps_s2, T1,T2) "[W]….Q12 with shield"

T_shield=Temp_Shield_concentric_spheres(R1,R2,R_shield,eps_1,eps_2,eps_s1,eps_s2,T1,T2)"[K]….Temp of shield"

BoilOff_with_shield = Abs(Q12_shield) / h_fg * 3600"[kg/h]….boil off rate of liq. nitrogen, when there is shield"

BoilOff_no_shield = Abs(Q12) / h_fg * 3600"[kg/h]….boil off rate of liq. nitrogen, when there is no shield"

Results:

Unit Settings: SI C Pa J mass deg

$BoilOff_{no,shield}$ = 3.324 [kg/h]	$BoilOff_{with,shield}$ = 0.6462 [kg/h]	eps_1 = 0.2
eps_2 = 0.2	eps_{s1} = 0.05	eps_{s2} = 0.05
h_{fg} = 200000 [J/kg]	Q12 = -184.7 [W]	$Q12_{shield}$ = -35.9 [W]
R1 = 0.5 [m]	R2 = 0.6 [m]	R_{shield} = 0.55 [m]
T1 = 78 [K]	T2 = 300 [K]	T_{shield} = 254.7 [K]

Download free eBooks at bookboon.com

Thus:

LN2 Boil off rate without shield = 3.324 kg/h …. Ans.

LN2 Boil off with shield = 0.6462 kg/h …. Ans.

Equilibrium temp of shield = 254.7 K … Ans.

To plot the variation of boil-off rate and the shield temp as emissivity of shield (on its either side) varies from 0.05 to 0.4:

First, compute the Parametric Table, keeping both eps_s1 = eps_s2 = 0.05, 0.1, 0.15 ….. 0.4.

1..8	1 eps_{s1}	2 eps_{s2}	3 $BoilOff_{no,shield}$ [kg/h]	4 $BoilOff_{with,shield}$ [kg/h]	5 T_{shield} [K]
Run 1	0.05	0.05	3.324	0.6462	254.7
Run 2	0.1	0.1	3.324	1.101	256.2
Run 3	0.15	0.15	3.324	1.439	257.3
Run 4	0.2	0.2	3.324	1.699	258.1
Run 5	0.25	0.25	3.324	1.906	258.8
Run 6	0.3	0.3	3.324	2.075	259.3
Run 7	0.35	0.35	3.324	2.215	259.7
Run 8	0.4	0.4	3.324	2.333	260.1

Now, plot the results:



Download free eBooks at bookboon.com



==========

Prob.5.D.19. Write VBA Functions for heat transfer when radiation shield is present for the cases of:

1) Parallel plates,
2) concentric cylinders, and
3) concentric spheres

Also write Functions for the equilibrium temp of the shield in each case.

EXCEL Solution:

Before we write VBA Functions for heat transfer when the shield is present, let us recollect the Functions we wrote earlier for heat transfer without the shield for the above three cases, since in most of the problems, we are asked to compare the heat transfer with and without the shields:

Download free eBooks at bookboon.com

Heat transfer Q12 (W), when there is *no* radiation shield:

```
Function Q_12_Infinite_large_parallel_plates(Area As Double, eps_1 As Double, eps_2 As Double, _
T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) between two infinite parallel plates of area A (m2) each,
'i.e. (A_1/A_2) = 1, F_12 = 1

Dim sigma As Double
sigma = 0.0000000567 'W/m2.K^4

Q_12_Infinite_large_parallel_plates = (sigma * Area * (T_1 ^ 4 - T_2 ^ 4)) / _
(1 / eps_1 + 1 / eps_2 - 1)

End Function
```

```
Function Q_12_Infinite_concentric_cylinders(A_1 As Double, R_1 As Double, R_2 As Double, _
eps_1 As Double, eps_2 As Double, T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) between infinite concentric cylinders,
'i.e. (A_1/A_2) = R_1/R_2, F_12 = 1

Dim sigma As Double
sigma = 0.0000000567 'W/m2.K^4

Q_12_Infinite_concentric_cylinders = (sigma * A_1 * (T_1 ^ 4 - T_2 ^ 4)) / _
(1 / eps_1 + ((1 - eps_2) / eps_2) * (R_1 / R_2))

End Function
```

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

```
Function Q_12_concentric_spheres(A_1 As Double, R_1 As Double, R_2 As Double, _
eps_1 As Double, eps_2 As Double, T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) between concentric spheres,
'i.e. (A_1/A_2) = (R_1/R_2)^2, F_12 = 1

Dim sigma As Double
sigma = 0.0000000567 'W/m2.K^4

Q_12_concentric_spheres = (sigma * 4 * Application.Pi() * R_1 ^ 2 * (T_1 ^ 4 - T_2 ^ 4)) / _
(1 / eps_1 + ((1 - eps_2) / eps_2) * (R_1 / R_2) ^ 2)

End Function
```

Heat transfer Q12 (W), when a *radiation shield is present* between the two surfaces:

```
Function Q_12_ParallelPlates_with_NRadiationShields(A As Double, N As Integer, _
eps_1 As Double, eps_2 As Double, eps_s1 As Double, eps_s2 As Double, _
T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) ..heat tr with N radiation shieds

Dim sigma As Double, XX As Double, YY As Double, ZZ As Double
sigma = 0.0000000567 'W/m2.K^4

XX = A * sigma * (T_1 ^ 4 - T_2 ^ 4)
YY = 1 / eps_1 + 1 / eps_2 - 1
ZZ = 1 / eps_s1 + 1 / eps_s2 - 1
Q_12_ParallelPlates_with_NRadiationShields = XX / (YY + N * ZZ)
End Function
```

Note *that the above Function can be used when there are N shields in between the two parallel plates. If there is only one shield, simply put N = 1.*

```
Function Q_12_ConcentricCylinders_with_RadiationShield(L As Double, R_1 As Double, _
R_2 As Double, R_3 As Double, eps_1 As Double, eps_2 As Double, eps_31 As Double, _
eps_32 As Double, T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) ..heat tr with a cyl. radiation shied

Dim sigma As Double, A_1 As Double, XX As Double, YY As Double, ZZ As Double
sigma = 0.0000000567 'W/m2.K^4
A_1 = 2 * Application.Pi() * R_1 * L
XX = A_1 * sigma * (T_1 ^ 4 - T_2 ^ 4)
YY = (R_1 / R_2) * (1 / eps_2 - 1)
ZZ = (R_1 / R_3) * (1 / eps_31 + 1 / eps_32 - 1)

Q_12_ConcentricCylinders_with_RadiationShield = XX / (1 / eps_1 + YY + ZZ)

End Function
```

Download free eBooks at bookboon.com

```
Function Q_12_ConcentricSpheres_with_RadiationShield(R_1 As Double, _
R_2 As Double, R_3 As Double, eps_1 As Double, eps_2 As Double, eps_31 As Double, _
eps_32 As Double, T_1 As Double, T_2 As Double) As Double

'Gives Q_12 (W) ..heat tr with a spherical radiation shied

Dim sigma As Double, A_1 As Double
sigma = 0.0000000567 'W/m2.K^4

A_1 = 4 * Application.Pi() * R_1 ^ 2

 Q_12_ConcentricSpheres_with_RadiationShield = (A_1 * sigma * (T_1 ^ 4 - T_2 ^ 4)) / _
 (1 / eps_1 + (R_1 / R_2) ^ 2 * (1 / eps_2 - 1) + (R_1 / R_3) ^ 2 * (1 / eps_31 + 1 / eps_32 - 1))


End Function
```

Equilibrium temp of shield, T_shield (K), when a *radiation shield is present* between the two surfaces:

```
Function T_shield_ParallelPlates(eps_1 As Double, eps_2 As Double, eps_31 As Double, _
eps_32 As Double, T_1 As Double, T_2 As Double) As Double
'Gives Q_12 (W) ..heat tr with N radiation shieds

Dim sigma As Double, XX As Double, YY As Double, ZZ As Double
Dim Q_12 As Double, AA As Double, A As Integer

A = 1 'm^2 .... area of plate
sigma = 0.0000000567 'W/m2.K^4
XX = A * sigma * (T_1 ^ 4 - T_2 ^ 4)
YY = 1 / eps_1 + 1 / eps_2 - 1
ZZ = 1 / eps_31 + 1 / eps_32 - 1

Q_12 = XX / (YY + ZZ) '..heat transfer when one shield is present

AA = 1 / eps_1 + 1 / eps_31 - 1

T_shield_ParallelPlates = (T_1 ^ 4 - Q_12 * AA / (A * sigma)) ^ 0.25

End Function
```

```
Function T_shield_ConcentricCylinders(L As Double, R_1 As Double, _
R_2 As Double, R_3 As Double, eps_1 As Double, eps_2 As Double, eps_31 As Double, _
eps_32 As Double, T_1 As Double, T_2 As Double) As Double

'Gives T_shield ..equilibrium temp of radiation shied, (K)


Dim sigma As Double, A_1 As Double, XX As Double, YY As Double, ZZ As Double
Dim Q_12 As Double, AA As Double

sigma = 0.0000000567 'W/m2.K^4

A_1 = 2 * Application.Pi() * R_1 * L
XX = A_1 * sigma * (T_1 ^ 4 - T_2 ^ 4)
YY = (R_1 / R_2) * (1 / eps_2 - 1)
ZZ = (R_1 / R_3) * (1 / eps_31 + 1 / eps_32 - 1)

Q_12 = XX / (1 / eps_1 + YY + ZZ) '..heat transfer when one shield is present

AA = 1 / eps_1 + (R_1 / R_3) * (1 / eps_31 - 1)

T_shield_ConcentricCylinders = (T_1 ^ 4 - Q_12 * AA / (A_1 * sigma)) ^ 0.25

End Function
```

Download free eBooks at bookboon.com

```
Function T_shield_ConcentricSpheres(R_1 As Double, R_2 As Double, R_3 As Double, _
eps_1 As Double, eps_2 As Double, eps_31 As Double, _
eps_32 As Double, T_1 As Double, T_2 As Double) As Double

'Gives T_shield (K)) ..equilibrium temp of a spherical radiation shied

Dim sigma As Double, A_1 As Double, Q_12 As Double, AA As Double

sigma = 0.0000000567 'W/m2.K^4

A_1 = 4 * Application.Pi() * R_1 ^ 2

'Heat transfer when one shield is present is given by:

Q_12 = (A_1 * sigma * (T_1 ^ 4 - T_2 ^ 4)) / _
 (1 / eps_1 + (R_1 / R_2) ^ 2 * (1 / eps_2 - 1) + (R_1 / R_3) ^ 2 * (1 / eps_31 + 1 / eps_32 - 1))

AA = 1 / eps_1 + (R_1 / R_3) ^ 2 * (1 / eps_31 - 1)

T_shield_ConcentricSpheres = (T_1 ^ 4 - Q_12 * AA / (A_1 * sigma)) ^ 0.25

End Function
```

==========

Now, let us solve some problems in EXCEL using the above Functions.

Prob.5.D.20. Consider two large parallel plates, one at 1000 K with emissivity 0.8 and the other at 300 K having emissivity 0.6. A radiation shield is placed between them. The shield has emissivity of 0.1 on the side facing the hot plate and 0.3 on the side facing the cold plate. Calculate the percentage reduction in radiation heat transfer as a result of radiation shield. [P.U. 2000]

(b) Plot the Percentage reduction in heat transfer and the temp of Shield as emissivity of shield on both sides (eps_s1 = eps_s2 = eps_s) varies from 0.05 to 0.4:



Fig.(a)



Fig.(b)

Download free eBooks at bookboon.com

EXCEL Solution:

Following are the steps:

1. Set up the EXCEL worksheet, enter data:

	A	B	C	D	E
51		Data:			
52					
53		Area of plate	A	1	m^2
54		No. of shields	N	1	
55		emissivity of plate 1	eps1	0.8	
56		emissivity of plate 2	eps2	0.6	
57		emissivity of shield surface facing plate 1	epsilon_31	0.1	
58		emissivity of shield surface facing plate 2	epsilon_32	0.3	
59		Temp, plate 1	T_1	1000	K
60		Temp, plate 2	T_2	300	K



Download free eBooks at bookboon.com

Click on the ad to read more

2. Do calculations using the VBA Functions written above. Functions are available under 'User Defined' category:

For the case of parallel plates with no radiation shield, choose the appropriate Function:



Press OK. We get the following window; fill it up as shown:



Download free eBooks at bookboon.com

Press OK. We get the result in cell D62:



In the above, see the Formula entered in cell D62 for Q_12 _noshield.

Similarly, enter Function for Q12 with one Shield (i.e. N = 1):



And, see the Formula entered in cell D64 for Q_12 _shield.

And enter Function for the Temp of the Shield:



And, see the formula entered in cell D66 for the temp of Shield, in the Formula bar above

And, percentage reduction in heat transfer because of the shield is:



Download free eBooks at bookboon.com

Thus:

Q12 with no shield = 29342.99 W …. Ans.

Q12 with shield = 3946.718 W … Ans.

Percentage reduction due to shield = 86.55% …. Ans.

Equilibrium temp of shield = 731.635 K … Ans.

**Who is your target group?
And how can we reach them?**

At Bookboon, you can segment the exact right audience for your advertising campaign.

Our eBooks offer in-book advertising spot to reach the right candidate.

Contact us to hear more
kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

Plot the Percentage reduction in heat transfer and the temp of Shield as emissivity of shield on both sides (eps_s1 = eps_s2 = eps_s) varies from 0.05 to 0.4:

First set up a Table as shown:



	A	B	C	D	E	F	G
73							
74		eps_s	Q_12_shield(W)	Percent_reduction	T_shield (K)		
75		0.05	1374.519	95.316	844.697		
76		0.1					
77		0.15					
78		0.2					
79		0.25					
80		0.3					
81		0.35					
82		0.4					

In the above Table, in row 75 enter formulas for Q_12 with shield, % reduction in heat transfer and T_shield as shown. Formula for Q12 with shield, entered in cell C75, can be seen in the Formula bar. Remember to enter references to eps_s1 ans eps_s2 with relative reference so that we can drag-copy to get values at other values of eps_s. Similarly, for % reduction and T_shield.

Now, select cells C75 to E75 and drag-copy to the end of Table, i.e. up to cell E82. Immediately, all calculations are made and the Table is filled up:



	A	B	C	D	E
73					
74		eps_s	Q_12_shield(W)	Percent_reduction	T_shield (K)
75		0.05	1374.519	95.316	844.697
76		0.1	2688.800	90.837	846.693
77		0.15	3946.718	86.550	848.590
78		0.2	5151.823	82.443	850.396
79		0.25	6307.372	78.505	852.117
80		0.3	7416.360	74.725	853.758
81		0.35	8481.546	71.095	855.326
82		0.4	9505.475	67.606	856.825

Download free eBooks at bookboon.com

Now, plot the results in EXCEL:





==========

Download free eBooks at bookboon.com

Prob.5.D.21. Two parallel plates are at T1 = 700 K and T2 = 350 K. Their emissivities are 0.6 and 0.9 respectively. Determine the emissivity of a radiation shield if heat transfer between the plates is to be reduced to 10% of that without the radiation shield.

EXCEL Solution:

Following are the steps:

1. Set up the EXCEL worksheet, enter data:

	A	B	C	D	E
107		Data:			
108					
109		Area of plate	A	1	m^2
110		No. of shields	N	1	
111		emissivity of plate 1	eps1	0.6	
112		emissivity of plate 2	eps2	0.9	
113		emissivity of shield	epsilon_3	0.1	....assumed
114					
115		Temp, plate 1	T_1	700	K
116		Temp, plate 2	T_2	350	K

Brain power
By 2020, wind could provide one-tenth of our planet's electricity needs. Already today, SKF's innovative know-how is crucial to running a large proportion of the world's wind turbines.
Up to 25 % of the generating costs relate to maintenance. These can be reduced dramatically thanks to our systems for on-line condition monitoring and automatic lubrication. We help make it more economical to create cleaner, cheaper energy out of thin air.
By sharing our experience, expertise, and creativity, industries can boost performance beyond expectations.
Therefore we need the best employees who can meet this challenge!
The Power of Knowledge Engineering
Plug into The Power of Knowledge Engineering.
Visit us at www.skf.com/knowledge
SKF
Download free eBooks at bookboon.com
Click on the ad to read more

In the above, emissivity of shield (on its either side) is assumed as 0.1; its correct value will be found out later by Goal Seek.

2. Now, do calculations. Find out Q12_withnoshield and Q12_with shield and put the condition that Q12 with shield should be equal to 10% of Q12 with no shield:

For Q12_noshield:



D118 =Q_12_Infinite_large_parallel_plates(1,D111,D112,D115,D116)

	A	B	C	D	E
113		emissivity of shield	epsilon_3	0.1	....assumed
114					
115		Temp, plate 1	T_1	700	K
116		Temp, plate 2	T_2	350	K
117					
118		Heat transfer with no shield	Q_12_noShield	7179.083789	W

For Q12_with shield:



D120 =Q_12_ParallelPlates_with_NRadiationShields(1,1,D111,D112,D113,D113,D115,D116)

	A	B	C	D	E	F
116		Temp, plate 2	T_2	350	K	
117						
118		Heat transfer with no shield	Q_12_noShield	7179.083789	W	
119						
120		Heat transfer with shield	Q_12_shield	614.2531584	W	

And enter the constraint:



D122 =D120-0.1*D118

	A	B	C	D	
116		Temp, plate 2	T_2	350	K
117					
118		Heat transfer with no shield	Q_12_noShield	7179.083789	W
119					
120		Heat transfer with shield	Q_12_shield	614.2531584	W
121					
122		Contraint:	Q12_shield - 0.1*Q12_noshield	-103.6552205	W

Download free eBooks at bookboon.com

Now, apply Goal Seek to make value in D122 (see the eqn in Formula bar above) zero by changing the value of eps_shield in cell C113:

Go to Data – What If Analysis – Goal eek:



Click on Goal Seek. We get the following window. Fill it up as shown:



Press OK. We get:



Download free eBooks at bookboon.com

Goal Seek has found a solution. Click OK. See the value of eps_shield in cell D113:

C113 fx epsilon_3

	A	B	C	D	E
107		Data:			
108					
109		Area of plate	A	1	m^2
110		No. of shields	N	1	
111		emissivity of plate 1	eps1	0.6	
112		emissivity of plate 2	eps2	0.9	
113		emissivity of shield	epsilon_3	0.117647059	....assumed
114					
115		Temp, plate 1	T_1	700	K
116		Temp, plate 2	T_2	350	K
117					
118		Heat transfer with no shield	Q_12_noShield	7179.083789	W
119					
120		Heat transfer with shield	Q_12_shield	717.9083789	W
121					
122		Contraint:	Q12_shield - 0.1*Q12_noshield	-9.08256E-09	W
123					

Therefore the emissivity of shield required is: 0.118 …. Ans.

==========

Download free eBooks at bookboon.com

Click on the ad to read more

Prob.5.D.22. Two coaxial cylinders of diameters D1 = 0.1 m and D2 = 0.3 m, are at T1 = 1000 K and T2 = 500 K. Their emissivities are 0.7 and 0.4 respectively. Now, a coaxial radiation shield of dia D3 = 0.2 m and emissivity = 0.2 (on either face) is placed between the two cylinders. Determine (a) the net rate of heat transfer between the cylinders per unit length of cylinders, with and without the shield.

(b) equilibrium temp of the shield, and

(c) plot Q12_with shield and temp of shield as emissivity of shield is varied from 0.05 to 0.4.



Fig.(a)

EXCEL Solution:

Following are the steps:

1) Set up the EXCEL worksheet, enter data:

D134 =2*PI()*D131*D130

	A	B	C	D	
128		Data:			
129					
130		Length of cyl.	L	1	m
131		Radius, inner cyl	R_1	0.05	m
132		Radius, outer cyl.	R_2	0.15	m
133		Radius, shield	R_3	0.1	m
134		Surface area of inner cyl	A_1	0.31416	m^2
135					
136		emissivity of inner cyl. 1	eps1	0.7	
137		emissivity of outer cyl.2	eps2	0.4	
138		emissivity of shield	epsilon_3	0.2	
139					
140		Temp, inner cyl. 1	T_1	1000	K
141		Temp, outer cyl. 2	T_2	500	K

Download free eBooks at bookboon.com

2. Do the calculations for Q12 with and without shield and for the temp of shield using the VBA Functions written earlier:

Heat transfer without the Shield:



D143 =Q_12_Infinite_concentric_cylinders(D134,D131,D132,D136,D137,D140,D141)

	A	B	C	D	E	F
140		Temp, inner cyl. 1	T_1	1000	K	
141		Temp, outer cyl. 2	T_2	500	K	
142						
143		Heat transfer with no shield	Q_12_noShield	8659.014751	W	

In the above, eqn entered in cell D143 can be seen in the Formula bar.

Heat transfer with the Shield being present:



D145 =Q_12_ConcentricCylinders_with_RadiationShield(D130,D131,D132,D133,D136,D137,D138,D138,D140,D141)

	A	B	C	D	E	F	G	H	I
140		Temp, inner cyl. 1	T_1	1000	K				
141		Temp, outer cyl. 2	T_2	500	K				
142									
143		Heat transfer with no shield	Q_12_noShield	8659.014751	W				
144									
145		Heat transfer with shield	Q_12_shield	2597.7044	W				

In the above, eqn entered in cell D145 can be seen in the Formula bar.

Equilibrium temp of the Shield:



D147 =T_shield_ConcentricCylinders(D130,D131,D132,D133,D136,D137,D138,D138,D140,D141)

	A	B	C	D	E	F	G
140		Temp, inner cyl. 1	T_1	1000	K		
141		Temp, outer cyl. 2	T_2	500	K		
142							
143		Heat transfer with no shield	Q_12_noShield	8659.014751	W		
144							
145		Heat transfer with shield	Q_12_shield	2597.7044	W		
146							
147		Equilibrium temp of Shield	T_shield	840.896	K		

In the above, eqn entered in cell D147 can be seen in the Formula bar.

Thus:

Q12 with no shield = 8659.01 W …. Ans.

Q12 with shield = 2597.7 W … Ans.

Equilibrium temp of shield = 840.9 K … Ans.

Download free eBooks at bookboon.com

(c) To plot Q12_with shield and temp of shield as emissivity of shield is varied from 0.05 to 0.4:

First, set up a Table as follows:

	A	B	C	D
151				
152		eps_s	Q_12_shield(W)	T_shield (K)
153		0.05	779.31	849.95
154		0.1		
155		0.15		
156		0.2		
157		0.25		
158		0.3		
159		0.35		
160		0.4		

In cells C153 and D153 above, we have used the respective VBA Functions. In the Functions, take care to refer to eps_shield by 'relative reference' so that we can drag-copy to calculate for other values of eps_shield.

Download free eBooks at bookboon.com

Click on the ad to read more

For Q12_with shield, in cell C153, we have the Function:

=Q_12_ConcentricCylinders_with_RadiationShield($D$130,$D$131,$D$132,$D$133,$D$136,$D$137,B153,B153,$D$140,$D$141)

For T_ shield, in cell D153, we have the Function:

=T_shield_ConcentricCylinders($D$130,$D$131,$D$132,$D$133,$D$136,$D$137,B153,B153,$D$140,$D$141)

Now, select cells C153 to D153, and drag-copy to the end of Table, i.e. up to cell D160. Immediately, all calculations are done and the Table gets filled up:

	A	B	C	D
151				
152		eps_s	Q_12_shield(W)	T_shield (K)
153		0.05	779.31	849.95
154		0.1	1461.21	846.59
155		0.15	2062.88	843.59
156		0.2	2597.70	840.90
157		0.25	3076.23	838.47
158		0.3	3506.90	836.26
159		0.35	3896.56	834.25
160		0.4	4250.79	832.41

Now, plot the results in EXCEL:



Download free eBooks at bookboon.com



==========

Prob.5.D.23. Liquid oxygen (LOX) is stored in a dewar made of two concentric spheres, with the space between them evacuated. The inner sphere has an outer dia D1 = 0.3 m and for outer sphere the inner dia D2 = 0.4 m and emissivities eps1 = 0.2 and eps2 = 0.25. Temperatures are maintained at temps T1 = 90K and T2 = 300 K respectively. A coaxial shield of diameter D3 = 0.35 m and emissivity eps_s = 0.05 on both its surfaces is placed between the two spheres. If the latent heat of vaporization of LOX is 2.13 × 10^5 J/kg, determine:

a) the boil-off rate of liquid oxygen when there is no shield,
b) the boil-off rate of liquid oxygen when the shield is present. What is the equilibrium temp of the shield at that time?
c) Plot the variation of boil-off rate and the shield temp as emissivity of shield (on its either side) varies from 0.05 to 0.4.



Fig.(a)

Download free eBooks at bookboon.com

EXCEL Solution:

We shall use the VBA Functions for concentric spheres.

Following are the steps:

1. Set up the EXCEL worksheet, enter data:

	A	B	C	D	E
202					
203		**Data:**			
204					
205					
206		**Radius, inner sphere**	**R_1**	**0.15**	m
207		**Radius, outer sphere**	**R_2**	**0.2**	m
208		**Radius, shield**	**R_3**	**0.175**	m
209		**Surface area of inner sphere**	**A_1**	**0.28274**	m^2
210					
211		**emissivity of inner sphere. 1**	**eps1**	**0.2**	
212		**emissivity of outer sphere.2**	**eps2**	**0.25**	
213		**emissivity of shield**	**epsilon_3**	**0.05**	
214					
215		**Temp, inner cyl. 1**	**T_1**	**90**	K
216		**Temp, outer cyl. 2**	**T_2**	**300**	K
217		**Latent heat of evap. Of LOX**	**h_fg**	**2.13E+05**	J/kg

2. Do the calculations for Q12 with and without shield and for the temp of shield using the VBA Functions written earlier:

Heat transfer without the Shield:

D219 =Q_12_concentric_spheres(D209,D206,D207,D211,D212,D215,D216)

	A	B	C	D	E
217		**Latent heat of evap. Of LOX**	**h_fg**	**2.13E+05**	J/kg
218					
219		**Heat transfer with no shield**	**Q_12_noShield**	**-19.2604**	W

In the above, eqn entered in cell D219 can be seen in the Formula bar.

*Negative sign indicates heat flow **in to** the inner cylinder.*

Download free eBooks at bookboon.com

Heat transfer with the Shield being present:

D221 | =Q_12_ConcentricSpheres_with_RadiationShield(D206,D207,D208,D211,D212,D213,D213,D215,D216)

	A	B	C	D	E	F	G	H
217		Latent heat of evap. Of LOX	h_fg	2.13E+05	J/kg			
218								
219		Heat transfer with no shield	Q_12_noShield	-19.2604	W			
220								
221		Heat transfer with shield	Q_12_shield	-3.6446	W			

In the above, eqn entered in cell D221 can be seen in the Formula bar.

*Negative sign indicates heat flow **in to** the inner cylinder.*



Download free eBooks at bookboon.com

Click on the ad to read more

Percent reduction in heat transfer due to Shield:

D223 =(D219-D221)*100/D219

	A	B	C	D	E
217		Latent heat of evap. Of LOX	h_fg	2.13E+05	J/kg
218					
219		Heat transfer with no shield	Q_12_noShield	-19.2604	W
220					
221		Heat transfer with shield	Q_12_shield	-3.6446	W
222					
223		% reduction in heat transfer due to radiation shield	Percent_Reduction	81.077	%

In the above, eqn entered in cell D223 can be seen in the Formula bar.

Equilibrium temp of the Shield:

D225 =T_shield_ConcentricSpheres(D206,D207,D208,D211,D212,D213,D213,D215,D216)

	A	B	C	D	E	F
223		% reduction in heat transfer due to radiation shield	Percent_Reduction	81.077	%	
224						
225		Equilibrium temp of Shield	T_shield	257.196	K	

In the above, eqn entered in cell D225 can be seen in the Formula bar.

Evaporation Rate of LOX:

D227 =ABS(D221/D217)

	A	B	C	D	E
220					
221		Heat transfer with shield	Q_12_shield	-3.6446	W
222					
223		% reduction in heat transfer due to radiation shield	Percent_Reduction	81.077	%
224					
225		Equilibrium temp of Shield	T_shield	257.196	K
226					
227		Evapn. rate of LOX, with shield	m_evapn	1.7111E-05	kg/s
228		i.e.	m_evapn=	0.06160	kg/h

In the above, eqn entered in cell D227 can be seen in the Formula bar.

Note that evaporation rate is taken as positive quantity by using EXCEL Function ABS().

Download free eBooks at bookboon.com

Thus:

Q12 with no shield = 19.2604 W …. Ans.

Q12 with shield = 3.6446 W … Ans.

% reduction in heat flow = 81.077% …. Ans.

Equilibrium temp of shield = 267.196 K … Ans.

Evaporation rate of LOX = 0.0616 kg/h … Ans.

(c) Plot the variation of boil-off rate and the shield temp as emissivity of shield (on its either side) varies from 0.05 to 0.4.

First, set up a Table as follows:

	A	B	C	D	E
229					
230					
231		eps_s	Q_12_shield (W)	m_evapn (kg/h)	T_shield (K)
232		0.05	3.64	0.0616	257.1964841
233		0.1			
234		0.15			
235		0.2			
236		0.25			
237		0.3			
238		0.35			
239		0.4			

In cells C232 and D232 above, we have used the respective VBA Functions. In the Functions, take care to refer to eps_shield by 'relative reference' so that we can drag-copy to calculate for other values of eps_shield.

For Q12_with shield, in cell C232, we have the Function:

=ABS(Q_12_ConcentricSpheres_with_RadiationShield($D$206,$D$207,$D$208,$D$211,$D$212, B232,B232,$D$215, $D$216))

For evaporation rate of LOX, m_evapn in cell D232, we have the equation:

=C232*3600/$D$217

For T_ shield, in cell E232, we have the Function:

=T_shield_ConcentricSpheres($D$206,$D$207,$D$208,$D$211,$D$212,B232,B232,$D$215, $D$216)

Download free eBooks at bookboon.com

Now, select cells C232 to E232, and drag-copy to the end of Table, i.e. up to cell E239. Immediately, all calculations are done and the Table gets filled up:

	A	B	C	D	E
229					
230					
231		eps_s	Q_12_shield (W)	m_evapn (kg/h)	T_shield (K)
232		0.05	3.64	0.0616	257.196
233		0.1	6.24	0.1054	260.207
234		0.15	8.18	0.1382	262.393
235		0.2	9.68	0.1637	264.053
236		0.25	10.89	0.1840	265.357
237		0.3	11.87	0.2006	266.408
238		0.35	12.69	0.2145	267.273
239		0.4	13.38	0.2261	267.998

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.
Download free eBooks at bookboon.com
Click on the ad to read more

Now, plot the results in EXCEL:





Download free eBooks at bookboon.com



==========

Download free eBooks at bookboon.com

5E 'Radiation error' in temperature measurement:

Recollect that:

T_f = actual temp of fluid
T_c = temp reading by the Thermocouple (TC)
T_w = temp of channel walls
T_s = temp of radiation shield
A_c = surface area of TC bead
A_s = surface area of shield (one side)
h = convection coeff. between the fluid and TC bead / shield
ε_c = emissivity of TC bead
ε_s = emissivity of shield

The Wake
the only emission we want to leave behind
Low-speed Engines Medium-speed Engines Turbochargers Propellers Propulsion Packages PrimeServ
The design of eco-friendly marine power and propulsion solutions is crucial for MAN Diesel & Turbo.
Power competencies are offered with the world's largest engine programme – having outputs spanning
from 450 to 87,220 kW per engine. Get up front!
Find out more at www.mandieselturbo.com
Engineering the Future – since 1758.
MAN Diesel & Turbo
MAN

Download free eBooks at bookboon.com

Click on the ad to read more



(a) Thermometer without radiation shield



(b) Thermometer with radiation shield

Fig.13.39 Radiation shielding of thermometers

Making an **energy balance on the thermometer bulb,** in steady state, we have:

Without radiation shield:

q_{conv} to the bulb = q_{rad} from the bulb

i.e. $$h \cdot A_c \cdot (T_f - T_c) = \varepsilon_c \cdot A_c \cdot \sigma \cdot (T_c^4 - T_w^4)$$

i.e. $$T_f = T_c + \frac{\varepsilon_c \cdot \sigma \cdot (T_c^4 - T_w^4)}{h} \quad \text{.....(13.79)}$$

With radiation shield being present:

Energy balance on the *thermometer bulb*:

$$h \cdot A_c \cdot (T_f - T_c) = \frac{\sigma \cdot (T_c^4 - T_s^4)}{\left(\frac{1-\varepsilon_c}{A_c \cdot \varepsilon_c}\right) + \frac{1}{A_c \cdot F_{cs}} + \left(\frac{1-\varepsilon_s}{A_s \cdot \varepsilon_s}\right)} \quad \text{....(13.80)}$$

Download free eBooks at bookboon.com

In eqn. (13.80), F_{cs} = view factor of thermometer bulb w.r.t the shield and is, generally equal to 1.

Making an energy balance on the *shield*:

$$2 \cdot A_s \cdot h \cdot (T_f - T_s) + \frac{\sigma \cdot (T_c^4 - T_s^4)}{\left(\frac{1-\varepsilon_c}{A_c \cdot \varepsilon_c}\right) + \frac{1}{A_c \cdot F_{cs}} + \left(\frac{1-\varepsilon_s}{A_s \cdot \varepsilon_s}\right)} = \varepsilon_s \cdot A_s \cdot \sigma \cdot (T_s^4 - T_w^4) \quad \text{....(13.81)}$$

Here the assumption is,

$F_{sw}=1$ ...view factor between the shield and the walls

and,

$\frac{A_s}{A_w}=0$ ...i.e. surface area of shield is negligible compared to the area of the channel walls

Solving eqns. (13.80) and (13.81) simultaneously, we obtain the shield temperature T_s and the thermometer reading T_c, (if T_f is known), or T_f (if T_c is known).

Prob.5E.1. Write Mathcad Functions for Radiation error in temp. measurement:

Mathcad Functions for 'Radiation error' in temp. measurement:

1. Thermocouple with *no* radiation shield:

In steady state, making a heat balance on the tthermocouple bead, we have:

$$q_{conv} = q_{rad}$$

i.e. $$h \cdot A_c \cdot (T_f - T_c) = \sigma \cdot \varepsilon_c \cdot A_c \cdot (T_c^4 - T_w^4)$$

i.e. $$T_f = T_c + \frac{\varepsilon_c \cdot \sigma \cdot (T_c^4 - T_w^4)}{h} \quad \text{....(13.79)}$$

We write the Function to find T_f when other quantities are known:

$$\text{RadnError\_TC\_no\_shield\_Tf}(T_c, T_w, \varepsilon_c, h) := T_c + \frac{\varepsilon_c \cdot 5.67 \cdot 10^{-8} \cdot (T_c^4 - T_w^4)}{h}$$

Download free eBooks at bookboon.com

2. Thermocouple *with* radiation shield being present:

Making a heat balance on the thermocouple bead:

heat received by convection from the gas = heat lost by radiation to shield

$$q_{conv} = q_{rad}$$

i.e. $$h \cdot A_c \cdot (T_f - T_c) = \frac{\sigma \cdot \left(T_c^4 - T_s^4\right)}{\left(\frac{1 - \varepsilon_c}{A_c \cdot \varepsilon_c}\right) + \frac{1}{A_c \cdot F_{cs}} + \left(\frac{1 - \varepsilon_s}{A_s \cdot \varepsilon_s}\right)} \quad \text{....(13.80)}$$

where, $F_{cs} := 1$ ....view factor for thermocouple bead w.r.t. shield

Then, eqn. (13.80) becomes:

$$h \cdot A_c \cdot (T_f - T_c) = \frac{\sigma \cdot A_c \cdot \left(T_c^4 - T_s^4\right)}{\frac{1}{\varepsilon_c} + \left(\frac{A_c}{A_s}\right) \cdot \left(\frac{1}{\varepsilon_s} - 1\right)}$$

But, for a Thermocouple, $A_c / A_s << 1$.

Therefore:

$$h \cdot A_c \cdot (T_f - T_c) = \sigma \cdot \varepsilon_c \cdot A_c \cdot \left(T_c^4 - T_s^4\right)$$

i.e. $$h \cdot (T_f - T_c) = \sigma \cdot \varepsilon_c \cdot \left(T_c^4 - T_s^4\right) \quad \text{.....eqn. (A)}$$

Download free eBooks at bookboon.com

Next, making a heat balance on the shield:

heat received by convection from the gas by *both* surfaces of shield + heat received by radiation from the Thermocouple bead = heat lost by radiation from the shield to the channel walls.

So, we write:

$$2 \cdot A_s \cdot h \cdot (T_f - T_s) + \frac{\sigma \cdot (T_c^4 - T_s^4)}{\left(\frac{1 - \varepsilon_c}{A_c \cdot \varepsilon_c}\right) + \frac{1}{A_c \cdot F_{cs}} + \left(\frac{1 - \varepsilon_s}{A_s \cdot \varepsilon_s}\right)} = \varepsilon_s \cdot A_s \cdot \sigma \cdot (T_s^4 - T_w^4) \qquad \text{....(13.81)}$$

i.e.

$$2 \cdot A_s \cdot h \cdot (T_f - T_s) + \sigma \cdot \varepsilon_c \cdot A_c \cdot (T_c^4 - T_s^4) = \varepsilon_s \cdot A_s \cdot \sigma \cdot (T_s^4 - T_w^4)$$

Dividing by A_s, and since $A_c / A_s << 1$, we get:

$$2 \cdot h \cdot (T_f - T_s) = \varepsilon_s \cdot \sigma \cdot (T_s^4 - T_w^4) \qquad \text{.....eqn. (B)}$$

See the light!
The sooner you realize we are right, the sooner your life will get better!

A bit over the top? Yes we know!

We are just that sure that we can make your media activities more effective.

Get "Bookboon's Free Media Advice"
Email kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

Solving eqns (A) and (B) simultaneously using 'Solve Block' of Mathcad, we get T_c and T_s (if T_f is known) or T_f and T_s (if T_c is known).

Now, when T_f is known, to find T_c:

Now, when T_f is known, to find T_c:

$T_w := 500$ K $\quad \varepsilon_s := 0.1 \quad \varepsilon_c := 0.7 \quad h := 70$ W/m^2.K

$T_f := 1110.5$ K

$T_c := 100$ K $\quad T_s := 100$ K ....trial values

Given

$h \cdot (T_f - T_c) = 5.67 \cdot 10^{-8} \cdot \varepsilon_c \cdot (T_c^4 - T_s^4)$ .....eqn. (A) ....by heat balance on the TC junction...eqn. (A)

$2 \cdot h \cdot (T_f - T_s) = \varepsilon_s \cdot 5.67 \cdot 10^{-8} \cdot (T_s^4 - T_w^4)$ .....eqn. (B) ...by heat balance on the shield...eqn. (B)

$\text{RadnError\_TC\_with\_shield\_TcTs}(T_w, T_f, \varepsilon_c, \varepsilon_s, h) := \text{Find}(T_c, T_s)$

Note that the in the above Solve block, T_c and T_s are written as Functions of T_w, T_f, ε_c, ε_s and h. This helps us to vary any of those variables and find T_c and T_s and to draw graphs.

Result of above Function for the above example is:

$$\text{RadnError\_TC\_with\_shield\_TcTs}(T_w, T_f, \varepsilon_c, \varepsilon_s, h) = \begin{pmatrix} 1.075 \times 10^3 \\ 1.062 \times 10^3 \end{pmatrix}$$

T_c is the first item of the result vector, and T_s is the second item.

We extract these from the output vector as:

$\text{RadnError\_TC\_with\_shield\_TcTs}(T_w, T_f, \varepsilon_c, \varepsilon_s, h)_0 = 1.075 \times 10^3$ K....temp. Tc

$\text{RadnError\_TC\_with\_shield\_TcTs}(T_w, T_f, \varepsilon_c, \varepsilon_s, h)_1 = 1.062 \times 10^3$ K....temp. Ts

==========

Download free eBooks at bookboon.com

Prob.5E.2. Hot gas at 1350 K is flowing in a duct whose walls are maintained at a temperature Tw = 530 K. A thermocouple (TC) placed in the stream to measure temp. If the emissivity of the thermocouple junction is εc = 0.5 and the convective heat transfer coefficient between the flowing air and the thermocouple is h = 115 W/(m2.C), find out the temperature shown by the TC.

(b) Now, if a radiation shield (ε_S = 0.1) is placed between the thermocouple and the walls, what will be new value of T_C read by the thermocouple? And how much is the radiation error?



(a) Thermometer without radiation shield



(b) Thermometer with radiation shield

Mathcad Solution:

Data:

$T_f := 1350$ K $T_W := 530$ K $\varepsilon_s := 0.1$ $\varepsilon_c := 0.5$ $h := 115$ W/m^2.K

Here T_f is given. We have to find out T_c. We do this easily as follows:

We use the Mathcad Function written above for T_f in a 'Solve block'.

Start with a guess value for T_c and apply the Solve Block to fulfill the condition that T_f = 1350 K

Download free eBooks at bookboon.com

$T_c := 500$ K ...trial value

Given

$\text{RadnError\_TC\_no\_shield\_Tf}(T_c, T_w, \varepsilon_c, h) = T_f$

$\text{Find}(T_c) = 1.059 \times 10^3$ **K ... TC temp with no shield... Ans.**

i.e. $T_c := 1.059 \cdot 10^3$ K

$\text{Radiation\_error} := T_f - T_c$

i.e. $\text{Radiation\_error} = 291$ **K....error when no shield is present ... Ans.**

be
your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.

Download free eBooks at bookboon.com

Click on the ad to read more

With the radiation shield being present:

Use the Mathcad Function written above:

Let:

$$AA := RadnError\_TC\_with\_shield\_TcTs(T_w, T_f, \varepsilon_c, \varepsilon_s, h)$$

$$Temp\_TC := AA_0$$

i.e. $Temp\_TC = 1.306 \times 10^3$ **....K..temp reading of TC when shield is present...Ans.**

$$Temp\_shield := AA_1$$

i.e. $Temp\_shield = 1.285 \times 10^3$ **....K..temp of shield...Ans.**

Therefore:

$$Radiation\_error := T_f - Temp\_TC$$

i.e. $Radiation\_error = 44.468$ **K....error when no shield is present ... Ans.**

Note the great reduction in temp error, due to the presence of radiation shield.

In addition:

Plot the variation of 'Radiation error', with the shield being present, and also the Shield temp when the emissivity of shield varies from 0.05 to 0.5:

Express relevant quantities as functions of ε_s:

$$Radiation\_error(\varepsilon_s) := T_f - RadnError\_TC\_with\_shield\_TcTs(T_w, T_f, \varepsilon_c, \varepsilon_s, h)_0$$

$$Temp\_shield(\varepsilon_s) := RadnError\_TC\_with\_shield\_TcTs(T_w, T_f, \varepsilon_c, \varepsilon_s, h)_1$$

$\varepsilon_s := 0.05, 0.1 .. 0.5$ ...define a range variable

Download free eBooks at bookboon.com

ε_s =	Radiation_error(ε_s)	Temp_shield(ε_s)
0.05	24.837	$1.314 \cdot 10^3$
0.1	44.468	$1.285 \cdot 10^3$
0.15	60.564	$1.26 \cdot 10^3$
0.2	74.111	$1.238 \cdot 10^3$
0.25	85.737	$1.219 \cdot 10^3$
0.3	95.869	$1.202 \cdot 10^3$
0.35	104.807	$1.186 \cdot 10^3$
0.4	112.773	$1.172 \cdot 10^3$
0.45	119.933	$1.159 \cdot 10^3$
0.5	126.415	$1.147 \cdot 10^3$

Now, plot the results:





==========

Download free eBooks at bookboon.com

Prob. 5.E.3. Hot air is flowing in a duct whose walls are maintained at a temperature Tw = 450 K. A thermocouple (TC) placed in the stream shows a reading of 650 K. If the emissivity of the thermocouple junction is εc = 0.8 and the convective heat transfer coefficient between the flowing air and the thermocouple is h = 85 W/(m2.C), find out the true temperature of the flowing stream.

(b) Now, if a radiation shield (εs = 0.3) is placed between the thermocouple and the walls, what will be new value of Tc read by the thermocouple? And how much is the temperature error?

(c) Plot the radiation error and shield temp as ε_s varies from 0.05 to 0.5.

EES Solution:

"Data:"

T_w = 450 [K] "…temp of walls"
T_c = 650 [K] "..TC reading"
epsilon_c = 0.8 "…emissivity of TC"
h = 85 [W/m^2-K] "…conv. heat transfer coeff."
epsilon_s = 0.3 "…emissivity of shield"
sigma = 5.67E-08 [W/m^2-K^4] "..Stefan-Boltzmann const."



Download free eBooks at bookboon.com

Click on the ad to read more

"Calculations:"

"When there is no radiation shield:"

T_f = T_c + epsilon_c * sigma * (T_c^4 – T_w^4) / h "…finds true temp of fluid"

"When radiation shield is present:"

"By heat balance on the Thermocouple bead:"

h * (T_f – T_c_with_shield) = sigma * epsilon_c * (T_c_with_shield^4 – T_s^4) "…. eqn, (A)."

"By heat balance on the Shield:"

2 * h * (T_f – T_s) = epsilon_s * sigma * (T_s^4 – T_w^4) "…eqn. (B)."

"Solving eqns. (A) and (B) simultaneously, we get thermocouple reading (T_c) and the Shield temp. (T_s)"

"Radiation error:"

Error_no_shield = T_f – T_c "[deg.C]…. error when there is no shield"

Error_with_shield = T_f – T_c_with_shield "[deg.C]…. error when the shield is present"

Results:

Unit Settings: SI C kPa kJ mass deg

ε_c = 0.8
$Error_{with,shield}$ = 8.785 [C]
T_c = 650 [K]
T_s = 703 [K]

ε_s = 0.3
h = 85 [W/m^2-K]
$T_{c,with,shield}$ = 714.6 [K]
T_w = 450 [K]

$Error_{no,shield}$ = 73.38 [C]
σ = 5.670E-08 [W/m^2-K^4]
T_f = 723.4 [K]

Thus:

True temp of fluid = T_f = 723.4 K …. Ans.

TC reading when the shield is present = 714.6 deg.C … Ans.

Shield temp = T_s = 703 K … Ans.

Radiation error when there is no shield = 73.38 deg.C … Ans.

Radiation error when shield is present = 8.785 deg.C … Ans.

Download free eBooks at bookboon.com

(c) Plot the 'Radiation error' and shield temp as ε_s varies from 0.05 to 0.5:

First, compute the Parametric Table:

Table 1

1..10	1 ε_s	2 $Error_{with,shield}$ [C]	3 T_s [K]
Run 1	0.05	1.682	719.6
Run 2	0.1	3.265	716
Run 3	0.15	4.759	712.5
Run 4	0.2	6.173	709.2
Run 5	0.25	7.512	706.1
Run 6	0.3	8.785	703
Run 7	0.35	9.996	700.1
Run 8	0.4	11.15	697.3
Run 9	0.45	12.25	694.6
Run 10	0.5	13.31	692

Now, plot the results:



Download free eBooks at bookboon.com



==========

**Who is your target group?
And how can we reach them?**

At Bookboon, you can segment the exact right audience for your advertising campaign.

Our eBooks offer in-book advertising spot to reach the right candidate.

Contact us to hear more
kbm@bookboon.com

bp CREDIT SUISSE DAIMLER Unilever Microsoft bookboon.com

Download free eBooks at bookboon.com

Click on the ad to read more

"**Prob. 5.E.4.** Temp of hot exhaust gases flowing in to a room whose walls are maintained at a temperature T_w = 20 C is measured with a thermocouple(TC) whose emissivity is 0.6. The thermocouple shows a reading of 500 C. If the convective heat transfer coefficient between the flowing gases and the thermocouple is h = 200 W/(m2.C), find out the true temperature of the flowing stream, and the radiation error.

(b) Now, if a radiation shield (ε_s = 0.3) is placed between the thermocouple and the walls, what will be new value of Tc read by the thermocouple? And how much is the temperature error?

(c) Plot the radiation error and shield temp as emissivity of shield varies from 0.05 to 0.5."

EES Solution:

"Data:"

T_w = 293 [K] "…temp of walls"
T_c = 773 [K] "..TC reading"
epsilon_c = 0.6 "…emissivity of TC"
h = 200 [W/m^2-K] "…conv. heat transfer coeff."
epsilon_s = 0.3 "…emissivity of shield"

sigma = 5.67E-08 [W/m^2-K^4] "..Stefan-Boltzmann const."

"Calculations:"

"When there is no radiation shield:"

T_f = T_c + epsilon_c * sigma * (T_c^4 – T_w^4) / h "…finds true temp of fluid"

"When radiation shield is present:"

"By heat balance on the Thermocouple bead:"

h * (T_f – T_c_with_shield) = sigma * epsilon_c * (T_c_with_shield^4 – T_s^4) "…. eqn, (A)."

"By heat balance on the Shield:"

2 * h * (T_f – T_s) = epsilon_s * sigma * (T_s^4 – T_w^4) "…eqn. (B)."

"Solving eqns. (A) and (B) simultaneously, we get thermocouple reading (T_c) and the Shield temp. (T_s)"

"Radiation error:"

Error_no_shield = T_f – T_c "[deg.C]…. error when there is no shield"

Download free eBooks at bookboon.com

Error_with_shield = T_f – T_c_with_shield "[deg.C]…. error when the shield is present"

Results:

Unit Settings: SI C kPa kJ mass deg

ε_c = 0.6
$Error_{with,shield}$ = 5.021 [C]
T_c = 773 [K]
T_s = 814.1 [K]

ε_s = 0.3
h = 200 [W/m^2-K]
$T_{c,with,shield}$ = 827.5 [K]
T_w = 293 [K]

$Error_{no,shield}$ = 59.48 [C]
σ = 5.670E-08 [W/m^2-K^4]
T_f = 832.5 [K]

Thus:

True temp of fluid = T_f = 832.5 K …. Ans.

TC reading when the shield is present = 827.5 deg.C … Ans.

Shield temp = T_s = 814.1 K … Ans.

Radiation error when there is no shield = 59.48 deg.C … Ans.

Radiation error when shield is present = 5.021 deg.C … Ans.

(c) Plot the 'Radiation error' and shield temp as emissivity of shield varies from 0.05 to 0.5:

First, compute the Parametric Table:

Table 1 | Table 2

1..10	1 ε_s	2 $Error_{with,shield}$ [C]	3 T_s [K]
Run 1	0.05	0.9246	829.2
Run 2	0.1	1.811	826
Run 3	0.15	2.661	822.9
Run 4	0.2	3.478	819.9
Run 5	0.25	4.264	817
Run 6	0.3	5.021	814.1
Run 7	0.35	5.751	811.3
Run 8	0.4	6.455	808.7
Run 9	0.45	7.135	806
Run 10	0.5	7.792	803.5

Download free eBooks at bookboon.com

Now, plot the results:



Brain power
By 2020, wind could provide one-tenth of our planet's electricity needs. Already today, SKF's innovative know-how is crucial to running a large proportion of the world's wind turbines.
Up to 25 % of the generating costs relate to maintenance. These can be reduced dramatically thanks to our systems for on-line condition monitoring and automatic lubrication. We help make it more economical to create cleaner, cheaper energy out of thin air.
By sharing our experience, expertise, and creativity, industries can boost performance beyond expectations.
Therefore we need the best employees who can meet this challenge!
The Power of Knowledge Engineering
Plug into The Power of Knowledge Engineering.
Visit us at www.skf.com/knowledge
SKF

Download free eBooks at bookboon.com

Click on the ad to read more



==========

Prob. 5.E.5. A thermocouple (TC) whose emissivity is 0.4 is used to measure the temp of a gas flowing in a duct, and it records a temp of 280 C. If the film coeff of heat transfer is h = 150 W/(m^2.C), find out the true temperature of the flowing stream, and the radiation error. Temp of duct wall is 140 C.

(b) Now, what should be the emissivity of junction to reduce the temp error by 30%?

(c) Now, if a shield of emissivity 0.3 is kept surrounding the TC bead, what is the new temp error? And what is the shield temp?

(d) Plot the radiation error and shield temp as emissivity of shield varies from 0.1 to 0.55

Download free eBooks at bookboon.com



(a) Thermometer without radiation shield



(b) Thermometer with radiation shield

EXCEL Solution:

Following are the steps in EXCEL Solution:

1. Set up the worksheet, name the cells:

h | fx | 200

	A	B	C	D	E
4					
5		**Data:**			
6					
7		**Stefan Boltzmann constant**	**sigma**	**5.67E-08**	W/m^2.K^4
8		**Temp of walls**	**T_w**	**413**	K
9		**Thermocouple reading**	**T_c**	**553**	K
10		**emissivity of TC bead**	**eps_c**	**0.4**	
11		**conv. coeff.**	**h**	**200**	W/m^2.K
12					

Download free eBooks at bookboon.com

2. Continue with the calculations:

T_f | =T_c + (eps_c * sigma * (T_c^4 - T_w^4))/h

	A	B	C	D	E
10		emissivity of TC bead	eps_c	0.4	
11		conv. coeff.	h	200	W/m^2.K
12					
13		Calculations:			
14					
15		True temp of gas	T_f	560.306	K...Ans.
16		Therefore:			
17		Radn. error	Error_no_shield	7.306	deg.C
18					

Note the eqn for true temp of gas entered in cell D15, in the Formula bar.

Then, Error (with no radn. Shield) = (T_f – T_c) = 7.306 deg. C …. Ans.

(b) Next, what should be the emissivity of TC to reduce the error by 30%?

i.e. the New_error = 7.306 × 0.7 = 5.114 deg.C.

Download free eBooks at bookboon.com

Click on the ad to read more

3. Next pert of calculations is shown below:

	A	B	C	D	E	F
16		Therefore:				
17		**Radn. error**	**Error_no_shield**	**7.306**	**deg.C**	
18						
19		**If radn_error is reduced by 30 % :**				
20		**Then, new error = 5.114 C.**				
21						
22		**Find eps_c such that:**				
23		Error_no_shield = New_error				
24		**Apply Goal Seek to make value in cell D17 equal to 5.114 by changing cell D10 (i.e. eps_c):**				

Now, the condition to be satisfied is: **Error_no_shield = New_error**

We have to find eps_c such that this condition is satisfied.

So, apply Goal seek to make value in cell D17 equal to 5.114 by changing cell D10 (i.e. eps_c):

Go to Data-WhatIf Analysis – Goal Seek:



Click on Goal Seek; we get the following window, fill it up as shown:



Download free eBooks at bookboon.com

Press OK. We get:



Goal Seek has found a solution. Again, press OK, and see the value of new eps_c in cell D10:

	A	B	C	D	E
7		Stefan Boltzmann constant	sigma	5.67E-08	W/m^2.K^4
8		Temp of walls	T_w	413	K
9		Thermocouple reading	T_c	553	K
10		emissivity of TC bead	eps_c	0.279995339	
11		conv. coeff.	h	200	W/m^2.K
12					
13		Calculations:			
14					
15		True temp of gas	T_f	558.114	K...Ans.
16		Therefore:			
17		Radn. error	Error_no_shield	5.114	deg.C

Ths, eps_c required to reduce the radiation error by 30% is: 0.28 …. Ans.

Download free eBooks at bookboon.com

(c) Now, if a shield of emissivity 0.3 is kept surrounding the TC bead, what is the new temp error? And what is the shield temp?

D40 | =D38-D39

	A	B	C	D	E	F
25						
26		**When a Radiation shield is present:**				
27						
28		**Emissivity of Shield**	**eps_s**	**0.3**		
29						
30		**Let: Temp of Shield**	**T_s**	**450**	K	
31						
32		**Find temp of Shield from:**				
33						
34						
35		$2 \cdot h \cdot (T_f - T_s) = \varepsilon_s \cdot 5.67 \cdot 10^{-8} \cdot (T_s^4 - T_w^4)$ .....eqn. (B)		...by heat balance on the shield...eqn. (B)		
36						
37		In the above eqn:				
38			LHS=	44122.33436		
39			RHS=	202.6310507		
40			Diff.	43919.70331		
41						
42		**Apply Goal Seek to make value in cell D40 equal to zero by changing cell D30 (i.e. eps_s):**				

Note in the above screen shot that we have started with a guess value of 450 for T_s in cell D30.

Applying Goal Seek to make cell D40 equal to zero by changing cell D30 (i.e. T_s), we get the value of temp of Shield T_s:



Press OK. We get:



Download free eBooks at bookboon.com

Again, pres OK, and see the value of T_s in cell D30:

	A	B	C	D	E	F
28		**Emissivity of Shield**	**eps_s**	**0.3**		
29						
30		**Let: Temp of Shield**	**T_s**	**557.4369692**	K	
31						
32		**Find temp of Shield from:**				
33						
34						
35		$2 \cdot h \cdot (T_f - T_s) = \varepsilon_s \cdot 5.67 \cdot 10^{-8} \cdot (T_s^4 - T_w^4)$ .....eqn. (B)		...by heat balance on the shield...eqn. (B)		
36						
37		In the above eqn:				
38			LHS=	1147.546687		
39			RHS=	1147.546687		
40			Diff.	-2.59206E-11		
41						
42		**Apply Goal Seek to make value in cell D40 equal to zero by changing cell D30 (i.e.T_s):**				

i.e. Shield temp = T_s = 557.437 K … Ans.

Download free eBooks at bookboon.com

Click on the ad to read more

Now, continue to calculate the new reading of TC:

D55 =D53-D54

	A	B	C	D	E	F	G	H
43								
44		**Find TC reading when Shield is present, from:**						
45								
46								
47		$h\cdot(T_f - T_c) = 5.67\cdot10^{-8}\cdot e_c\cdot(T_c^4 - T_s^4)$ .....eqn. (A)		....by heat balance on the TC junction...eqn. (A)				
48								
49								
50		**Let: TC reading with shield:**						
51			**T_C_with_shield=**	**500** K				
52		In the above eqn:						
53			LHS=	12061.16718				
54			RHS=	-772.4092655				
55			Diff.	12833.57645				
56								
57		**Apply Goal Seek to make value in cell D55 equal to zero by changing cell D51 (i.e. T_c_with_shield):**						

Note in the above screen shot that we have started with a guess value of 500 for T_c_with_shield in cell D51.

Applying Goal Seek to make cell D55 equal to zero by changing cell D51 (i.e. T_c_with_shield), we get the value of temp of Shield T_c_with_shield:



Press OK We get:



Download free eBooks at bookboon.com

Again, press OK and see the value of T_c_with_shield in cell D51:

D59 =T_f - T_C_with_shield

	A	B	C	D	E	F	G
43							
44		**Find TC reading when Shield is present, from:**					
45							
46							
47		$h\cdot(T_f - T_c) = 5.67\cdot10^{-8}\cdot e_c\cdot(T_c^4 - T_s^4)$ .....eqn. (A)		....by heat balance on the TC junction...eqn. (A)			
48							
49							
50		**Let: TC reading with shield:**					
51			**T_C_with_shield=**	**560.0955** K			
52		In the above eqn:					
53			LHS=	42.07563757			
54			RHS=	42.07563746			
55			Diff.	1.16613E-07			
56							
57		**Apply Goal Seek to make value in cell D55 equal to zero by changing cell D51 (i.e. T_c_with_shield):**					
58							
59		**And, new temp error is:**	**Error_with_shield**	**0.21038** C.....Ans.			

Thus:

TC reading when the shield is present = 560.096 K …. Ans.

Temp error when shield is present = 0.2104 C … Ans.

(c) Plot the 'Radiation error' and shield temp as emissivity of shield varies from 0.1 to 0.55:

Following are the steps:

1. First, prepare a Table as shown below:

	A	B	C	D
64				
65		**eps_s**	**T_s (K)**	**Error_with_shield (deg.C)**
66		**0.1**		
67		**0.15**		
68		**0.2**		
69		**0.25**		
70		**0.3**		
71		**0.35**		
72		**0.4**		
73		**0.45**		
74		**0.5**		
75		**0.55**		

Download free eBooks at bookboon.com

2. Now, we need a VBA program to read eps_s values one by one and apply Goal Seek **twice** to get T_s and T_c_with_shield, and thereby get Error_with_shield, and then copy the calculated values in the main worksheet to their respective places in the Table. Also, this program should be run from a command button.

To do this, first go to: Developer- Insert-ActiveX Controls:





Download free eBooks at bookboon.com

Click on the ad to read more

Click on the command button i.e. first top left button under ActiveX Controls. Then click at the required place in the worksheet and draw the button to a suitable size:



Then, click on Developer-View Code, and complete the code as shown below:

```
Private Sub CommandButton1_Click()

Dim i As Integer

For i = 0 To 9 ' start of For....Next loop

Range("D28") = Cells(66 + i, 2) 'copy the first value of eps_s from the Table to cell D28

' Goal Seek to find Temp of Shield, T_s, in cell D30:
'
'
    Range("D40").Select
    Range("D40").GoalSeek Goal:=0, ChangingCell:=Range("D30")
    ActiveWindow.SmallScroll Down:=18

 Cells(66 + i, 3) = Range("D30") 'copy the value of T_s from cell D30 to its place in Table

' Goal Seek to find temp of Thermocouple when shield is present, T_C_with_shield, in cell D51:
'
'
    Range("D55").Select
    Range("D55").GoalSeek Goal:=0, ChangingCell:=Range("D51")
    ActiveWindow.SmallScroll Down:=18

Cells(66 + i, 4) = Range("D59") 'copy the value of Error_with_shield from cell D59
                                'to its place in Table

Next i  'Go to next value of i

End Sub
```

Read the comments in the above program to know what each step does.

3. Now, click on the Command Button. Immediately, calculations are completed and the Table is filled up:

eps_s	T_s (K)	Error_with_shield (deg.C)
0.1	559.331	0.072
0.15	558.850	0.107
0.2	558.375	0.142
0.25	557.904	0.176
0.3	557.437	0.210
0.35	556.975	0.244
0.4	556.517	0.277
0.45	556.063	0.310
0.5	555.613	0.342
0.55	555.168	0.374

Download free eBooks at bookboon.com

4. Now, plot the results in EXCEL:





==========

Download free eBooks at bookboon.com

References

1. M. Thirumaleshwar, *Fundamentals of Heat & Mass Transfer*, Pearson Education, India, 2006
2. Yunus A Cengel, *Heat and Mass Transfer*, 3rd Ed., McGraw Hill Co.
3. F.P. Incropera and D.P.DeWitt, *Fundamentals of Heat and Mass Transfer*, 5th Ed., John Wiley & Sons
4. Domkundwar et al, *A Course in Heat & Mass Transfer*, Dhanpat Rai & Co, 5th Ed, 1999
5. Frank Kreith and Mark S Bohn, *Principles of Heat Transfer*, PWS Publ. Co. (Intl. Thomson Publ.), 5th Ed., 1997

be > your degree
© 2013 Accenture. All rights reserved.
Bring your talent and passion to a global organization at the forefront of business, technology and innovation. Discover how great you can be.
Visit accenture.com/bookboon
Be greater than.
consulting | technology | outsourcing
accenture
High performance. Delivered.
Click on the ad to read more